

0 Tools

Student Group

First Name	Surname	Matrikel Nr.

Table of Contents

0. Tools

Why two simulation tools?

0.1 First steps in TINA TI

Manual

Exercises

Goals

Tasks

Goals

Tasks

Goals

Tasks

0.2 Online Circuit Simulator

Tasks

0.3 Further Simulation Tools

0.4 Literature recommendations

2

2

2

2

2

3

3

3

4

4

5

6

6

7

7

0. Tools

In the following you will learn about two simulation tools. With these tools you can reconstruct circuits and display their voltages and currents. This is particularly important for understanding circuits with operational amplifiers and transistors.

Why two simulation tools?

- For learning and understanding, it is important on the one hand that you get a feeling for how currents and voltages are set in circuits.
- On the other hand, you should practice using professional tools that enable high-quality simulations.

The former tools should allow simple visualization. The latter tools are usually a bit more difficult to handle, but allow more complex circuits and more detailed measurements. For high-quality simulation, you will use the free program TINA TI in the following. Illustration of concepts is made possible by Falstad's online simulation.

0.1 First steps in TINA TI

TINA is a SPICE (Simulation Program with Integrated Circuit Emphasis) program from Texas Instruments. With this program you can simulate electronic circuits and display the time sequences. This is very useful for learning and testing, but can also simulate more realistic setups.

Introduction to TINA TI 0 - Explanation of TINA, download and installation

The free version of the program is already very comprehensive. You can find it as follows (recommended is link 1!):

1. [TINA TI Download](#) on this wiki (login via university account)
2. in the [ILIAS course](#)
3. Download (a bit cumbersome) via the [TI page](#)



Manual

An english manual can be found [here in the wiki](#).
A German manual is only available for the [full version](#).



Exercises

Please install TINA TI.
Here some tips:



- For "User Name" and "Company Name" you can enter pseudonyms (Hinz&Kunz, HHN).
- Select European (DIN) at "Select schematic symbol set you want to use".
- All file paths should fit as recommended.

Introduction to TINA TI 1 - Structure of TINA TI, first circuitry

Goals

After this lesson you should:

1. be familiar with the various component bars in TINA TI,
2. be able to insert and rotate components and their descriptions,
3. be able to edit component values,
4. be able to draw connections.



Tasks




1. Rebuild the circuit from the video in TINA TI.
2. Change the following additional values:
 1. Output value of the voltage source: \$10 V\$
 2. Size of resistor R1: \$20k\$
 3. Size of resistor R2: \$30k\$

Introduction to TINA TI 2 - Output of values and debugging

Goals

After this lesson you should:

- be able to perform the "Electrical Rule Check" and use it for debugging,
- measure output values such as voltages and currents,
- be able to use multimeters in TINA TI to measure voltages and currents,
- be able to insert current measuring points correctly,



Tasks

1. Rebuild the circuit from the video in TINA TI.
2. Instead of the Current Arrow, use the Ammeter and instead of the Voltmeter, use the Voltage Pin.
Are there any differences when you use them?
3. Imagine you want to build a small circuit with 3 light emitting diodes and wonder how much the voltage of the two 1.5V batteries will drop.




Fig. 1: parallel circuit 1




Fig. 2: parallel circuit 2



1. Build the simplified parallel circuit 1 (see picture).

The internal resistance of the battery should be 500mOhm (property "Internal Resistance").

1. What voltage/current is measured?
 2. How large is the current through one strand?
2. **Optional:** To do this, reconstruct the parallel circuit 2 (see picture). The internal resistance of the battery should be maintained.
 1. What voltage / current is measured?
 2. What is the current through one strand?

Solution:

Introduction to TINA TI 3 - Even more errors and many diagrams

Goals

After this lesson you should:

1. be able to correct the most common errors in the simulation yourself,
2. be able to display time sequences of signals,
3. work with the cursor in diagrams,

- separate curves and insert a legend,
4. be able to create and evaluate curves over temperature and other variables,
 5. be able to create a structured simulation with title.

You can find the template file under
Tipps für TINA TI



Video



Tasks

- You can find exercises for this video in the following chapter

Tips for TINA TI

- Avoid nodes directly on the output of a component.
- The following keyboard shortcuts make Tina easier to use:
 - <Strg>+<R>: Right-rotate a selected component.
 - <Strg>+<L>: Left-rotate a selected component.
 - <Strg>+<Space>: Switch to connection mode (wire).
 - <Strg>+<C>, <Strg>+<V>: Copy, Paste.
 - <Strg>+<Z>, <Strg>+<Y>: Undo, Redo.
- Please use the template file

Vorlage_EST.TSC

when starting a simulation.

- [even more tips for tina TI](#)



General tips

- Use rule checks available with simulation tools, such as the “Electrical Rule Check” (ERC)..
Rule checks show errors and warnings. If there are errors, the simulation will not run. If there are warnings, it will run, but there are unclear areas in the circuitry.
- Avoid unclear identifiers and text. I.e. try to write text so that it is direct legible (not overlapping, similar alignment).
- Always specify a reference potential (ground).

0.2 Online Circuit Simulator

Introduction to Online Circuit Simulator - Explanation, Example

In addition to TINA TI,
another simulation tool
is used in this course:
The [Online Circuit
Simulator](#).

This tool can help to
better understand the
currents and voltages in
different circuits. The
program displays the
current flow and the
applied voltage in
animated form. Under
"Circuits" " "Operational
amplifiers (OPVs)" you
will find various circuits
that are useful for this
course.



There is a German [quick
guide to Online Circuit
Simulator](#) available from
the Landesberufsschule
Salzburg. The [Source
Code](#) of the simulator
can be found on GitHub.

Tasks

Familiarize yourself with the Online Circuit Simulator from Falstad



- first with the embedded example on the right
 - If the circuit is too small, click on Edit » Center Circuit
If only part of the available space is taken up by the circuit after this, refreshing the browser window (<Ctrl>+R) or editing directly on the [Online Circuit Simulator Homepage](#) will help.
 - Most circuits on the wiki are initially stopped. The simulation can be started by pressing RUN/Stop.
 - Check the change in the current flow results when




different switches are activated.

- Change the resistor values by double-clicking on the respective resistor.
- further examples of equivalent voltage source (Thévenin's theorem) and equivalent current source (Norton's theorem)
 - Search in Circuits » Basics » Thévenin Theorem
 - At the bottom left of the window, you will see two running graphs of the currents and voltages of the two circuits. Click with the right mouse button on one of the diagrams and select Combine. The curves should now be directly on top of each other
 - Move the mouse over one of the two voltage sources. The respective voltage/current curve is highlighted. Are both curves on top of each other?
 - Do the same for the equivalent current source (Norton theorem).

0.3 Further Simulation Tools

In addition to the tools explained so far, there are other simulation tools - which we do not use in the courses. Some of them are briefly summarized here with their limitations.

Name	Focus	Limits	Commercial Product
Tina TI	Simulation of analog circuits (e.g. amplifier circuits)	function limited in the commercial product also the simulation of mixed digital-analog circuits is possible	Designsoft Tina
MPLab Mindi	Simulation of transient transitions (z.B. DCDC-converter)	Number of nodes < 150 (approx.)	SIMETRIX / SIMPLIS
LTSpice	broadly based Simulation	flat learning curve (unusual key mapping)	-

Title , Author , Short description Operational amplifier , J. Federau , Textbook with illustrative approaches. Accessible via university network or VPN. OP Amp Applications Handbook ,, very nice and detailed textbook of the manufacturer Analog Devices, "Freeware", online available. Handbook of Operational Amplifiers Application ,, A similar nice handbook is available from the competitor Texas Instruments Semiconductor Circuit Technology , U. Tietze, Chr. Schenk, E. Gamm , very detailed reference book. Accessible via university network or VPN. Additionally there is a collection of exercises

0.4 Literature recommendations

For self-study I recommend the following literature.

Title	Author	Short description
Operationsverstärker	J. Federau	German textbook with illustrative approaches. Accessible via university network or VPN .
OP Amp Applications Handbook		very nice and detailed textbook of the manufacturer Analog Devices, "Freeware", online available .
Handbook of Operational Amplifiers Application		A similar nice handbook is available from the competitor Texas Instruments
Halbleiter-Schaltungstechnik	U. Tietze, Chr. Schenk, E. Gamm	very detailed reference book. Accessible via university network or VPN . Additionally there is a collection of exercises

From:

<https://wiki.mexle.te.hs-heilbronn.de/> - **MEXLE Wiki**

Permanent link:

https://wiki.mexle.te.hs-heilbronn.de/circuit_design/0_tools?rev=1632352264

Last update: **2021/09/23 01:11**

