

rechnung_betragundphase_umkehrintegrator

Student Group

First Name	Surname	Matrikel Nr.

Table of Contents

\$\;\$ \$\;\$	$U_A = -\{1 \over R \cdot C\} \cdot \int_{t_0}^{t_1} U_E(t) \, dt + U_{A0}$
\$\;\$ \$\;\$ insert sine function: \$ \$\color{blue}\{U_E(t)\}=\$ \$\hat{U}_E \cdot \sin(\omega \cdot t)\$	
	$U_A = -\{1 \over R \cdot C\} \cdot \int_{t_0}^{t_1} \hat{U}_E \cdot \sin(\omega \cdot t) \, dt + U_{A0}$
\$\;\$ \$\;\$ insert root function with limits \$ \$\color{blue}\{\int_{x_0}^{x_1} \sin(a \cdot x) \, dx\} = [-1 \over a] \cdot \cos(a \cdot x)\$ \$\;\$ \$\;\$	
	$U_A = -\{1 \over R \cdot C\} \cdot [-1 \over \omega] \cdot \cos(\omega \cdot t) \Big _{t_0}^{t_1} + U_{A0}$
\$\;\$ \$\;\$ put constant before integral	
	$U_A = \{1 \over R \cdot C\} \cdot \hat{U}_E \cdot \cos(\omega \cdot t) \Big _{t_0}^{t_1} + U_{A0}$
\$\;\$ \$\;\$ insert limits: \$t_0=0\$, \$t_1=t\$	
	$U_A = \{ \hat{U}_E \over \omega \cdot R \cdot C \} \cdot (\cos(\omega \cdot t) - \cos(0)) + U_{A0}$
\$\;\$ \$\;\$	$\cos(0) = 1$
	$U_A = \{ \hat{U}_E \over \omega \cdot R \cdot C \} \cdot (\cos(\omega \cdot t) - 1) + U_{A0}$
\$\;\$ \$\;\$ multiply	
	$U_A = \{ \hat{U}_E \over \omega \cdot R \cdot C \} \cdot \cos(\omega \cdot t) \cdot \{ -\{ \hat{U}_E \over \omega \cdot R \cdot C \} + U_{A0} \}$
\$\;\$ \$\;\$ consider the non-cosine terms	
	$U_A = \{ \hat{U}_E \over \omega \cdot R \cdot C \} \cdot \cos(\omega \cdot t) \cdot \{ -\{ \hat{U}_E \over \omega \cdot R \cdot C \} + U_{A0} \}$
\$\;\$ \$\;\$ This part is independent in time. Since we assume purely sinusoidal quantities, the initial voltage of the capacitor must be: \$\;\$ \$\;\$	
	$U_A = \{ \hat{U}_E \over \omega \cdot R \cdot C \} \cdot \cos(\omega \cdot t)$
\$\;\$ \$\;\$	

From:

<https://wiki.mexle.te.hs-heilbronn.de/> - MEXLE Wiki

Permanent link:

https://wiki.mexle.te.hs-heilbronn.de/circuit_design/rechnung_betragundphase_umkehrintegrator?rev=1641770218

Last update: 2022/01/10 00:16

