

rechnung_betragundphase_umkehrintegrator

Student Group

First Name	Surname	Matrikel Nr.

Table of Contents

\$\;\$ \$\;\$ \$\;\$	$U_{\rm O} = -\{1 \over R \cdot C\} \cdot \int_{t_0}^{t_1} \color{blue}{U_{\rm I}(t)} \cdot dt + U_{\rm O0}$
\$\;\$ \$\;\$ \$\;\$	insert sine function: $\color{blue}{U_{\rm I}(t)} = \hat{U}_{\rm I} \cdot \sin(\omega \cdot t)$
\$\;\$ \$\;\$ \$\;\$	$U_{\rm O} = -\{1 \over R \cdot C\} \cdot \int_{t_0}^{t_1} \hat{U}_{\rm I} \cdot \sin(\omega \cdot t) \cdot dt + U_{\rm O0}$
\$\;\$ \$\;\$ \$\;\$	insert root function with limits $\color{blue}{\int_{x_0}^{x_1} \sin(a \cdot x) \cdot dx} = [-1 \over a] \cdot \cos(a \cdot x) \Big _{x_0}^{x_1}$
\$\;\$ \$\;\$ \$\;\$	$U_{\rm O} = -\{1 \over R \cdot C\} \cdot [-\color{blue}{\hat{U}_{\rm I} \over \omega} \cdot \cos(\omega \cdot t)]_{t_0}^{t_1} + U_{\rm O0}$
\$\;\$ \$\;\$ \$\;\$	put constant before integral $U_{\rm O} = \{1 \over R \cdot C\} \cdot \{\color{blue}{\hat{U}_{\rm I} \over \omega} \cdot \cos(\omega \cdot t) - \color{blue}{\cos(0)}\} \cdot \int_{t_0}^{t_1} dt + U_{\rm O0}$
\$\;\$ \$\;\$ \$\;\$	insert limits: \$t_0=0\$, \$t_1=t\$ $U_{\rm O} = \{ \color{blue}{\hat{U}_{\rm I} \over \omega} \cdot \cos(\omega \cdot t) - \color{blue}{\cos(0)} \} \cdot \int_0^t dt + U_{\rm O0}$
\$\;\$ \$\;\$ \$\;\$	$U_{\rm O} = \{ \color{blue}{\hat{U}_{\rm I} \over \omega} \cdot \cos(\omega \cdot t) - \color{blue}{\cos(0)} \} \cdot t + U_{\rm O0}$
\$\;\$ \$\;\$ \$\;\$	multiply $U_{\rm O} = \{ \color{blue}{\hat{U}_{\rm I} \over \omega} \cdot \cos(\omega \cdot t) - \color{blue}{\cos(0)} \} \cdot t + U_{\rm O0}$
\$\;\$ \$\;\$ \$\;\$	consider the non-cosine terms: The blue part is independent in time. We assume purely sinusoidal quantities!
\$\;\$ \$\;\$ \$\;\$	$U_{\rm O} = \{ \color{blue}{\hat{U}_{\rm I} \over \omega} \cdot \cos(\omega \cdot t) - \color{blue}{\cos(0)} \} \cdot t + U_{\rm O0}$
\$\;\$ \$\;\$ \$\;\$	\$\rightarrow\$ initial voltage of the capacitor: $U_{\rm C0} = U_{\rm O0} = \color{blue}{\hat{U}_{\rm I} \over \omega} \cdot \cos(0)$
\$\;\$ \$\;\$ \$\;\$	$U_{\rm O} = \{ \color{blue}{\hat{U}_{\rm I} \over \omega} \cdot \cos(\omega \cdot t) - \color{blue}{\cos(0)} \} \cdot t + U_{\rm O0}$

From:
<https://wiki.mexle.te.hs-heilbronn.de/> - **MEXLE Wiki**

Permanent link:
https://wiki.mexle.te.hs-heilbronn.de/circuit_design/rechnung_betragundphase_umkehrintegrator

Last update: **2023/03/28 14:52**

