

rechnung_signalzeitverlauf_umkehrintegrator

Student Group

First Name	Surname	Matrikel Nr.

Table of Contents

\$I.\quad\$ At the point \$t_1\$

$U_{\rm O}(t_1) = -\frac{1}{\tau} \cdot \int_{t_0}^{t_1} U_{\rm I} dt + U_{\rm O}(t_0)$	
$U_{\rm O}(t_1) = -\frac{1}{5 \text{ ms}} \cdot 1 \text{ V} \cdot 10 \text{ ms} + 0 \text{ V}$	
$U_{\rm O}(t_1) = -\frac{1}{5 \text{ ms}} \cdot 1 \text{ V} \cdot 10 \text{ ms} = -2 \text{ V}$	

\$I.\quad\$ At the point \$t_2\$

$U_{\rm O}(t_1) = -\frac{1}{\tau} \cdot \int_{t_0}^{t_1} U_{\rm I} dt + U_{\rm O}(t_0)$	
$U_{\rm O}(t_1) = -\frac{1}{5 \text{ ms}} \cdot (-1 \text{ V}) \cdot 10 \text{ ms} + 2 \text{ V} = 0 \text{ V}$	

\$I.\quad\$ At the point \$t_3\$

$U_{\rm O}(t_1) = -\frac{1}{\tau} \cdot \int_{t_0}^{t_1} U_{\rm I} dt + U_{\rm O}(t_0)$	
$U_{\rm O}(t_1) = -\frac{1}{5 \text{ ms}} \cdot (-2 \text{ V}) \cdot 10 \text{ ms} + 0 \text{ V} = -2 \text{ V}$	

From:
<https://wiki.mexle.te.hs-heilbronn.de/> - **MEXLE Wiki**

Permanent link:
https://wiki.mexle.te.hs-heilbronn.de/circuit_design/rechnung_signalzeitverlauf_umkehrintegrator

Last update: **2023/03/28 14:49**

