

# task\_ddjurcpk494go2q1\_with\_calculation

## Student Group

| First Name | Surname | Matrikel Nr. |
|------------|---------|--------------|
|            |         |              |
|            |         |              |
|            |         |              |

## Table of Contents

Exercise E1 Fields of an coax Cable (written test, approx. 12 % of a 120-minute written test, SS2024) ..... 2

electric field, magnetic field, exam ee2 SS2024

### Exercise E1 Fields of an coax Cable

**(written test, approx. 12 % of a 120-minute written test, SS2024)**

[illegible]

- Inner conductor:  $+3.3 \text{ mA}$ ,  $+10 \text{ nC}$  (current into the plane of the diagram)
- Outer conductor:  $-3.3 \text{ mA}$ ,  $-10 \text{ nC}$  (current out of the plane of diagram)
  - for  $(0.1 \text{ mm} \leq r \leq 0.55 \text{ mm})$ :  $E = 328 \text{ V/m}$
  - for  $(0.55 \text{ mm} \leq r \leq 1 \text{ mm})$ :  $E = 985 \text{ V/m}$

The magnitude of the electric displacement field  $D$  can be calculated by:  $\int D \cdot dA = Q$ .

Here, for any position  $r$  inside the rectangular conducting area is the surface of a cylindrical shape (here for simplicity without the round endings).

Force on the surface of the cylinder is  $\vec{F} = -\int \vec{n} \cdot \vec{\sigma} dA$ . This leads to  $\vec{F} = -\int \vec{n} \cdot \vec{\sigma} dA$ . The current is calculated within a circle with the radius  $R$ .

This is proportional to the area within this radius. Therefore, the formula  $H = \frac{1}{2} \pi r^2$  gives  $H(x) = \frac{1}{2} \pi (x \text{ mm})^2$ . So, we get  $H(0.1 \text{ mm}) = 0.0157 \text{ mm}^2$ , and  $H(0.5 \text{ mm}) = 0.39 \text{ mm}^2$ . This leads to a formula proportional to  $x^2$ .

- For  $s_x$  within the outer conductor one also gets a linear proportionality with a

Hint: For the direction, one has to consider the sign of the enclosed charge. By this, we see that the  $\vec{D}$ -field is positive.

But here, again only the magnitude was questioned!

.. What is the magnitude of the magnetic field strength  $H$  at  $(0.1 \text{ ~mm} | 0)$  and  $(0.55 \text{ ~mm} | 0)$ ?

The magnitude of the magnetic field strength  $H$  can be calculated by:  $H = \frac{I}{2 \pi \cdot r}$

So, we get for  $H_{\text{i}}$  at  $r_{\text{i}} = 0.1 \text{ mm}$ , and  $H_{\text{o}}$  at  $r_{\text{o}} = 0.55 \text{ mm}$ :

$$H_{\text{i}} = \frac{I}{2 \pi \cdot r_{\text{i}}} = \frac{+3.3 \text{ A}}{2 \pi \cdot 0.1 \cdot 10^{-3} \text{ m}} \quad H_{\text{o}} = \frac{I}{2 \pi \cdot r_{\text{o}}} = \frac{+3.3 \text{ A}}{2 \pi \cdot 0.55 \cdot 10^{-3} \text{ m}}$$

Hint: For the direction, one has to consider the right-hand rule. By this, we see that the  $H$ -field on the right side points downwards.

Therefore, the sign of the  $H$ -field is negative.

But here, only the magnitude was questioned!

From:

<https://wiki.mexle.te.hs-heilbronn.de/> - **MEXLE Wiki**

Permanent link:

[https://wiki.mexle.te.hs-heilbronn.de/ee2/task\\_ddjurcpk494go2q1\\_with\\_calculation](https://wiki.mexle.te.hs-heilbronn.de/ee2/task_ddjurcpk494go2q1_with_calculation)

Last update: **2024/07/15 21:37**

