

task_abh4vhlgczdbni37_with_calculation

Student Group

First Name	Surname	Matrikel Nr.

Table of Contents

Exercise E18 Signal Analysis (written test, approx. 6 % of a 120-minute written test, SS2021)

..... 2

signal analysis, RMS, exam ee2 SS2021

Exercise E18 Signal Analysis**(written test, approx. 6 % of a 120-minute written test, SS2021)**

A) Determine the effective value of the signal $i(t)$ and the effective value of the voltage $u(t)$ (independent quantities are available in the consumer arrow system). (hard)

- $u(t) = 50 \sqrt{2} \cos(6000 t + 4) \text{ V}$

- $i(t) = 30 \sqrt{2} \sin(6000 t + 5) \text{ A}$

Result

a) Determine the amplitude values $\hat{U}$, $\hat{I}$ and the RMS values U , I

- $f = 955 \text{ Hz}$

- $\hat{U} = 50 \sqrt{2} \text{ V}$

The frequency can be derived by the term in the sine function: $\omega = 6000 \text{ rad/s}$

- $\hat{I} = 30 \sqrt{2} \text{ A}$

$$f = \frac{\omega}{2\pi} = \frac{6000}{2\pi} \approx 954.93 \text{ Hz}$$

RMS values:

For the phase φ , we have to subtract φ_i from φ_u .

But to get these values, both the $u(t)$ and $i(t)$ need to have the same sinusoidal function! Therefore:

- For the RMS values of sinusoidal functions the amplitudes have to be multiplied with $\frac{1}{\sqrt{2}}$
- $U = 50 \text{ V}$
- $I = 30 \text{ A}$

$$\varphi = \varphi_u - \varphi_i = 4 - 5 = -1 \text{ rad} = -1 \cdot \frac{360^\circ}{2\pi} \approx -57.2958^\circ$$

$$\varphi = -1 \text{ rad} \cdot \frac{360^\circ}{2\pi} \approx -57.2958^\circ$$

From:
<https://wiki.mexle.te.hs-heilbronn.de/> - MEXLE Wiki

Permanent link:
https://wiki.mexle.te.hs-heilbronn.de/electrical_engineering_and_electronics/task_abh4vhlgczbni37_with_calculation

Last update: 2024/07/04 02:36

