

# task\_rj0r6j4apumukrj6\_with\_calculation

## Student Group

| First Name | Surname | Matrikel Nr. |
|------------|---------|--------------|
|            |         |              |
|            |         |              |
|            |         |              |

## Table of Contents

Exercise E1 Resistance of a Wire by Resistivity (written test, approx. 6 % of a 60-minute  
written test, WS2022) ..... 2

resistivity, power, exam ee1 WS2022

### Exercise E1 Resistance of a Wire by Resistivity (written test, approx. 6 % of a 60-minute written test, WS2022)

2. The heating element made of solid nichrome wire with a temperature coefficient of  $1.80 \times 10^{-5} \text{ } ^\circ\text{C}^{-1}$  is electrically connected to a power supply. A power dissipation (= heat flow) of  $P = 40 \text{ W}$  is necessary. Calculate the current  $I$  needed to operate it. for heating elements.  
The Nichrome wire has a resistivity of  $1.10 \cdot 10^{-6} \text{ } \Omega \text{ m}$ .  
The heating element is  $3 \text{ m}$  long and has a diameter of  $3.57 \text{ mm}$ .  
Solution:  $R = 10^{-3} \text{ } \Omega$   
∴ Calculate the resistance  $R$  of the heating element.

Solution

$$\begin{aligned} P &= U \cdot I = R \cdot I^2 \quad \rightarrow \quad I = \\ &= \sqrt{\frac{P}{R}} = \sqrt{\frac{40 \text{ W}}{0.33 \text{ } \Omega}} \end{aligned}$$

$$\begin{aligned} R &= \rho \cdot \frac{l}{A} \quad \text{with } A = r^2 \cdot \pi = \\ &= \frac{1}{4} d^2 \cdot \pi \quad R = \rho \cdot \frac{4 \cdot l}{d^2 \cdot \pi} \quad \text{and } R = \\ &= 1.10 \cdot 10^{-6} \text{ } \Omega \text{ m} \cdot \frac{4 \cdot 3 \text{ m}}{(3.57 \cdot 10^{-3} \text{ m})^2 \cdot \pi} \end{aligned}$$

From:  
<https://wiki.mexle.te.hs-heilbronn.de/> - MEXLE Wiki

Permanent link:  
[https://wiki.mexle.te.hs-heilbronn.de/electrical\\_engineering\\_and\\_electronics/task\\_rj0r6j4apumukrj6\\_with\\_calculation](https://wiki.mexle.te.hs-heilbronn.de/electrical_engineering_and_electronics/task_rj0r6j4apumukrj6_with_calculation)

Last update: 2023/10/12 03:54

