

Exam Summer Semester 2023

Student Group

First Name	Surname	Matrikel Nr.

Table of Contents

Exam Summer Semester 2023	3
Additional permitted Aids	3
Hits	3
Only EEE1-relevant Part	3
Exercise E1 Resistivity and temperature dependent Resistance (written test, approx. 7 % of a 60-minute written test, SS2023)	3
Exercise E2 Pure Resistor Network Simplification (written test, approx. 12 % of a 60-minute written test, SS2023)	4
Exercise E3 Pure Resistor Network Simplification I (written test, approx. 14 % of a 60-minute written test, SS2023)	6
Exercise E4 Equivalent Linear Source (written test, approx. 10 % of a 60-minute written test, SS2023)	9
Full Exam	12
Exercise E1 Resistivity and temperature dependent Resistance (written test, approx. 7 % of a 60-minute written test, SS2023)	12
Exercise E5 Analyzing a Scope Plot (written test, approx. 12 % of a 60-minute written test, SS2023)	13
Exercise E6 Complex voltage dividers (written test, approx. 16 % of a 60-minute written test, SS2023)	14
Exercise E2 Pure Resistor Network Simplification (written test, approx. 12 % of a 60-minute written test, SS2023)	15
Exercise E3 Pure Resistor Network Simplification I (written test, approx. 14 % of a 60-minute written test, SS2023)	17
Exercise E4 Equivalent Linear Source (written test, approx. 10 % of a 60-minute written test, SS2023)	20
Exercise E7 (Dis)Charging Capacities (written test, approx. 14 % of a 60-minute written test, SS2023)	23
Exercise E8 Impedances at Frequencies (written test, approx. 14 % of a 60-minute written test, SS2023)	24

Exercise E9 Efficiency (written test, approx. 14 % of a 60-minute written test, SS2023) 25

Exam Summer Semester 2023

Additional permitted Aids

- non-programmable calculator,
- formulary (2 DIN A4 pages)

Hits

- The duration of the exam is 60 min.
- Attempts to cheat will lead to exclusion and failure of the exam.
- Withdrawal is no longer possible after these exam has been handed out.
- Please write down intermediate calculations and results on the assignment sheet. (when more space is needed also on the reverse side. In this case: Mark it clearly).
- Always use units in the calculation.
- Use a document-proof, non-red pen.

Only EEE1-relevant Part

This part is only for about 25 minutes !

Exercise E1 Resistivity and temperature dependent Resistance (written test, approx. 7 % of a 60-minute written test, SS2023)

The resistivity ρ of a dielectric material is temperature dependent and is described by the Arrhenius law: $\rho = \rho_0 \exp\left(\frac{A}{T}\right)$ with $\rho_0 = 10^{17} \Omega \cdot \text{m}$ and $A = 10^4 \text{ K}$. The resistivity ρ is given in $\Omega \cdot \text{m}$ and T in $^\circ\text{C}$. The temperature T is given in $^\circ\text{C}$ and ρ in $\Omega \cdot \text{m}$. The temperature T is given in $^\circ\text{C}$ and ρ in $\Omega \cdot \text{m}$. The temperature T is given in $^\circ\text{C}$ and ρ in $\Omega \cdot \text{m}$.

Solution: The resistivity of the dielectric material is $\rho_{\text{PP}}(20 \text{ } ^\circ\text{C}) = 10^{17} \Omega \cdot \text{m}$.

For the given material the temperature coefficients in the range of $20 \text{ } ^\circ\text{C}$ and $55 \text{ } ^\circ\text{C}$ are given as $\alpha = -0.048 \text{ } ^\circ\text{C}^{-1}$ and $\beta = +0.00057 \text{ } ^\circ\text{C}^{-2}$.

$$R(55 \text{ } ^\circ\text{C}) = R(20 \text{ } ^\circ\text{C}) \cdot (1 + \alpha \cdot \Delta T + \beta \cdot T^2 + \dots)$$
$$= 80 \text{ } \Omega \cdot \text{m} \cdot (1 - 0.048 \text{ } ^\circ\text{C}^{-1} \cdot (35 \text{ } ^\circ\text{C}) + 0.00057 \text{ } ^\circ\text{C}^{-2} \cdot (35 \text{ } ^\circ\text{C})^2)$$

Calculate the resistance for the dielectric material for $20\text{ }^\circ\text{C}$.

Solution

$$R(20\text{ }^\circ\text{C}) = \rho \cdot \frac{d}{A} = 10^{17}\text{ }\Omega \cdot \frac{0.8 \cdot 10^{-6}\text{ m}}{1\text{ m}^2}$$

Exercise E2 Pure Resistor Network Simplification (written test, approx. 12 % of a 60-minute written test, SS2023)

Calculate the voltage U_K across the resistor R_K , when switch S is closed.

Result

The values in the circuit are

Solution

$$R_1 = 60 \, \Omega$$

$$R_2 = 40 \, \Omega$$

$$R_3 = 40 \, \Omega$$

$$R_4 = 100 \, \Omega$$

The voltage divider for node K has the same proportionality as the voltage divider for node K' . Therefore, the potential of K is the same as for K' . There will be no current flow through R_3 . The resistance does not create a voltage drop and therefore does not interfere with the circuit.

1. Calculate the voltage at node K , when switch S is open.
It might be beneficial to redraw the circuit first.

Solution

Rearranging the circuit one can get:

Once the switch S is opened, the upper part is a parallel circuit. Therefore, R_{eq} is given as:

$$R_{\text{eq}} = (R_1 + R_2) \parallel (R_1 + R_2) + R_4 \\ = \frac{1}{2} \cdot (R_1 + R_2) + R_4 = \frac{1}{2} \cdot (60 \, \Omega + 40 \, \Omega) + 100 \, \Omega$$

Exercise E3 Pure Resistor Network Simplification I (written test, approx. 14 % of a 60-minute written test, SS2023)

The circuit below shall be given as $U_{\text{AB}} = 60 \, \text{V}$. What is the value for I_{AB} in the circuit?

Solution


$$I_{\text{AB}} = \frac{U_{\text{AB}}}{R_{\text{eq}}} = \frac{60 \, \text{V}}{120 \, \Omega} = 0.5 \, \text{A}$$

The current through the circuit is given as $I_{\text{AB}} = \frac{U_{\text{AB}}}{R_{\text{eq}}}$.

This current has to flow in summary through parallel branches. The voltage U in question in the upper right branch given by $(4R \parallel 4R) + 2R + 2R$. Its resistance is just the same as the upper left branch $6R$.

Therefore, half of the current flows to the left half to the right side.


The voltage U is consequently:
$$U = \frac{I_{\text{arm AB}}}{2 \cdot R_{\text{eq}}} \quad \& \quad U_{\text{AB}} = \frac{U_{\text{AB}} \cdot 2R}{2 \cdot R_{\text{eq}}} \quad \& \quad 60 \text{ V} = \frac{U}{5}$$



1. What is the equivalent resistance R_{eq} ?

Solution

Part of the circuit is shorted. Here the resistors (marked in red) are shorted by the connections marked in blue:



The circuit can then be rearranged for better interpretation:

Therefore, R_{eq} is given as:
$$R_{\text{eq}} = (2R \parallel 2R + R +$$


$$R) \parallel 6R \text{ \&\&+ } 6R \parallel (2R + 2R + 4R) \parallel 4R \text{ \&\&= } (R + R + R) \parallel 6R \text{ \&\&+ } 6R \parallel (2R + 2R + 2R) \text{ \&\&= } 3R \parallel 6R \text{ \&\&+ } 6R \parallel 6R \text{ \&\&= } \frac{\{3R \cdot 6R\}}{\{3R+6R\}} \text{ \&\&+ } 3R \text{ \&\& \end{align*}}$$

Exercise E4 Equivalent Linear Source (written test, approx. 10 % of a 60-minute written test, SS2023)

The circuit below has to be simplified. Use equivalent linear sources for simplification.


Calculate the internal resistance R_{i} and the source voltage U_{s} of an equivalent linear voltage source.

- $R_1 = 5 \text{ } \Omega$
 - $U_1 = 10 \text{ V}$
 - $R_2 = 5 \text{ } \Omega$
 - $I_3 = 0.5 \text{ A}$
 - $R_4 = 10 \text{ } \Omega$
 - $U_5 = 4 \text{ V}$
- $$U_{\text{AB}} = 1.11 \text{ V} \quad R_{\text{i}} = 5.55 \text{ } \Omega$$



Solution

The principle idea here is to find parts of the circuit which are already a linear (voltage or current) source. Then this can be transformed into the equivalent other source, as shown in the next picture.



In order to get the currents one has to calculate it by $I_x = \frac{U_x}{R_x}$

$$\begin{aligned} I_0 &= \frac{U_0}{R_1} = \frac{10 \text{ V}}{5 \text{ } \Omega} = 2 \text{ A} \\ I_5 &= \frac{U_5}{R_4} = \frac{4 \text{ V}}{10 \text{ } \Omega} = 0.4 \text{ A} \end{aligned}$$

I_3 and I_0 can be combined to $I_{03} = I_0 - I_3$ facing upwards:

$$I_{03} = 1.5 \text{ A}$$

Then, the linear current source I_{03} with R_1 gets transformed into a linear voltage source with $U_{03} = R_1 \cdot I_{03}$ facing down.

$$U_{03} = 7.5 \text{ V}$$

Then, the resistors R_1 and R_2 can be combined to $R_{12} = R_1 + R_2$.

After this, the next step is to make a linear current source out of U_{03} and R_{12} . The current will be $I_{0123} = \frac{U_{03}}{R_{12}}$, facing up again.

$$I_{0123} = 0.6 \text{ A}$$

The second-last step is the sum up of the current sources I_{0123} and I_5 as $I_{01235} = I_{0123} - I_5$ and the resistors as $R_{124} = R_{12} || R_4$.

$$I_{01235} = 0.2 \text{ A} \quad R_{124} = 5.55 \text{ } \Omega$$

The final step is the back-transformation to a linear voltage source, with $U_{\rm AB} = R_{124} \cdot I_{01235}$.

The simplest and fastest (= for exams) is to work with interim results in the calculation.

Here, there there is also a full final formula given:

$$\begin{aligned} U_{\rm s} &= U_{\rm AB} = I_{\{01235\}} \cdot R_{\{124\}} \quad \&= (I_{\{0123\}} - I_5) \cdot (R_{\{12\}} || R_4) \quad \&= \left(\frac{U_{\{03\}}}{R_{\{12\}}} - I_5 \right) \cdot \left((R_1 + R_2) || R_4 \right) \\ &\quad \&= \left(\frac{R_1 \cdot I_{\{03\}}}{R_1 + R_2} - I_5 \right) \cdot \left((R_1 + R_2) || R_4 \right) \\ &\quad \&= \left(\frac{R_1 \cdot \left(\frac{U_0}{R_1} - I_3 \right)}{R_1 + R_2} - I_5 \right) \cdot \left((R_1 + R_2) || R_4 \right) \end{aligned}$$

Full Exam

These is the full exam

Full exam

Exercise E1 Resistivity and temperature dependent Resistance (written test, approx. 7 % of a 60-minute written test, SS2023)

The results of the correlation coefficient R^2 of the linear fit of $\ln C_{\text{eq}}$ vs $\ln C_0$ is better described by eqs. S25 in a capacitor exponential adsorption surface of $A = 100$, then eq. S26 and eq. S25 of $b = 0.05$ for $\ln C_0$ vs $\ln C_{\text{eq}}$ of $-0.28 \sim (\text{m}^2/\text{g})$ and $100 \sim (\text{m}^2/\text{g})$.

The resistivity of the dielectric material is $\rho_{\text{PP}}(20^\circ\text{C}) = 10^{17} \Omega\cdot\text{m}$.

[illegible]

Calculate the resistance for the dielectric material for $20 \text{ }^\circ\text{C}$.

Solution

```
\begin{align*} R(20 \text{ }^\circ\text{C}) &= \rho \cdot \frac{d}{A} \\ &= 10^{17} \text{ } \Omega \cdot \text{m} \cdot \frac{0.8 \cdot 10^{-6} \text{ m}}{1 \text{ m}^2} \\ \end{align*}
```


[electrical_engineering_and_electronics:task_kyt15w11e3sempb2_with_calculation](#)
resistivity, power, exam ee1 ss2023

Exercise E5 Analyzing a Scope Plot (written test, approx. 12 % of a 60-minute written test, SS2023)

9. What is the RMS value of a sine wave with a peak-to-peak voltage of 10 V and a phase shift of 90 degrees? (in radian and degree)?

Result: measured current curve shall be visible as a dashed line.

The continuous line shows the voltage.



Use the correct symbols and units in your answers!

1. Calculate the frequency f of the periodic signals.

Solution

Frequency f is given by the period T . The period can be measured in the image of the scope.

1. The sine waves repeat after 6 divisions (e.g. from falling turning point to falling turning point of one curve)
2. The scale is 0.1 ms/Div

$$f = \frac{1}{T} \quad T = 6 \text{ Div} \cdot 0.1 \text{ ms/Div} \quad \rightarrow f = \frac{1}{6 \text{ Div} \cdot 0.1 \text{ ms/Div}}$$

electrical_engineering_and_electronics:task_1m3izw2szosswtto_with_calculation
exam ee1 ss2023

Exercise E6 Complex voltage dividers

(written test, approx. 16 % of a 60-minute written test, SS2023)

Task: Draw the two impedances in the circuit below, resulting phase shift between

Result: U_1 and U_2 . Choose an appropriate scaling factor and write it down.

- $R = 1.1 \text{ k}\Omega$

Result $L = 3.5 \sim \text{mH}$

$$\underline{U}_O = \underline{U}_I \cdot \frac{R}{R + \underline{Z}_L} \quad \underline{U}_O = 0.5 \sim \text{V} - j \cdot 1.5 \sim \text{V}$$

The formula to start with is the (complex) voltage divider: $\underline{U}_O = \underline{U}_I \cdot \frac{R}{R + \underline{Z}_L}$

At the off-frequency the absolute values of impedances $\underline{Z}_L$ is equal to R . This leads to $\frac{R}{R + \underline{Z}_L} = \frac{1}{2}$. Therefore $\underline{Z}_L = R$. $\underline{Z}_L = j\omega L$. $j\omega L = R$. $L = \frac{R}{\omega} = \frac{10 \sim \text{m}\Omega}{2\pi \cdot 3.5 \cdot 10^3 \sim \text{Hz}} = 3.5 \sim \text{mH}$



1. Calculate the impedance $\underline{Z}_L$.

Solution

$$\underline{Z}_L = j\omega L = j \cdot 2\pi \cdot 150 \sim \text{kHz} \cdot 3.5 \sim \text{mH} = j \cdot 3.5 \sim \text{m}\Omega$$

electrical_engineering_and_electronics:task_c9f15i7l797equs_with_calculation
impedance, phasor, cutoff, exam ee1 ss2023

Exercise E2 Pure Resistor Network Simplification (written test, approx. 12 % of a 60-minute written test, SS2023)

Calculate the voltage U_K , when switch S is closed.

Result

The values in the circuit are

Solution

• $R_1 = 60 \sim \Omega$
• $R_2 = 40 \sim \Omega$
• $R_3 = 40 \sim \Omega$
• $R_4 = 150 \sim \Omega$
The voltage divider node K has the same proportionality as the voltage divider node K' . Therefore, the potential of K is the same as for K' . There will be no current flow through R_3 . The resistance does not create a voltage drop and therefore does not interfere with the circuit.

1. Calculate the voltage at node K , when switch S is open.
It might be beneficial to redraw the circuit first.

Solution

Rearranging the circuit one can get:

Once the switch S is opened, the upper part is a parallel circuit. Therefore, R_{eq} is given as:

$$R_{\text{eq}} = \frac{(R_1 + R_2) \parallel (R_1 + R_2) + R_4}{1} = \frac{1}{2} \cdot (R_1 + R_2) + R_4 = \frac{1}{2} \cdot (60 \, \Omega + 40 \, \Omega) + 100 \, \Omega$$

[electrical_engineering_and_electronics:task_cgcyprm6oboukcci_with_calculation_network_simplification, exam ee1 ss2023](#)

Exercise E3 Pure Resistor Network Simplification I (written test, approx. 14 % of a 60-minute written test, SS2023)

The input voltage is given as $U_{\text{AB}} = 60 \, \text{V}$. What is the value for I_{AB} in the circuit?

Solution


$$I_{\text{AB}} = \frac{U_{\text{AB}}}{R_{\text{eq}}} = \frac{60 \, \text{V}}{120 \, \Omega} = 0.5 \, \text{A}$$

The current through the circuit is given as $I_{\text{AB}} = \frac{U_{\text{AB}}}{R_{\text{eq}}}$.

This current has to flow in summary through parallel branches. The voltage U in question in the upper right branch given by $(4R \parallel 4R) + 2R + 2R$. Its resistance is just the same as the upper left branch $6R$.

Therefore, half of the current flows to the left half to the right side.


The voltage U is consequently:
$$U = \frac{I_{\text{AB}}}{2 \cdot R_{\text{eq}}} \quad \&= \quad \frac{U_{\text{AB}} \cdot 2R}{2 \cdot R_{\text{eq}}} \\ \&= \quad \frac{60 \text{ V}}{5}$$



1. What is the equivalent resistance R_{eq} ?

Solution

Part of the circuit is shorted. Here the resistors (marked in red) are shorted by the connections marked in blue:



The circuit can then be rearranged for better interpretation:

Therefore, R_{eq} is given as:
$$R_{\text{eq}} = (2R \parallel 2R + R + R) \parallel 6R + 6R \parallel (2R + 2R + 4R \parallel 4R) \parallel (R + R + R) \parallel 6R + 6R \parallel (2R + 2R)$$

$$+ 2R) \parallel \&= 3R \parallel 6R \&\&+ 6R \parallel 6R \parallel \&= \frac{3R \cdot 6R}{3R+6R} \&\&+ 3R \parallel$$

$$\end{align*}$$


[electrical_engineering_and_electronics:task_erlctd760zmvox0t_with_calculation_network_simplification, exam ee1 ss2023](#)

Exercise E4 Equivalent Linear Source

(written test, approx. 10 % of a 60-minute written test, SS2023)


The circuit below has to be simplified. Use equivalent linear sources for simplification. Calculate the internal resistance R_{i} and the source voltage U_{ss} of an equivalent linear voltage source.

- $R_1 = 5 \, \Omega$
- $U_1 = 10 \, \text{V}$
- $R_2 = 10 \, \Omega$
- $R_3 = 5 \, \Omega$
- $I_3 = 0.5 \, \text{A}$
- $R_4 = 10 \, \Omega$
- $U_5 = 4 \, \text{V}$



Solution

The principle idea here is to find parts of the circuit which are already a linear (voltage or current) source. Then this can be transformed into the equivalent other source, as shown in the next picture.



In order to get the currents one has to calculate it by $I_x = \frac{U_x}{R_x}$

$$\begin{aligned} I_0 &= \frac{U_0}{R_1} = \frac{10 \text{ V}}{5 \text{ } \Omega} = 2 \text{ A} \\ I_5 &= \frac{U_5}{R_4} = \frac{4 \text{ V}}{10 \text{ } \Omega} = 0.4 \text{ A} \end{aligned}$$

I_3 and I_0 can be combined to $I_{03} = I_0 - I_3$ facing upwards:

$$I_{03} = 1.5 \text{ A}$$

Then, the linear current source I_{03} with R_1 gets transformed into a linear voltage source with $U_{03} = R_1 \cdot I_{03}$ facing down.

$$U_{03} = 7.5 \text{ V}$$

Then, the resistors R_1 and R_2 can be combined to $R_{12} = R_1 + R_2$.

After this, the next step is to make a linear current source out of U_{03} and R_{12} . The current will be $I_{0123} = \frac{U_{03}}{R_{12}}$, facing up again.

$$I_{0123} = 0.6 \text{ A}$$

The second-last step is the sum up of the current sources I_{0123} and I_5 as $I_{01235} = I_{0123} - I_5$ and the resistors as $R_{124} = R_{12} || R_4$.

$$I_{01235} = 0.2 \text{ A} \quad R_{124} = 5.55... \text{ } \Omega$$

The final step is the back-transformation to a linear voltage source, with U_{rm}

$$AB\} = R_{124} \cdot I_{01235}\}.$$

The simplest and fastest (= for exams) is to work with interim results in the calculation.

Here, there is also a full final formula given:

$$\begin{aligned} U_{AB} &= U_{AB} = I_{01235} \cdot R_{124} \parallel \\ &= (I_{0123} - I_5) \cdot (R_{12} \parallel R_4) \parallel \\ &= \left(\frac{U_{03}}{R_{12}} - I_5 \right) \cdot \left((R_1 + R_2) \parallel R_4 \right) \parallel \\ &= \left(\frac{R_1 \cdot I_{03}}{R_1 + R_2} - I_5 \right) \cdot \left((R_1 + R_2) \parallel R_4 \right) \parallel \\ &= \left(\frac{R_1 \cdot \left(\frac{U_0}{R_1} - I_3 \right)}{R_1 + R_2} - I_5 \right) \cdot \left((R_1 + R_2) \parallel R_4 \right) \end{aligned}$$

electrical_engineering_and_electronics:task_lefxcuaxiu8ewcr9_with_calculation
network simplification, equivalent sources, exam ee1 ss2023

Exercise E7 (Dis)Charging Capacities

(written test, approx. 14 % of a 60-minute written test, SS2023)

The circuit diagram shows a DC voltage source $U = 10 \text{ V}$, a switch S_1 , a capacitor $C = 200 \text{ nF}$, and two resistors $R_1 = 8.0 \text{ k}\Omega$ and $R_2 = 17 \text{ k}\Omega$. The switch S_1 can connect the capacitor to either the voltage source or to a parallel combination of R_1 and R_2 . Initially, the capacitor is fully charged to $U = 10 \text{ V}$. At $t = 0$, the switch S_1 is moved to the position where it connects the capacitor to the parallel resistors. What is the voltage across the capacitor at $t = 10 \text{ ms}$?


- $C = 200 \text{ nF}$

Solution: $R_1 = 8.0 \text{ k}\Omega$

Solution: $R_2 = 17 \text{ k}\Omega$

$$\begin{aligned} U_C(t) &= U_C(0) \cdot e^{-t/\tau} \\ \tau &= (R_1 \parallel R_2) \cdot C = (8.0 \text{ k}\Omega \parallel 17 \text{ k}\Omega) \cdot 200 \text{ nF} = 1.17 \text{ ms} \\ U_C(10 \text{ ms}) &= 10 \text{ V} \cdot e^{-10 \text{ ms} / 1.17 \text{ ms}} = 10 \text{ V} \cdot e^{-8.54} = 10 \text{ V} \cdot 0.0002 = 0.002 \text{ V} \end{aligned}$$

The current of the source flows through the circuit consisting of C in parallel with R_1 and R_2 . Without the parallel resistors, the current source would charge the capacitor "to infinity" ($U_C \rightarrow \infty$). This is here limited by the parallel resistors. When S_2 is closed, then, the source U drives the current through the series circuit given by S_1 , C , R_1 and R_2 . Therefore, the voltage on the branch with the resistors ($R_1 \parallel R_2$) is $U_C = (R_1 \parallel R_2) \cdot I = (8.0 \text{ k}\Omega \parallel 17 \text{ k}\Omega) \cdot 0.2 \text{ mA} = 25 \text{ V} \cdot 10^{-3} = 0.25 \text{ V}$. This is also the maximum voltage on the capacitor, since it is in parallel with the resistors.



Before $t = 0$ all switches are switched as shown and the capacitor is fully discharged. At $t = 0$ the switch S_1 shall switch to the voltage source.

1. Calculate the time constant for charging the capacitor.

Solution

The time constant is generally given as: $\tau = R \cdot C$

Once S_1 is closed and S_2 is open at t_0 , the source U drives the current through the series circuit given by S_1 , C , R_1 and R_3 .
Therefore, $R = R_1 + R_3$ $\tau_1 = (R_1 + R_3) \cdot C = (8 \text{ k}\Omega + 7 \text{ k}\Omega) \cdot 0.2 \text{ }\mu\text{F} = 15 \cdot 10^3 \cdot 0.2 \cdot 10^{-6} \text{ s} = 3 \text{ }\mu\text{s}$

...

Solution

Both courses of the voltage for charging and discharging are described with an exponential function. However, the curve for charging increases first steep and flattens out for longer time scales ($\propto (1 - e^{-x})$).

[electrical_engineering_and_electronics:task_p8yrdjr60k6bvc4n_with_calculation_charging, capacities, exam ee1 ss2023](#)

Exercise E8 Impedances at Frequencies

(written test, approx. 14 % of a 60-minute written test, SS2023)

At an inductor with $L = 50 \text{ mH}$ following harmonic voltage $u(t) = 100 \sin(2\pi \cdot 15.9 \cdot t) \text{ V}$ is applied. The resulting current $i(t)$ is measured with a 5.6 mF capacitor.

1. An inductor with $X_{L1} = 60 \text{ m}\Omega$ and $L_1 = 15.9 \text{ mH}$.

Solution

Solution

$$f = 15.9 \text{ kHz} \quad \omega = 2\pi \cdot 15.9 \text{ kHz} = 1000 \text{ rad/s}$$

$$X_{L1} = \omega L_1 = 1000 \text{ rad/s} \cdot 15.9 \text{ mH} = 15.9 \text{ m}\Omega$$

$$X_{C1} = \frac{1}{\omega C_1} = \frac{1}{1000 \text{ rad/s} \cdot 5.6 \text{ mF}} = 17.86 \text{ m}\Omega$$

$$X_{\text{total}} = X_{L1} - X_{C1} = 15.9 \text{ m}\Omega - 17.86 \text{ m}\Omega = -1.96 \text{ m}\Omega$$

$$I_{\text{eff}} = \frac{U_{\text{eff}}}{|X_{\text{total}}|} = \frac{100 \text{ V}}{1.96 \text{ m}\Omega} = 51.02 \text{ A}$$

electrical_engineering_and_electronics:task_uzbbnoz8abe6201d_with_calculation
exam ee1 ss2023

Exercise E9 Efficiency

(written test, approx. 14 % of a 60-minute written test, SS2023)

A. (34.4%) Efficiency of a power transistor is determined by the ratio of the output power to the input power. The battery shall

provide energy for an antenna with a resistance of $R_{\text{ant}} = 3.5 \text{ m}\Omega$. The efficiency of the antenna is $\eta = 0.95$. The battery datasheet:

$$U_{\text{nom}} = 3.5 \text{ V} \quad I_{\text{max}} = 3.5 \text{ A} \quad R_{\text{int}} = 0.5 \text{ m}\Omega$$

Solution: The efficiency of the antenna is $\eta = 0.95$. The efficiency of the antenna is $\eta = 0.95$.

$$\eta = \frac{P_{\text{out}}}{P_{\text{in}}} = \frac{I_{\text{ant}}^2 R_{\text{ant}}}{I_{\text{ant}}^2 R_{\text{ant}} + I_{\text{ant}}^2 R_{\text{int}}} = \frac{R_{\text{ant}}}{R_{\text{ant}} + R_{\text{int}}}$$

lowest efficiency for highest resistance of $R_{\text{ant}} = 3.5 \text{ m}\Omega$ in this case, the

.. efficiency is $\eta = 0.95$.


valent circuit diagram with the internal resistance and an external

load. The voltage and current I_{ant} are $I_{\text{ant}} = 2.6 \text{ A}$.

$$P_{\text{out}} = I_{\text{ant}}^2 R_{\text{ant}} = (2.6 \text{ A})^2 \cdot 3.5 \text{ m}\Omega = 2.38 \text{ W}$$

$$\eta = \frac{P_{\text{out}}}{P_{\text{in}}} = \frac{2.38 \text{ W}}{2.5 \text{ W}} = 0.95$$

Result: $\eta = 0.95$



electrical_engineering_and_electronics:task_w3wf215v2u98ty07_with_calculation
efficiency, charges, power, exam ee1 ss2023

From:

<https://wiki.mexle.te.hs-heilbronn.de/> - MEXLE Wiki

Permanent link:

https://wiki.mexle.te.hs-heilbronn.de/electrical_engineering_and_electronics_1/ss2023_exam

Last update: 2026/01/12 00:31

