

task_wjttvmydrskzhcim_with_calculation

Student Group

First Name	Surname	Matrikel Nr.

Table of Contents

Exercise E1 Component Parameters (written test, approx. 10 % of a 120-minute written test,
SS2021) 2

complex voltage divider, RMS, inductor, exam ee2 SS2021

Exercise E1 Component Parameters**(written test, approx. 10 % of a 120-minute written test, SS2021)**

For the next exercises consider the following circuit. The motor presents a resistive inductive load!

From measurements, an AC voltage with a constant RMS value of $U_{\text{RMS}} = 50 \text{ V}$ is determined. Both results in the impedance of the motor.

This resulted in the recorded current of

a) Derive in general the equation for the absolute value of the impedance of the motor.

$$|Z| = \sqrt{(2\pi f \cdot L_{\text{M}})^2 + R_{\text{M}}^2}$$

$$R_{\text{M}} = 4.3301 \text{ } \Omega$$

$$L_{\text{M}} = 14.346 \text{ mH}$$

b) Determine the absolute values of the impedances with the specified RMS values at f_1 and f_2 (independent).

$$|Z_1| = \sqrt{(2\pi f_1 \cdot L_{\text{M}})^2 + R_{\text{M}}^2} = 50 \text{ V}$$

$$|Z_2| = \sqrt{(2\pi f_2 \cdot L_{\text{M}})^2 + R_{\text{M}}^2} = 14.346 \text{ mH}$$

The complex impedance $\underline{Z}$ for a resistive inductive load is given as

$$\underline{Z} = R_{\text{M}} + j\omega L_{\text{M}}$$

$$|Z| = \sqrt{R_{\text{M}}^2 + (\omega L_{\text{M}})^2}$$

$$|Z_1| = \sqrt{R_{\text{M}}^2 + (2\pi f_1 L_{\text{M}})^2} = 50 \text{ V}$$

$$|Z_2| = \sqrt{R_{\text{M}}^2 + (2\pi f_2 L_{\text{M}})^2} = 14.346 \text{ mH}$$

$$|Z_1|^2 = R_{\text{M}}^2 + (2\pi f_1 L_{\text{M}})^2 = 50^2$$

$$|Z_2|^2 = R_{\text{M}}^2 + (2\pi f_2 L_{\text{M}})^2 = (14.346 \text{ mH})^2$$

$$|Z_1|^2 - |Z_2|^2 = (2\pi f_1 L_{\text{M}})^2 - (2\pi f_2 L_{\text{M}})^2 = 50^2 - (14.346 \text{ mH})^2$$

$$L_{\text{M}} = \frac{\sqrt{|Z_1|^2 - |Z_2|^2}}{2\pi(f_1^2 - f_2^2)}$$

$$L_{\text{M}} = 14.346 \text{ mH}$$

And then to R_{M} :

$$R_{\text{M}} = \sqrt{|Z_1|^2 - (2\pi f_1 L_{\text{M}})^2} = 4.3301 \text{ } \Omega$$

With the values:

$$L_{\text{M}} = \frac{\sqrt{(50 \text{ V})^2 - (2\pi \cdot 100 \text{ Hz} \cdot L_{\text{M}})^2}}{2\pi((100 \text{ Hz})^2 - (50 \text{ Hz})^2)}$$

$$R_{\text{M}} = \sqrt{(50 \text{ V})^2 - (2\pi \cdot 100 \text{ Hz} \cdot 14.346 \text{ mH})^2} = 4.3301 \text{ } \Omega$$

$$R_{\text{M}} = \sqrt{(50 \text{ V})^2 - (2\pi \cdot 100 \text{ Hz} \cdot 14.346 \text{ mH})^2} = 4.3301 \text{ } \Omega$$

From:

<https://wiki.mexle.te.hs-heilbronn.de/> - **MEXLE Wiki**

Permanent link:

https://wiki.mexle.te.hs-heilbronn.de/ee2/task_wjttvmydrskzhcim_with_calculation?rev=1720050503

Last update: **2024/07/04 01:48**

