

7 Networks at variable frequency

Student Group

First Name	Surname	Matrikel Nr.

Table of Contents

7. Networks at variable frequency	2
Introduction	2
Targets	2
7.1 From Two-Terminal Network to Four-Terminal Network	2
Reminder:	3
7.2 RL Series Circuit	4
7.2.1 RL High Pass	5
Reminder:	9
7.2.2 RL Low Pass	18
7.3 RC Series Circuit	22
7.3.1 RC High Pass	22
7.3.2 RC Low Pass	26

7. Networks at variable frequency

Further content can be found at this [Tutorial](#) or that [Tutorial](#)

Introduction

At the previous chapters it was explained how the “influence of a sinusoidal current flow” of capacitor and inductors look like. To describe this, the impedance was introduced. This can be understood as a complex resistance for sinusoidal excitation.

It applies to the capacitor:

$$\begin{aligned} \underline{U}_C &= \frac{1}{j\omega \cdot C} \cdot \underline{I}_C \quad \rightarrow \\ \underline{Z}_C &= \frac{1}{j\omega \cdot C} \end{aligned}$$

and for the inductance

$$\begin{aligned} \underline{U}_L &= j\omega \cdot L \cdot \underline{I}_L \quad \rightarrow \\ \underline{Z}_L &= j\omega \cdot L \end{aligned}$$

Complex impedances can be dealt with in much the same way as ohmic resistances in Electrical Engineering 1 (see: [simple DC Circuits](#), [linear Sources and two-terminal network](#), [Analysis of DC Networks](#)). In these transformations, the fraction $j\omega$ is preserved. Circuits with impedances such as inductors and capacitors will show a frequency dependence accordingly.


Targets

After this lesson, you should:

1. know that ...
2. know that ... is formed.
3. be able to ... can ...

7.1 From Two-Terminal Network to Four-Terminal Network

Fig. 1: Two-Terminal Network to Four-Terminal Network



Until now, components such as resistors, capacitors and inductors have been understood as two-terminal. This is also obvious, since there are only two connections. In the following however circuits are considered, which behave similar to a voltage divider: On one side a voltage $\underline{U}_I$ is applied, on the other side $\underline{U}_O$ is formed with it. This results in 4 terminals. The circuit can and will be considered as a four-terminal network in the following. However, the input and output values will be complex.

For a four-terminal network, the relation of “what goes out” (e.g. $\underline{U}_O$ or $\underline{U}_2$) to “what goes in” (e.g. voltage $\underline{U}_I$ or $\underline{U}_1$) is important. Thus, the output and input variables ($\underline{U}_O$) and ($\underline{U}_I$) give the quotient:

$$\begin{aligned} \underline{A} &= \frac{\underline{U}_O}{\underline{U}_I} \quad \& \text{with} \quad \underline{U}_O = U_O \cdot e^{j\varphi_O} \quad \& \text{and} \quad \underline{U}_I = U_I \cdot e^{j\varphi_I} \\ \underline{A} &= \frac{U_O \cdot e^{j\varphi_O}}{U_I \cdot e^{j\varphi_I}} = \frac{U_O}{U_I} \cdot e^{j(\varphi_O - \varphi_I)} \end{aligned}$$

$$\boxed{\underline{A}} = \frac{U_O}{U_I} \cdot e^{j\Delta\varphi} \quad \Delta\varphi = \varphi_O - \varphi_I$$


Reminder:

- The complex-valued quotient $\frac{\underline{U}_O}{\underline{U}_I}$ is called the **transfer function**.
- The frequency-dependent magnitude of the quotient $A(\omega) = \frac{U_O}{U_I}$ is called **amplitude response** and the angular difference $\Delta\varphi_u(\omega)$ is called **phase response**.

The frequency behaviour of the amplitude response and the frequency response is not only important in electrical engineering and electronics, but will also play a central role in control engineering.

7.2 RL Series Circuit

Fig. 2: RL-series



$\underline{U}_I = \underline{X}_I \cdot \underline{I}$ with $\underline{X}_I = R + j\omega L$ and corresponding for $\underline{U}_O$: $\underline{A} = \frac{\underline{U}_O}{\underline{U}_I} = \frac{j\omega L}{R + j\omega L} = \frac{\omega L}{\sqrt{R^2 + (\omega L)^2}} \cdot e^{j\left(\frac{\pi}{2} - \arctan \frac{\omega L}{R}\right)}$

First, a series connection of a resistor R and an inductor L shall be considered (see [figure 2](#)). This structure is also called RL-element.

Here, $\underline{U}_I = \underline{X}_I \cdot \underline{I}$ with $\underline{X}_I = R + j\omega L$ and corresponding for $\underline{U}_O$: $\underline{A} = \frac{\underline{U}_O}{\underline{U}_I} = \frac{j\omega L}{R + j\omega L} = \frac{\omega L}{\sqrt{R^2 + (\omega L)^2}} \cdot e^{j\left(\frac{\pi}{2} - \arctan \frac{\omega L}{R}\right)}$

This results in the following for

- the amplitude response: $A = \frac{\omega L}{\sqrt{R^2 + (\omega L)^2}}$ and
- the phase response: $\Delta\varphi_u = \arctan \frac{R}{\omega L} = \frac{\pi}{2} - \arctan \frac{\omega L}{R}$

The main focus should first be on the amplitude response. Its frequency response can be derived from the equation in various ways.

1. Extreme frequency consideration of this RL circuit (in the equation and in the system)
2. Plotting amplitude and frequency response
3. Determination of prominent frequencies

These three points are now to be gone through.

7.2.1 RL High Pass

For the first step we investigate the limit consideration: We look at what happens, when the frequency ω runs to the definition range limits, i.e. $\omega \rightarrow 0$ and $\omega \rightarrow \infty$:

- For $\omega \rightarrow 0$, $A = \frac{\omega L}{\sqrt{R^2 + (\omega L)^2}} \rightarrow 0$ as the numerator approaches zero and the denominator remains greater than zero.
- For $\omega \rightarrow \infty$, $A \rightarrow 1$, because in the root in the denominator $(\omega L)^2$ becomes larger and larger in the ratio R^2 to . So the root tends to ωL and thus to the numerator.

It can thus be seen that:

- at small frequencies there is no voltage U_2 at the output.
- at high frequencies $A = \frac{U_O}{U_I} \rightarrow 1$, so the voltage at the output is equal to the voltage at the input.

Result:

The RL element shown here therefore only allows large frequencies to pass (= pass through) and small ones are filtered out.

The circuit corresponds to a **high pass**.

This can also be derived from understanding the components:

- At small frequencies, the current in the coil and thus the magnetic field changes only slowly. So only a negligibly small reverse voltage is induced. The coil acts like a short circuit at low frequencies.
- At higher frequencies, the current generated by U_I through the coil changes faster, the induced voltage $U_i = - \frac{dI}{dt}$ becomes large.
As a result, the coil inhibits the current flow and a voltage drops across the coil.
- If the frequency becomes very high, only a negligible current flows through the coil - and hence through the resistor. The voltage drop at R thus approaches zero and the output voltage U_O tends towards U_I .

The transfer function can also be decomposed into amplitude response and frequency response. Often this plots are not given in with linear axis but:

- the amplitude response with a double logarithmic coordinate system and
- the phase response single logarithmic coordinate system.

By this, the course from low to high frequencies are easier to see. The following simulation in [figure 3](#) shows the amplitude response and frequency response in the lower left corner.

Fig. 3: RL high pass filter

For further consideration, the equation of the transfer function $\underline{A} = \frac{\underline{U}_O}{\underline{U}_I}$ is to be rewritten so that it becomes independent of component values R and L .

This allows for a generalized representation. This representation is called **normalization**:

$$\underline{A} = \frac{\underline{U}_O}{\underline{U}_I} = \frac{\omega L}{\sqrt{R^2 + (\omega L)^2}} \cdot e^{j\left(\frac{\pi}{2} - \arctan \frac{\omega L}{R}\right)}$$


$$\underline{A}_{\text{norm}} = \frac{\omega L / R}{\sqrt{1 + (\omega L / R)^2}} \cdot e^{j\left(\frac{\pi}{2} - \arctan \frac{\omega L}{R}\right)}$$

$$\underline{A} = \frac{x}{\sqrt{1 + x^2}} \cdot e^{j\left(\frac{\pi}{2} - \arctan x\right)}$$

This equation behaves quite the same as the one considered so far.

figure 4 shows the two plots. On the x-axis, $x = \omega L / R$ has been plotted as the normalization variable. This represents a weighted frequency.

Fig. 4: Amplitude and phase response of the RL high-pass filter



Here, too, the behavior determined in the limit value observation can be seen:

- at small frequencies ω (corresponds to small x), the amplitude response tends toward zero.
- At high frequencies, the ratio $U_O / U_I = 1$ is established.

Interesting in the phase response is the point $x = 1$.

- Further to the left of this point (i.e. at smaller frequencies) a tenfold increase of the frequency ω produces a tenfold increase of U_O / U_I .
- Further to the right of this point (i.e. at higher frequencies) $U_O / U_I = 1$ remains.

So this point marks a limit. Far to the left, the ohmic resistance is significantly greater the amount of impedance of the coil: $R \gg \omega L$. far to the right is just the opposite.

The point $x=1$ just marks the cut-off frequency.

It holds

$$\underline{A}_{\text{norm}} = \frac{x}{\sqrt{1 + x^2}} \cdot e^{j\left(\frac{\pi}{2} - \arctan x\right)} = \frac{U_O}{U_I} \cdot e^{j\varphi} \quad \left\{ \begin{array}{l} x \gg 1 \end{array} \right. \&$$

$\widehat{=} \& \omega L \parallel R \&: \quad \quad \frac{U_O}{U_I} = x \&, \varphi = \frac{\pi}{2} \setminus,$
 $\widehat{=} \setminus, 90^\circ \setminus x \leq 1 \& \widehat{=} \& \omega L \leq R \&: \quad \quad \frac{U_O}{U_I} = 1 \&, \varphi = 0 \setminus: \widehat{=} \setminus, 0^\circ \setminus x = 1 \& \widehat{=} \& \omega L = R \&: \quad \quad \frac{U_O}{U_I} = \frac{1}{\sqrt{2}} \&, \varphi = \frac{\pi}{4} \setminus, \widehat{=} \setminus, 45^\circ \end{array}$
 \right. \end{align*}

1 <\WRAP>

2 <\WRAP> <\WRAP>

$$\begin{aligned} & \underline{\{A\}_{\text{norm}}} = \\ & \frac{x}{\sqrt[3]{1 + x^2}} \cdot e^{j \left(\frac{\pi}{2} - \arctan x \right)} \\ & = \\ & \frac{U_O}{U_I} \cdot e^{j \varphi} \end{aligned}$$

$$\begin{aligned} & \underline{\{A\}_{\text{norm}}} \\ & x \parallel 1 \& \widehat{=} \& \omega L \parallel R \&: \quad \quad \frac{U_O}{U_I} = 1 \&, \varphi = 0 \setminus: \widehat{=} \setminus, 0^\circ \setminus x = 1 \& \widehat{=} \& \omega L = R \&: \quad \quad \frac{U_O}{U_I} = \frac{1}{\sqrt{2}} \&, \varphi = \frac{\pi}{4} \setminus, \widehat{=} \setminus, 45^\circ \end{aligned}$$

$d \backslash q_u$

ad

$\frac{1}{\omega}$

$\{U_O$

$\} \{U_O$

$\} = x$

$\&$,

φ

$h_i =$

$\frac{1}{\omega}$

$\{\pi\}$

$\{2\}$

$\backslash$,

$\widehat{}$

$\hat{}$

$= \} \backslash$,

90°

$\backslash x$

$\lg 1$

$\&$

$\widehat{}$

$\hat{}$

$= \} \&$

ω

g_L

$\lg R$

$\&:$

$\backslash q_u$

$d \backslash q_u$

ad

$\frac{1}{\omega}$

$\{U_O$

$\} \{U_O$

$\} = 1$

$\&$,

φ

$h_i =$

$0 \backslash:$

$\widehat{}$

$\hat{}$

$= \} \backslash$,

$0^\circ \backslash$

$x = 1$

$\&$

$\widehat{}$

$\hat{}$

$= \} \&$

ω

g_L

$= R$

$\&:$

```
\qua
d\qu
ad
\frac
{U_O
}{U_
l}=\f
rac{
1}{\
sqrt{
2}}
&,
\varp
hi =
\frac
{\pi}
{4}
\,
\wide
hat{
=} \,
45^\circ
\end
{arra
y}
\right
.
\end
{alig
n*}
<\W
RAP
>
<\W
RAP
>
```

Rem
inde
r:

-

T
h
e
c
u
t
-
o

f
f
r
e
q
u
e
n
c
y
\$
f
-
c
\$
f
o
r
h
i
g
h
-
p
a
s
s
a
n
d
l
o
w
-
p
a
s
s
fi
l
t
e
r
s
i
s
t
h
e
f
r

e
q
u
e
n
c
y
a
t
w
h
i
c
h
t
h
e
o
h
m
i
c
r
e
s
i
s
t
a
n
c
e
j
u
s
t
e
q
u
a
l
s
t
h
e
v
a
l
u
e
o

f
t
h
e
i
m
p
e
d
a
n
c
e
.

• The cut-off frequency separates a range in w

h
i
c
h
t
h
e
fi
l
t
e
r
a
l
l
o
w
s
s
i
g
n
a
l
s
t
h
r
o
u
g
h
f
r
o
m
o
n
e
i
n
w
h
i
c
h
t
h
e
y
a

r
e
s
u
p
p
r
e
s
s
e
d
(
=
b
l
o
c
k
e
d
)
.

- A
t
t
h
e
c
u
t
-
o
ff
f
r
e
q
u
e
n
c
y
,
t
h
e
p
h
a

s
e
\$
\
v
a
r
p
h
i
=
4
5
°
\$
a
n
d
t
h
e
a
m
p
l
i
t
u
d
e
\$
A
=
\
f
r
a
c
{
1
}
{
\
s
q
r
t
{
2
}
}

\$
.
•
l
n
G
e
r
m
a
n
t
h
e
c
u
t
-
o
ff
F
r
e
q
u
e
n
c
y
i
s
c
a
l
l
e
d
G
r
e
n
z
f
r
e
q
u
e
n
z
\$

$$f$$

$$\frac{1}{\omega C}$$

$$G$$

$$r$$

$$\}$$

$$\frac{1}{\omega L}$$

These statements apply to single-stage passive filters, i.e. one RL or one RC element. Multi-stage filters are considered in circuit engineering.

The cut-off frequency

in
this
case
is
give
n by:

[illegible]

7.2.2

RL Low Pass s

Fig.
5:
Circuit,
point
er
diagram,
and
amplitude
and
phase
response
of RL
low-pass
filter

So
far,
only
one
variant
of
the
RL
element
has
been
considered,
namely
the
one
where
the
output

volta
ge
\$\un
derli
ne{U
}_O\$
is
tapp
ed at
the
induc
tanc
e.
Here
we
will
briefl
y
discu
ss
what
happ
ens
when
the
two
com
pone
nts
are
swap
ped.

In
this
case,
the
norm
alize
d
trans
fer
funct
ion is
give
n by:

\begi
n{ali
gn*}
\und

$$\frac{1}{\sqrt{1 + \left(\frac{\omega L}{R}\right)^2}} \cos \arctan \frac{\omega L}{R}$$

The cut-off frequency is again given by $\omega_c = \frac{R}{2\pi \cdot L}$.

Fig.
6: RL
low
pass

filter

7. 3 RC Se rie s Cir cui t

7.3. 1 RC Hig h Pas s

Fig.
7:
Circu
it,
point
er
diagr
am,
and
ampl
itude
and
phas
e
resp
onse
of
the
RC
high-
pass
filter

Now
a
volta
ge
divid
er is
to be
const
ructe
d by
a
resis
tor
 $\frac{R}{\omega C}$
and
a
capa
city
 $\frac{1}{\omega C}$.
Quite
simil
ar to
the
previ
ous
chap
ters,
the
trans
fer
funct
ion
can
also
be
deter
mine
d
here.

Here
resul
ts as
norm
alize
d
trans
fer
funct

ion:

$$\begin{aligned} & \begin{aligned} & \frac{1}{\sqrt{1 + (\omega RC)^2}} \\ & \cdot e^{\frac{j\pi}{2}} \\ & \cdot \arctan(\omega RC) \end{aligned} \\ & \end{aligned}$$

In this case, the normalization variable $x = \omega RC$. Again,

$$\frac{1}{\sqrt{1 + \left(\frac{\omega}{\omega_c}\right)^2}}$$

Fig.
8: RC
high
pass
filter

7.3. 2 RC Low Pas s

Fig.
9:
Circu
it,
point
er
diagr
am,
and
ampl
itude
and
phas
e

resp
onse
of RC
low-
pass
filter

Agai
n,
the
volta
ge at
the
impe
danc
e is
to be
used
as
the
outp
ut
volta
ge.
This
resul
ts in
a
low-
pass
filter.

Here
resul
ts as
norm
alize
d
trans
fer
funct
ion:

\begi
n{ali
gn*}
\und
erlin
e{A}
_{no

$$\frac{1}{\sqrt{1 + (\omega RC)^2}}$$

Also,
the
cut-
off
frequ
ency
is
give
n by
 f_c
 $= \frac{1}{2\pi RC}$

Fig.
10:
RC
low
pass
filter

