

# task\_kricv9fh7haauo6q\_with\_calculation

## Student Group

| First Name | Surname | Matrikel Nr. |
|------------|---------|--------------|
|            |         |              |
|            |         |              |
|            |         |              |

## Table of Contents

complex impedance, exam ee1 WS2022

## Exercise 1.1 : Complex Impedance Circuit

(written test, approx. 15% of a 60-minute written test, WS2022)

A circuit designed to filter the noise from a signal shall be analysed.


The input is given by a voltage source  $u(t) = 3.0 \text{ V} \cdot \sin(2\pi \cdot 15 \text{ kHz} \cdot t)$  with an internal resistance of  $10 \text{ } \Omega$ .

This linear source is connected with an inductor of  $330 \text{ } \mu\text{H}$  and a capacitor of  $0.22 \text{ } \mu\text{F}$ , all in series.

1. Draw the circuit diagram of the given circuit.  
Label all components, voltages and currents.

Result





2. Calculate the single impedance  $\underline{Z}_C$ ,  $\underline{Z}_L$  such as  $\underline{Z}$  of the overall circuit.

Solution

$$\begin{aligned} Z_C &= \frac{1}{2\pi \cdot f \cdot C} = \frac{1}{2\pi \cdot 15 \text{ kHz} \cdot 0.22 \text{ } \mu\text{F}} \\ Z_L &= 2\pi \cdot f \cdot L = 2\pi \cdot 15 \text{ kHz} \cdot 0.22 \text{ } \mu\text{F} \\ Z_C &= \frac{1}{2\pi \cdot f \cdot C} = \frac{1}{2\pi \cdot 15 \text{ kHz} \cdot 330 \text{ } \mu\text{H}} \\ \underline{Z} &= R + \underline{Z}_L + \underline{Z}_C = R + j \cdot \{Z_L - Z_C\} = R + j \cdot (\{Z_L - Z_C\}) \\ |\underline{Z}| &= \sqrt{R^2 + (\underline{Z}_L - \underline{Z}_C)^2} \end{aligned}$$

Final result

$$\begin{aligned} Z_L &= 31.1 \text{ } \Omega \\ Z_C &= 48.2 \text{ } \Omega \\ Z &= 19.8 \text{ } \Omega \end{aligned}$$

3. Draw the three impedance phasors  $\underline{Z}_C$ ,  $\underline{Z}_L$  and  $\underline{Z}_R$  in a diagram.  
Choose an appropriate scaling factor and write it down.

Result

4. Calculate the current  $\underline{I}$ .

Solution

SS10...

$$\begin{aligned} Z &= \frac{\hat{U}}{\hat{I}} \quad \hat{I} = \frac{\hat{U}}{Z} \end{aligned}$$

With  $I = \frac{1}{\sqrt{2}} \cdot \hat{I}$ :

$$\frac{1}{\sqrt{2}} \cdot \frac{\hat{U}}{Z} = \frac{1}{\sqrt{2}} \cdot \frac{3.0 \text{ V}}{19.28 \text{ } \Omega}$$

Final result

$$I = 107 \text{ mA}$$

From:  
<https://wiki.mexle.te.hs-heilbronn.de/> - MEXLE Wiki

Permanent link:  
[https://wiki.mexle.te.hs-heilbronn.de/electrical\\_engineering\\_1/task\\_kricv9fh7haauo6q\\_with\\_calculation?rev=1676178192](https://wiki.mexle.te.hs-heilbronn.de/electrical_engineering_1/task_kricv9fh7haauo6q_with_calculation?rev=1676178192)

Last update: **2023/02/12 06:03**

