

task_pdkggtyexxy1ktu3_with_calculation

Student Group

First Name	Surname	Matrikel Nr.

Table of Contents

complex impedance, exam ee1 WS2022

Exercise 1.1 : Impedances at Frequencies

(written test, approx. 18% of a 60-minute written test, WS2022)

Calculate the **resistor values** which have to be used the following circuits.

1. A resistor R_1 shall have the same absolute value of the impedance like a capacitor $C_1=40 \text{ nF}$ at $f_1=4 \text{ MHz}$.

Solution

$$R_1 = |\underline{X}_{C1}| = \frac{1}{2\pi \cdot f \cdot C_1} = \frac{1}{2\pi \cdot 4 \text{ MHz} \cdot 40 \text{ nF}}$$

Final result

$$R_1 = 1.00 \text{ } \Omega$$

2. A RL series circuit with $L_2=4.7 \text{ } \mu\text{H}$, where an AC voltage source of $U_2=1.0 \text{ V}$ with $f_2=450 \text{ kHz}$ generates a current $I_2=60 \text{ mA}$.

Solution

Series circuit means that the current is constant on every component.

The equivalent impedance for R and L combined is given by
$$\frac{\underline{U}}{\underline{I}} = R_2 + \underline{X}_{L2} = R_2 + j \cdot \omega L$$
 Since $j \cdot \omega L$ is perpendicular to R_2 this can be simplified to:
$$|\frac{\underline{U}}{\underline{I}}|^2 = |R_2 + j \cdot \omega L|^2 = R_2^2 + (\omega L)^2$$

This can be rearranged to get R_2 :
$$R_2 = \sqrt{\left(\frac{U}{I}\right)^2 - X_{L2}^2} = \sqrt{\left(\frac{1\text{V}}{60\text{mA}}\right)^2 - (2\pi \cdot 450\text{kHz} \cdot 4.7 \text{ } \mu\text{H})^2}$$

Final result

$$R_2 = 10.0 \text{ } \Omega$$

3. A RC parallel circuit with $C_3 = 4.7 \text{ nF}$ on an AC current source ($I_{3S} = 1.3 \text{ A}$, $f_3 = 200 \text{ kHz}$), which generates a current of $I_{3R} = 1.0 \text{ A}$ through R_3 .

Solution

Parallel circuit means that the voltage is the same on R_3 and C_3 :

$$\underline{U}_3 = R_3 \cdot \underline{I}_{3R} = -j \cdot X_{3C} \cdot \underline{I}_{3C}$$
 So it gets clear, that $\underline{I}_{3R}$ is perpendicular to $\underline{I}_{3C}$ (It has to, since R_3 is perpendicular to $-j \cdot X_{3C}$, too). Therefore, the resulting current of the parallel circuit is given as:

$$\underline{I}_3 = \underline{I}_{3R} + \underline{I}_{3C} \quad || \quad |\underline{I}_3|^2 = |\underline{I}_{3R}|^2 + |\underline{I}_{3C}|^2 \quad || \quad \underline{I}_3 = \sqrt{|\underline{I}_{3R}|^2 + |\underline{I}_{3C}|^2}$$

Back on the first formula:

$$R_3 \cdot \underline{I}_{3R} = X_{3C} \cdot \underline{I}_{3C} \quad || \quad R_3 = X_{3C} \cdot \frac{|\underline{I}_{3C}|}{|\underline{I}_{3R}|} \quad || \quad = \frac{1}{2\pi \cdot f \cdot C_3} \cdot \frac{\sqrt{|\underline{I}_3|^2 - |\underline{I}_{3R}|^2}}{|\underline{I}_{3R}|}$$

Final result

$$R_3 = 70.0 \, \Omega$$

From:
<https://wiki.mexle.te.hs-heilbronn.de/> - MEXLE Wiki

Permanent link:
https://wiki.mexle.te.hs-heilbronn.de/electrical_engineering_1/task_pdkggyexxy1ktu3_with_calculation?rev=1676178203

Last update: 2023/02/12 06:03

