task_x357drkaqv84jnsc_with_calculation

Student Group

First Name	Surname	Matrikel Nr.

Table of Contents

exam ee1 WS2022

Exercise 1.1 : Pure Resistor Network Simplification

(written test, approx. 13 % of a 60-minute written test, WS2022)

The following circuit with $R_1=200 ~\Omega$, $R_2=R_3=100 ~\Omega$ and the switch S is given.

1. The switch shall now be open. Calculate the equivalent resistance R_{eq} between A and B.

Solution

> With the switch open the resistor R_3 dies not take part into the resulting resistor.



The equivalent resistor is given by a parallel configuration of resistors in series: \begin{align*} R_{eq} &= (R_2 + R_1 + R_1)||(R_2 + R_2)\\ R_{eq} &= (100 ~\Omega + 200 ~\Omega + 200 ~\Omega)&&||(100 ~\Omega + 100 ~\Omega) &&\\ R_{eq} &= (500 ~\Omega)&&||(200 ~\Omega)&&\\ R_{eq} &= {{500 ~\Omega \cdot 200 ~\Omega }\over{500 ~\Omega + 200 ~\Omega}}&&\\ \end{align*}

Final result

\begin{align*} R_{eq} &= 142.8 ~\Omega \\ \end{align*}

2. The switch shall now be closed. Calculate the equivalent resistance R_{eq} between A and B.

Solution

Now a wye-delta transformation is necessary.



Since $R_2=R_3$ and based on the equations for the transformation, the transformed R_Y is given as: \begin{align*} R_{Y} &= {{R_2 \cdot R_2}\over{R_2 + R_2 + R_2}} \\ &= {{(100 ~\Omega)^2}\over{3 \cdot 100 ~\Omega}} \\ &= {{1}\over{3}} \cdot 100 ~\Omega = 33.33 ~\Omega \end{align*}

The equivalent resistor is given by a parallel configuration of resistors in series: \begin{align*} R_{eq} &= R_Y + (R_Y + R_1 + R_1)||(R_Y + R_2)\\ R_{eq} &= 33.33 ~\Omega + (33.33 ~\Omega + 400 ~\Omega)||(33.33 ~\Omega + 100 ~\Omega)\\ \end{align*}

Final result

\begin{align*} R_{eq} &= 135.3 ~\Omega \\ \end{align*}

From:
https://wiki.mexle.te.hs-heilbronn.de/ - **MEXLE Wiki**

Permanent link:
https://wiki.mexle.te.hs-heilbronn.de/electrical_engineering_1/task_x357drkaqv84jnsc_with_calculation?rev=1680081991

Last update: **2023/03/29 11:26**