

# task\_x357drkaqv84jnc\_with\_calculation

## Student Group

| First Name | Surname | Matrikel Nr. |
|------------|---------|--------------|
|            |         |              |
|            |         |              |
|            |         |              |

## Table of Contents

Exercise E1 Pure Resistor Network Simplification (written test, approx. 13 % of a 60-minute  
written test, WS2022) ..... 2

## exam ee1 WS2022


### Exercise E1 Pure Resistor Network Simplification (written test, approx. 13 % of a 60-minute written test, WS2022)

The following shall now be done: Calculate the equivalent resistance  $R_{\text{eq}}$  between the terminals A and B. The switch shall now be open. Calculate the equivalent resistance  $R_{\text{eq}}$  between the terminals A and B.

Solution

$$R_{\text{eq}} = 133.8 \, \Omega$$

Now a wye-delta transformation is necessary.




Since  $R_2 = R_3$  and based on the equations for the transformation, the transformed  $R_Y$  is given as: 
$$R_Y = \frac{R_2 \cdot R_2}{R_2 + R_2 + R_2} = \frac{(100 \, \Omega)^2}{3 \cdot 100 \, \Omega} = \frac{1}{3} \cdot 100 \, \Omega = 33.33 \, \Omega$$

The equivalent resistor is given by a parallel configuration of resistors in series:

$$R_{\text{eq}} = R_Y + (R_Y + R_1 + R_1) \parallel (R_Y + R_2) \parallel R_{\text{eq}} = 33.33 \, \Omega + (33.33 \, \Omega + 400 \, \Omega) \parallel (33.33 \, \Omega + 100 \, \Omega)$$

.. The switch shall now be open. Calculate the equivalent resistance  $R_{\text{eq}}$  between the terminals A and B.

Solution



The equivalent resistor is given by a parallel configuration of resistors in series:

$$R_{\text{eq}} = (R_2 + R_1 + R_1) \parallel (R_2 + R_2) \parallel R_{\text{eq}} = (100 \sim \Omega + 200 \sim \Omega + 200 \sim \Omega) \parallel (100 \sim \Omega + 100 \sim \Omega) \parallel R_{\text{eq}} = (500 \sim \Omega) \parallel (200 \sim \Omega) \parallel R_{\text{eq}} = \frac{500 \sim \Omega \cdot 200 \sim \Omega}{500 \sim \Omega + 200 \sim \Omega}$$

From:  
<https://wiki.mexle.te.hs-heilbronn.de/> - MEXLE Wiki

Permanent link:  
[https://wiki.mexle.te.hs-heilbronn.de/electrical\\_engineering\\_1/task\\_x357drkaqv84jnc\\_with\\_calculation?rev=1680388284](https://wiki.mexle.te.hs-heilbronn.de/electrical_engineering_1/task_x357drkaqv84jnc_with_calculation?rev=1680388284)

Last update: 2023/04/02 00:31

