

Exam Winter Semester 2022

Student Group

First Name	Surname	Matrikel Nr.

Table of Contents


Exercise E1 Equivalent linear Source (written test, approx. 14 % of a 60-minute written test, WS2022)	3
Exercise E1 Temperature-dependent Resistance (written test, approx. 6 % of a 60-minute written test, WS2022)	6
Exercise E1 Analyzing complex Impedances (written test, approx. 14 % of a 60-minute written test, WS2022)	7
Exercise E1 Complex Impedance Circuit (written test, approx. 15 % of a 60-minute written test, WS2022)	7
Exercise E1 Impedances at different Frequencies (written test, approx. 18 % of a 60-minute written test, WS2022)	10
Exercise E1 Resistance of a Wire by Resistivity (written test, approx. 6 % of a 60-minute written test, WS2022)	10
Exercise E1 Charging Capacitors (written test, approx. 16 % of a 60-minute written test, WS2022)	11
Exercise E1 Pure Resistor Network Simplification (written test, approx. 13 % of a 60-minute written test, WS2022)	12
Exercise E4 Equivalent linear Source (written test, approx. 14 % of a 60-minute written test, WS2022)	14
Exercise E2 Temperature-dependent Resistance (written test, approx. 6 % of a 60-minute written test, WS2022)	18
Exercise E6 Analyzing complex Impedances (written test, approx. 14 % of a 60-minute written test, WS2022)	19
Exercise E8 Complex Impedance Circuit (written test, approx. 15 % of a 60-minute written test, WS2022)	19
Exercise E7 Impedances at different Frequencies (written test, approx. 18 % of a 60-minute written test, WS2022)	22
Exercise E1 Resistance of a Wire by Resistivity (written test, approx. 6 % of a 60-minute written test, WS2022)	22
Exercise E5 Charging Capacitors (written test, approx. 16 % of a 60-minute written test,	

WS2022)	23
Exercise E3 Pure Resistor Network Simplification (written test, approx. 13 % of a 60-minute written test, WS2022)	24

Exercise E1 Equivalent linear Source (written test, approx. 14 % of a 60-minute written test, WS2022)

The circuit in the following has to be simplified.
Result


$$\begin{aligned} U_{\text{S}} &= U_{\text{AB}} = 4.5 \text{ V} \\ R_{\text{i}} &= R_{\text{AB}} = 6 \text{ } \Omega \end{aligned}$$




Calculated the internal resistance R_{i} and the source voltage U_{S} of an equivalent linear voltage source on the connectors A and B .
 $R_1 = 5.0 \text{ } \Omega$, $U_2 = 6.0 \text{ V}$, $R_3 = 10 \text{ } \Omega$, $I_4 = 4.2 \text{ A}$, $R_5 = 10 \text{ } \Omega$, $R_6 = 7.5 \text{ } \Omega$, $R_7 = 15 \text{ } \Omega$ Use equivalent sources in order to simplify the circuit!

Solution

The best thing is to re-think the wiring like rubber bands and adjust them:



The linear voltage source of U_2 and R_1 can be transformed into a current source $I_2 = \frac{U_2}{R_1}$ and R_1 :



Now a lot of them can be combined. The resistors R_1 , R_3 , R_5 are in parallel, like also I_2 and I_4 :

$$R_{135} = R_1 || R_3 || R_5$$

$$I_{24} = I_2 - I_4 = \frac{U_2}{R_1} - I_4$$

The resulting circuit can again be transformed:



Here, the U_{24} is calculated by I_{24} as the following:

$$U_{24} = I_{24} \cdot R_{135}$$

$$U_{24} = R_{135} \cdot I_{24} \quad \&= \left(\frac{U_2}{R_1} - I_4 \right) \cdot R_1 \parallel R_3 \parallel R_5$$

On the right side of the last circuit, there is a voltage divider given by R_{135} , R_6 , and R_7 .

Therefore the voltage between A and B is given as:

$$U_{AB} = U_{24} \cdot \frac{R_7}{R_6 + R_7 + R_1 \parallel R_3 \parallel R_5} \quad \&= \left(\frac{U_2}{R_1} - I_4 \right) \cdot \frac{R_7 \cdot R_1 \parallel R_3 \parallel R_5}{R_6 + R_7 + R_1 \parallel R_3 \parallel R_5}$$

For the internal resistance R_i the ideal voltage source is substituted by its resistance ($=0\Omega$, so a short-circuit):

$$R_{AB} = R_7 \parallel (R_6 + R_1 \parallel R_3 \parallel R_5)$$

with $R_1 \parallel R_3 \parallel R_5 = 5\Omega \parallel 10\Omega \parallel 10\Omega = 5\Omega \parallel 5\Omega = 2.5\Omega$:

$$U_{AB} = \frac{6.0\text{V}}{5.0\Omega} - 4.2\Omega \cdot \frac{15\Omega \cdot 2.5\Omega}{7.5\Omega + 15\Omega + 2.5\Omega} \quad R_{AB} = 15\Omega \parallel (7.5\Omega + 2.5\Omega)$$

Exercise E1 Temperature-dependent Resistance (written test, approx. 6 % of a 60-minute written test, WS2022)

2. According to question 2, the effective resistance is not given, but can be identified. Result: $R_{eff} = 15\Omega$ at 25°C and 2.5Ω at 0°C for your answer.

Its temperature coefficients are: $\alpha = 0.01\text{K}^{-1}$ and $\beta = 71 \cdot 10^{-6}\text{K}^{-2}$

Result

The temperature inside the refrigeration system can reach down to -40°C .

$$R = 6.5\text{k}\Omega \quad \text{at } -40^\circ\text{C}$$

The power transfer is reduced by a factor of 10 and the heat flow is reduced by a factor of 10. Therefore, a solution is to use a heat exchanger.

Therefore, with constant U and increasing R the power decreases. Ten times more resistance decreases the heat flow to one-tenth.

$$R = R_0 \cdot (1 + \alpha \cdot \Delta T + \beta \cdot \Delta T^2) \quad | \quad \Delta T = T_{\text{end}} - T_{\text{start}} \\ R = 10\text{k}\Omega \cdot \left(1 + 0.01\text{K}^{-1} \cdot (-40^\circ\text{C} - 25^\circ\text{C}) + 71 \cdot 10^{-6}\text{K}^{-2} \cdot (-40^\circ\text{C} - 25^\circ\text{C})^2 \right)$$

Exercise E1 Analyzing complex Impedances**(written test, approx. 14 % of a 60-minute written test, WS2022)**

2. Calculate the complex impedance $\underline{Z}$ of the circuit shown in the figure. The components R and X_L shall be given.

After analysis, the full bridge circuit can be simplified to a series circuit. The equivalent circuit is shown in the figure. The impedance $\underline{Z}$ is given by:

.. Calculate the physical values of the two components.

Solution: $R = 10 \Omega$, $X_L = 10 \Omega$, $\varphi = 45^\circ$

Solution

$$\underline{I} = \frac{\underline{U}}{\underline{Z}} \quad \underline{U} = 50 \text{ V} \quad \underline{Z} = R + jX_L = 10 + j10 \Omega$$

The voltage U is given by $U = 50 \text{ V}$. The impedance Z is given by $Z = R + jX_L = 10 + j10 \Omega$. The current I is given by $I = \frac{U}{Z} = \frac{50}{10 + j10} = 4.68 \angle -45^\circ \text{ A}$.

Therefore, the component R is $R = 10 \Omega$ and the component X_L is $X_L = 10 \Omega$.

The phase φ is given by $\varphi = \arctan\left(\frac{X_L}{R}\right) = \arctan\left(\frac{10}{10}\right) = 45^\circ$.

With the complex part $\underline{Z} = 10 + j10 \Omega$, the physical values are $R = 10 \Omega$ and $X_L = 10 \Omega$.

The phase φ is given by $\varphi = \arctan\left(\frac{X_L}{R}\right) = \arctan\left(\frac{10}{10}\right) = 45^\circ$.

Exercise E1 Complex Impedance Circuit**(written test, approx. 15 % of a 60-minute written test, WS2022)**

2. Calculate the complex impedance $\underline{Z}$ of the circuit shown in the figure. The components R and X_L shall be given. The voltage source $u(t) = 3.0 \sin(2\pi \cdot 15 \cdot t) \text{ V}$ is connected to a series circuit of an inductor of $330 \mu\text{H}$ and a capacitor of $0.22 \mu\text{F}$.

Solution: $R = 10 \Omega$, $X_L = 10 \Omega$, $\varphi = 45^\circ$

Result


.. Draw the circuit diagram of the bridge circuit. The components, voltages, and currents.

$$\underline{Z} = \frac{\underline{U}}{\underline{I}} \quad \underline{U} = 3.0 \text{ V} \quad \underline{I} = 1.92 \angle -45^\circ \text{ A}$$

Therefore, the component R is $R = 10 \Omega$ and the component X_L is $X_L = 10 \Omega$.

With the complex part $\underline{Z} = 10 + j10 \Omega$, the physical values are $R = 10 \Omega$ and $X_L = 10 \Omega$.

The phase φ is given by $\varphi = \arctan\left(\frac{X_L}{R}\right) = \arctan\left(\frac{10}{10}\right) = 45^\circ$.



Exercise E1 Impedances at different Frequencies

(written test, approx. 18 % of a 60-minute written test, WS2022)

2. A series circuit consists of a resistor with $R_1 = 1.00 \text{ k}\Omega$ and a capacitor with $C_1 = 40 \text{ nF}$. The voltage across the resistor is $U_R = 10.0 \text{ V}$ at a frequency of $f = 4 \text{ MHz}$. Calculate the absolute value of the impedance of the capacitor Z_C at $f = 4 \text{ MHz}$.

Solution

$$Z_C = \frac{1}{\omega C_1} = \frac{1}{2\pi \cdot 4 \cdot 10^6 \cdot 40 \cdot 10^{-9}} = 1.00 \text{ k}\Omega$$

$$Z_C = \frac{1}{\omega C_1} = \frac{1}{2\pi \cdot 4 \cdot 10^6 \cdot 40 \cdot 10^{-9}} = 1.00 \text{ k}\Omega$$

A series circuit means that the current is constant on every component.

The equivalent impedance for R_1 and C_1 combined is given by

$$Z_{\text{eq}} = \sqrt{R_1^2 + X_{C1}^2} = \sqrt{R_1^2 + \left(\frac{1}{\omega C_1}\right)^2} = \sqrt{1.00^2 + 1.00^2} = 1.41 \text{ k}\Omega$$

$$I = \frac{U_R}{R_1} = \frac{10.0 \text{ V}}{1.00 \text{ k}\Omega} = 10.0 \text{ mA}$$

$$U_{\text{eq}} = I \cdot Z_{\text{eq}} = 10.0 \text{ mA} \cdot 1.41 \text{ k}\Omega = 14.1 \text{ V}$$

$$Z_C = \frac{U_C}{I} = \frac{U_{\text{eq}}}{I} = \frac{14.1 \text{ V}}{10.0 \text{ mA}} = 1.41 \text{ k}\Omega$$

$$Z_C = \frac{1}{\omega C_1} = \frac{1}{2\pi \cdot 4 \cdot 10^6 \cdot 40 \cdot 10^{-9}} = 1.00 \text{ k}\Omega$$

$$Z_C = \frac{1}{\omega C_1} = \frac{1}{2\pi \cdot 4 \cdot 10^6 \cdot 40 \cdot 10^{-9}} = 1.00 \text{ k}\Omega$$

$$Z_C = \frac{1}{\omega C_1} = \frac{1}{2\pi \cdot 4 \cdot 10^6 \cdot 40 \cdot 10^{-9}} = 1.00 \text{ k}\Omega$$

$$Z_C = \frac{1}{\omega C_1} = \frac{1}{2\pi \cdot 4 \cdot 10^6 \cdot 40 \cdot 10^{-9}} = 1.00 \text{ k}\Omega$$

$$Z_C = \frac{1}{\omega C_1} = \frac{1}{2\pi \cdot 4 \cdot 10^6 \cdot 40 \cdot 10^{-9}} = 1.00 \text{ k}\Omega$$

Exercise E1 Resistance of a Wire by Resistivity

(written test, approx. 6 % of a 60-minute written test, WS2022)

2. A heating element made of nichrome wire with a diameter of $d = 0.5 \text{ mm}$ and a length of $L = 3 \text{ m}$ is used for heating. The power dissipation (= heat flow) of $P = 40 \text{ W}$ is necessary.

Calculate the current I needed for heating elements.

The Nichrome wire has a resistivity of $\rho = 1.10 \cdot 10^{-6} \text{ }\Omega \cdot \text{m}$.

The heating element is 3 m long and has a diameter of 0.5 mm .

Calculate the resistance R of the heating element.

Solution

$$P = U \cdot I = R \cdot I^2 \quad \rightarrow \quad I = \sqrt{\frac{P}{R}}$$

$$\sqrt{\frac{P}{R}} = \sqrt{\frac{40 \cdot W}{0.33 \cdot \Omega}} \quad \text{align*}$$

$$\begin{aligned} R &= \rho \cdot \frac{l}{A} \quad \& \quad | \quad \text{with } A = r^2 \cdot \pi = \\ \frac{1}{4} d^2 \cdot \pi \quad \& \quad R &= \rho \cdot \frac{4 \cdot l}{d^2 \cdot \pi} \quad \& \quad R = \\ 1.10 \cdot 10^{-6} \cdot \Omega \cdot \frac{4 \cdot 3 \cdot m}{(3.57 \cdot 10^{-3} \cdot m)^2 \cdot \pi} \quad \& \quad \end{aligned} \quad \text{align*}$$

Exercise E1 Charging Capacitors


(written test, approx. 16 % of a 60-minute written test, WS2022)

The circuit (without the light bulb) also is the circuit of Exercise 2. The voltage across the capacitor is again 0 V at the moment $t_0 = 0 \text{ s}$ when the switch S_1 is closed. Calculate the voltage $u_c(t_2)$ across the capacitor at $t_2 = 1 \text{ ms}$ after closing the switch.

Solution Hint: To solve this, first create an equivalent linear voltage source from U , R_1 , and R_2 .

Solution The ideal voltage source $U = 12 \text{ V}$ is in series with the resistor $R_1 = 20 \Omega$. The voltage $u_c(t)$ is independent of this series combination.

On an alternative view, one can try to create an equivalent linear voltage source again. Then, the internal resistance is given by substituting the ideal voltage source is again short-circuiting S_2 .




The circuit contains a voltage source $U = 12 \text{ V}$, a switch S_1 , a resistor of $R_1 = 20 \Omega$ and a capacitor of $C = 100 \mu\text{F}$.

The switch S_2 to an additional consumer R_2 will be considered to be open for the first tasks. At the moment $t_0 = 0 \text{ s}$ the switch S_1 is closed, the voltage across the capacitor is $u_c(t_0) = 0 \text{ V}$.

.. First do not consider the light bulb - it is not connected to the RC circuit. Calculate the point of time t_1 when $u_c(t_1) = 0.5 \cdot U$.

Solution



An equivalent linear voltage source can be given with U_s , R_1 , and R_B as seen in yellow.

Therefore, the voltage of the equivalent linear voltage source is: $U_s = U \cdot \frac{R_B}{R_1 + R_B} = \frac{1}{2} \cdot U$. The internal resistance is given by substituting the ideal voltage source with its resistance ($= 0 \Omega$, short-circuit).

$$R_i = R_1 \parallel R_B = 10 \Omega$$

$$u_c(t_2) = U_s \cdot (1 - e^{-t_2/(R_i \cdot C)}) = \frac{1}{2} \cdot U$$

So, here only R_1 and C gives the time constant: $\tau = R_1 \cdot C$

The following formula describes the time course of $u_c(t)$ which has to be $u_c(t_1) = 0.5 \cdot U$:

$$u_c(t) = U \cdot (1 - e^{-t/\tau}) = 0.5 \cdot U$$

It has to be rearranged to t :

$$(1 - e^{-t/\tau}) = 0.5$$

$$e^{-t/\tau} = 0.5 \quad \ln(0.5) = -t/\tau \quad t = \tau \cdot \ln(0.5) = R_1 \cdot C \cdot \ln(0.5)$$


Exercise E1 Pure Resistor Network Simplification (written test, approx. 13 % of a 60-minute written test, WS2022)

The following shall be simplified with $R_1 = 200 \Omega$, $R_2 = 100 \Omega$, $R_3 = 150 \Omega$, $R_4 = 100 \Omega$ and the voltage $U = 10 \text{ V}$.
Result given: R_B .

Solution

$$R_{\text{eq}} = 132.8 \Omega$$

Now a wye-delta transformation is necessary.



Since $R_2 = R_3$ and based on the equations for the transformation, the transformed R_Y is given as:


$$R_Y = \frac{R_2 \cdot R_2}{R_2 + R_2 + R_2} = \frac{(100 \, \Omega)^2}{3 \cdot 100 \, \Omega} = \frac{1}{3} \cdot 100 \, \Omega = 33.33 \, \Omega$$

The equivalent resistor is given by a parallel configuration of resistors in series:

$$R_{\text{eq}} = R_Y + (R_Y + R_1 + R_1) \parallel (R_Y + R_2) \parallel R_{\text{eq}} = 33.33 \, \Omega + (33.33 \, \Omega + 400 \, \Omega) \parallel (33.33 \, \Omega + 100 \, \Omega)$$

1. The switch shall now be open. Calculate the equivalent resistance R_{eq} between A and B .

Solution



The equivalent resistor is given by a parallel configuration of resistors in series:

$$R_{\text{eq}} = (R_2 + R_1 || R_3) || (R_4 + R_5)$$

$$R_{\text{eq}} = (100 \, \Omega + 200 \, \Omega || 200 \, \Omega) || (100 \, \Omega + 100 \, \Omega)$$

$$R_{\text{eq}} = (500 \, \Omega) || (200 \, \Omega)$$


$$R_{\text{eq}} = \frac{500 \, \Omega \cdot 200 \, \Omega}{500 \, \Omega + 200 \, \Omega}$$

Exercise E4 Equivalent linear Source (written test, approx. 14 % of a 60-minute written test, WS2022)

The circuit in the following has to be simplified.
Result

$$U_s = U_{AB} = 4.5 \, \text{V}$$


$$R_i = R_{AB} = 6 \, \Omega$$




Calculate the internal resistance R_{int} and the source voltage U_s of an equivalent linear voltage source on the connectors A and B. $\begin{aligned} R_1 &= 5.0 \, \Omega, \quad U_2 = 6.0 \, \text{V}, \quad R_3 = 10 \, \Omega, \quad I_4 = 4.2 \, \text{A}, \\ R_5 &= 10 \, \Omega, \quad R_6 = 7.5 \, \Omega, \quad R_7 = 15 \, \Omega \end{aligned}$ Use equivalent sources in order to simplify the circuit!

Solution

The best thing is to re-think the wiring like rubber bands and adjust them:



The linear voltage source of U_2 and R_1 can be transformed into a current source $I_2 = \frac{U_2}{R_1}$ and R_1 :



Now a lot of them can be combined. The resistors R_1 , R_3 , R_5 are in parallel, like also I_2 and I_4 :

$$R_{135} = R_1 || R_3 || R_5$$

$$I_{24} = I_2 - I_4 = \frac{U_{24}}{R_1} - I_4$$

The resulting circuit can again be transformed:



Here, the U_{24} is calculated by I_{24} as the following:

$$U_{24} = I_{24} \cdot R_{135} + I_4 \cdot R_1$$

$$U_{24} = R_{135} \cdot I_{24} \quad \&= \left(\frac{U_2}{R_1} - I_4 \right) \cdot R_1 \parallel R_3 \parallel R_5$$

On the right side of the last circuit, there is a voltage divider given by R_{135} , R_6 , and R_7 .

Therefore the voltage between \$A\$ and \$B\$ is given as:

$$U_{AB} = U_{24} \cdot \frac{R_7}{R_6 + R_7 + R_1 \parallel R_3 \parallel R_5} \quad \&= \left(\frac{U_2}{R_1} - I_4 \right) \cdot \frac{R_7 \cdot R_1 \parallel R_3 \parallel R_5}{R_6 + R_7 + R_1 \parallel R_3 \parallel R_5}$$

For the internal resistance R_i the ideal voltage source is substituted by its resistance ($=0\Omega$, so a short-circuit):

$$R_{AB} = R_7 \parallel (R_6 + R_1 \parallel R_3 \parallel R_5)$$

with $R_1 \parallel R_3 \parallel R_5 = 5\Omega \parallel 10\Omega \parallel 10\Omega = 5\Omega \parallel 5\Omega = 2.5\Omega$:

$$U_{AB} = \frac{6.0\text{V}}{5.0\Omega} - 4.2\Omega \cdot \frac{15\Omega \cdot 2.5\Omega}{7.5\Omega + 15\Omega + 2.5\Omega} \quad R_{AB} = 15\Omega \parallel (7.5\Omega + 2.5\Omega)$$

Exercise E2 Temperature-dependent Resistance (written test, approx. 6 % of a 60-minute written test, WS2022)

2. According to question 2, the effect of temperature on the resistance of a thermistor can be described by the Steinhart-Hart equation:

Resistance of a thermistor (R) in Ω as a function of temperature (T) in $^\circ\text{C}$ is given by:

Its temperature coefficients are: $\alpha = 0.01 \text{ K}^{-1}$ and $\beta = 71 \cdot 10^{-6} \text{ K}^{-2}$.

Result

The temperature inside the refrigeration system can reach down to -40°C .

$$R = 6.5 \text{ k}\Omega \quad \text{at } T = -40^\circ\text{C}$$

The power transfered to the thermistor is $P = \frac{U^2}{R}$ and $Q = P \cdot t$. Therefore, a solution is to use a heat sink to cool the thermistor.

Therefore, with constant U and increasing R the power decreases. Ten times more resistance decreases the heat flow to one-tenth.

$$R = R_0 \cdot (1 + \alpha \cdot \Delta T + \beta \cdot \Delta T^2) \quad \& \quad R = 10 \text{ k}\Omega \cdot \left(1 + 0.01 \cdot (-40 - 25) + 71 \cdot 10^{-6} \cdot (-40 - 25)^2 \right)$$

Exercise E6 Analyzing complex Impedances

(written test, approx. 14 % of a 60-minute written test, WS2022)

2. Calculate the complex impedance $\underline{Z}$ of the circuit shown in the figure. The components R and X_L shall be given.

After analysis, the full bridge network can be impedance, and be extracted and begin to align in phase. The full bridge network can be impedance, and be extracted and begin to align in phase. The full bridge network can be impedance, and be extracted and begin to align in phase.

.. Calculate the physical values of the two components.

Solution
$$\underline{Z} = \frac{\underline{U}}{\underline{I}} = \frac{10 \text{ V}}{0.2 \text{ A}} = 50 \text{ } \Omega$$

Solution

$$\underline{I} = \frac{\underline{U}}{\underline{Z}} = \frac{10 \text{ V}}{50 \text{ } \Omega} = 0.2 \text{ A}$$

 The voltage $\underline{U}$ is the sum of the voltage across the resistor R and the voltage across the inductor X_L .

$$\underline{U} = \underline{U}_R + \underline{U}_L$$

$$\underline{U} = \underline{I} \cdot \underline{Z} = \underline{I} \cdot (R + jX_L)$$

$$10 \text{ V} = 0.2 \text{ A} \cdot (R + jX_L)$$

$$50 \text{ } \Omega = R + jX_L$$

 The real part of the impedance is the resistance R , and the imaginary part is the inductive reactance X_L .

$$R = 50 \text{ } \Omega$$

$$X_L = 0 \text{ } \Omega$$

 With the complex part $\underline{Z}$ and the physical values R and X_L , the impedance $\underline{Z}$ can be calculated as $\underline{Z} = R + jX_L$.

$$\underline{Z} = 50 \text{ } \Omega$$

 The phase φ can be calculated as $\varphi = \arctan \left(\frac{X_L}{R} \right)$.

$$\varphi = \arctan \left(\frac{0}{50} \right) = 0 \text{ rad}$$

Exercise E8 Complex Impedance Circuit

(written test, approx. 15 % of a 60-minute written test, WS2022)

2. Calculate the complex impedance $\underline{Z}$ of the circuit shown in the figure. The components R and X_L shall be given. The voltage source $u(t) = 3.0 \text{ V} \cdot \sin(2\pi \cdot 15 \text{ kHz} \cdot t)$ is connected to a series circuit of a resistor R and an inductor L .

Solution
$$\underline{Z} = \frac{\underline{U}}{\underline{I}} = \frac{3.0 \text{ V}}{0.2 \text{ A}} = 15 \text{ } \Omega$$

Result

.. Draw the circuit diagram of the bridge network. The components, voltages, and currents.

$$\underline{Z} = \frac{\underline{U}}{\underline{I}} = \frac{3.0 \text{ V}}{0.2 \text{ A}} = 15 \text{ } \Omega$$

$$\underline{Z} = R + jX_L$$


$$15 \text{ } \Omega = R + jX_L$$

With the complex part $\underline{Z}$ and the physical values R and X_L , the impedance $\underline{Z}$ can be calculated as $\underline{Z} = R + jX_L$.

$$\underline{Z} = 15 \text{ } \Omega$$

 The phase φ can be calculated as $\varphi = \arctan \left(\frac{X_L}{R} \right)$.

$$\varphi = \arctan \left(\frac{0}{15} \right) = 0 \text{ rad}$$



Exercise E7 Impedances at different Frequencies

(written test, approx. 18 % of a 60-minute written test, WS2022)

2. A series circuit with two resistors $R_1 = 1.00 \text{ k}\Omega$ and $R_2 = 10.0 \text{ k}\Omega$ is connected to an AC voltage source of $U = 230 \text{ V}$ at $f = 50 \text{ Hz}$. A capacitor $C = 40 \text{ nF}$ is connected in parallel with R_2 . Calculate the total impedance Z of the circuit.

Solution

$$Z = \sqrt{R_1^2 + \left(\frac{R_2}{\sqrt{1 + (\omega C R_2)^2}} \right)^2}$$

$$Z = \sqrt{1.00^2 + \left(\frac{10.0}{\sqrt{1 + (2\pi \cdot 50 \cdot 40 \cdot 10^{-9} \cdot 10.0 \cdot 10^3)^2}} \right)^2}$$

A series circuit means that the current is constant on every component.

The equivalent impedance for R_1 and R_2 combined is given by

Parallel circuit means that the voltage is the same on R_1 and R_2 .

$$\frac{1}{Z} = \frac{1}{R_1} + \frac{1}{R_2}$$

$$Z = \frac{R_1 R_2}{R_1 + R_2}$$

Since R_1 and R_2 are in parallel, the voltage across them is the same. The current through R_1 is $I_1 = \frac{U}{R_1}$ and the current through R_2 is $I_2 = \frac{U}{R_2}$. The total current is $I = I_1 + I_2$.

$$I = \frac{U}{R_1} + \frac{U}{R_2} = U \left(\frac{1}{R_1} + \frac{1}{R_2} \right)$$

$$I = U \frac{R_1 + R_2}{R_1 R_2}$$

Therefore, the resulting current of the parallel circuit is given as:

$$I = \frac{U}{Z} = \frac{U}{R_1 R_2} (R_1 + R_2)$$

$$Z = \frac{R_1 R_2}{R_1 + R_2} = \frac{1.00 \text{ k}\Omega \cdot 10.0 \text{ k}\Omega}{1.00 \text{ k}\Omega + 10.0 \text{ k}\Omega} = 0.909 \text{ k}\Omega$$

Back to the first formula:
$$Z = \sqrt{R_1^2 + \left(\frac{R_2}{\sqrt{1 + (\omega C R_2)^2}} \right)^2}$$

$$Z = \sqrt{1.00^2 + \left(\frac{10.0}{\sqrt{1 + (2\pi \cdot 50 \cdot 40 \cdot 10^{-9} \cdot 10.0 \cdot 10^3)^2}} \right)^2}$$

$$Z = \sqrt{1.00^2 + \left(\frac{10.0}{\sqrt{1 + (2\pi \cdot 50 \cdot 40 \cdot 10^{-9} \cdot 10.0 \cdot 10^3)^2}} \right)^2}$$

$$Z = \sqrt{1.00^2 + \left(\frac{10.0}{\sqrt{1 + (2\pi \cdot 50 \cdot 40 \cdot 10^{-9} \cdot 10.0 \cdot 10^3)^2}} \right)^2}$$

$$Z = \sqrt{1.00^2 + \left(\frac{10.0}{\sqrt{1 + (2\pi \cdot 50 \cdot 40 \cdot 10^{-9} \cdot 10.0 \cdot 10^3)^2}} \right)^2}$$

Exercise E1 Resistance of a Wire by Resistivity

(written test, approx. 6 % of a 60-minute written test, WS2022)

2. A heating element made of nichrome wire with a diameter of $d = 0.5 \text{ mm}$ and a length of $L = 3 \text{ m}$ is connected to a power supply of $U = 230 \text{ V}$. Calculate the power dissipation P of the heating element.

Result: The power dissipation P of the heating element is $P = 40 \text{ W}$.

Calculate the current I flowing through the heating element.

The Nichrome wire has a resistivity of $\rho = 1.10 \cdot 10^{-6} \text{ }\Omega \cdot \text{m}$.

The heating element is $L = 3 \text{ m}$ long and has a diameter of $d = 0.5 \text{ mm}$.

Calculate the resistance R of the heating element.

Solution

$$P = U \cdot I = R \cdot I^2 \quad \rightarrow \quad I = \sqrt{\frac{P}{R}}$$

$$\sqrt{\frac{P}{R}} = \sqrt{\frac{40 \cdot W}{0.33 \cdot \Omega}} \quad \text{align*}$$

$$\begin{aligned} R &= \rho \cdot \frac{l}{A} \quad \& \quad | \quad \text{with } A = r^2 \cdot \pi = \\ \frac{1}{4} d^2 \cdot \pi \quad \& \quad R &= \rho \cdot \frac{4 \cdot l}{d^2 \cdot \pi} \quad \& \quad R = \\ 1.10 \cdot 10^{-6} \cdot \Omega \cdot \frac{4 \cdot 3 \cdot m}{(3.57 \cdot 10^{-3} \cdot m)^2 \cdot \pi} \quad \& \quad \end{aligned} \quad \text{align*}$$

Exercise E5 Charging Capacitors

(written test, approx. 16 % of a 60-minute written test, WS2022)

The circuit (without the light bulb) also is the circuit of Exercise 2. The charging of the capacitor is again described by the equation $u_C(t) = U \cdot (1 - e^{-t/\tau})$. The voltage across the capacitor is again 0 V at the moment $t_0 = 0 \text{ s}$ when the switch S_1 is closed. Calculate the voltage $u_C(t_2)$ across the capacitor at $t_2 = 1 \text{ ms}$ after closing the switch.


Solution To solve this, first create an equivalent linear voltage source from U , R_1 , and R_2 .

$$\Delta U = U \cdot \frac{R_2}{R_1 + R_2} = 12 \text{ V} \cdot \frac{20 \Omega}{20 \Omega + 20 \Omega} = 6 \text{ V}$$

Solution The ideal voltage source $\Delta U = 6 \text{ V}$ is in series with the resistor $R_1 = 20 \Omega$. The voltage $u_C(t)$ is independent of this series resistor R_1 .

$$u_C(t) = \Delta U \cdot (1 - e^{-t/\tau}) = 6 \text{ V} \cdot (1 - e^{-t/\tau})$$

On an alternative view, one can try to create an equivalent linear voltage source again. Then, the internal resistance is given by substituting the ideal voltage source is again short-circuiting S_2 . R_1




The circuit contains a voltage source $U = 12 \text{ V}$, a switch S_1 , a resistor of $R_1 = 20 \Omega$ and a capacitor of $C = 100 \mu\text{F}$.

The switch S_2 to an additional consumer R_2 will be considered to be open for the first tasks. At the moment $t_0 = 0 \text{ s}$ the switch S_1 is closed, the voltage across the capacitor is $u_C(t_0) = 0 \text{ V}$.

.. First do not consider the light bulb - it is not connected to the RC circuit.
 Calculate the point of time t_1 when $u_C(t_1) = 0.5 \cdot U$.

Solution



An equivalent linear voltage source can be given with U_s , R_1 , and R_B as seen in yellow.

Therefore, the voltage of the equivalent linear voltage source is: $U_s = U \cdot \frac{R_B}{R_1 + R_B} = \frac{1}{2} \cdot U$. The internal resistance is given by substituting the ideal voltage source with its resistance ($= 0 \Omega$, short-circuit).

$$R_i = R_1 \parallel R_B = 10 \Omega$$

$$u_c(t_2) = U_s \cdot (1 - e^{-t_2/(R_i \cdot C)}) = \frac{1}{2} \cdot U$$

So, here only R_1 and C gives the time constant: $\tau = R_1 \cdot C$

The following formula describes the time course of $u_c(t)$ which has to be $u_c(t_1) = 0.5 \cdot U$:
$$u_c(t) = U \cdot (1 - e^{-t/\tau}) = 0.5 \cdot U$$
 It has to be rearranged to
$$(1 - e^{-t/\tau}) = 0.5$$

$$e^{-t/\tau} = 0.5 \quad \ln(0.5) = -t/\tau \quad t = \tau \cdot \ln(0.5) = R_1 \cdot C \cdot \ln(0.5)$$


Exercise E3 Pure Resistor Network Simplification (written test, approx. 13 % of a 60-minute written test, WS2022)

The following shall be shown with $R_1 = 200 \Omega$, $R_2 = 100 \Omega$, $R_3 = 150 \Omega$, $R_4 = 100 \Omega$ and the voltage $U = 10 \text{ V}$.
Result given: R_B .

Solution

$$R_{\text{eq}} = 132.8 \Omega$$

Now a wye-delta transformation is necessary.



Since $R_2 = R_3$ and based on the equations for the transformation, the transformed R_Y is given as:


$$R_Y = \frac{R_2 \cdot R_2}{R_2 + R_2 + R_2} = \frac{(100 \, \Omega)^2}{3 \cdot 100 \, \Omega} = \frac{1}{3} \cdot 100 \, \Omega = 33.33 \, \Omega$$

The equivalent resistor is given by a parallel configuration of resistors in series:

$$R_{\text{eq}} = R_Y + (R_Y + R_1 + R_1) \parallel (R_Y + R_2) \parallel R_{\text{eq}} = 33.33 \, \Omega + (33.33 \, \Omega + 400 \, \Omega) \parallel (33.33 \, \Omega + 100 \, \Omega)$$

1. The switch shall now be open. Calculate the equivalent resistance R_{eq} between A and B .

Solution



The equivalent resistor is given by a parallel configuration of resistors in series:

$$R_{eq} = (R_2 + R_1 + R_1) || (R_2 + R_2) || (100 \sim \Omega + 200 \sim \Omega + 200 \sim \Omega) || (100 \sim \Omega + 100 \sim \Omega) || (500 \sim \Omega) || (200 \sim \Omega) || R_{eq} = \{ \{ 500 \sim \Omega \cdot 200 \sim \Omega \} \over {500 \sim \Omega + 200 \sim \Omega} \} ||$$

From:

<https://wiki.mexle.te.hs-heilbronn.de/> - MEXLE Wiki

Permanent link:

https://wiki.mexle.te.hs-heilbronn.de/electrical_engineering_1/ws2022_exam?rev=1680124779

Last update: **2023/03/29 23:19**

