

Exam Winter Semester 2022

Student Group

First Name	Surname	Matrikel Nr.

Table of Contents

Exercise E1 Resistance of a Wire by Resistivity (written test, approx. 6 % of a 60-minute written test, WS2022)	3
Exercise E1 Resistance of a Wire by Resistivity (written test, approx. 6 % of a 60-minute written test, WS2022)	3
Exercise E1 Temperature-dependent Resistance (written test, approx. 6 % of a 60-minute written test, WS2022)	3
Exercise E2 Temperature-dependent Resistance (written test, approx. 6 % of a 60-minute written test, WS2022)	4
Exercise E1 Pure Resistor Network Simplification (written test, approx. 13 % of a 60-minute written test, WS2022)	5
Exercise E3 Pure Resistor Network Simplification (written test, approx. 13 % of a 60-minute written test, WS2022)	6
Exercise E1 Equivalent linear Source (written test, approx. 14 % of a 60-minute written test, WS2022)	8
Exercise E4 Equivalent linear Source (written test, approx. 14 % of a 60-minute written test, WS2022)	12
Exercise E1 Charging Capacitors (written test, approx. 16 % of a 60-minute written test, WS2022)	16
Exercise E5 Charging Capacitors (written test, approx. 16 % of a 60-minute written test, WS2022)	17
Exercise E1 Analyzing complex Impedances (written test, approx. 14 % of a 60-minute written test, WS2022)	19
Exercise E6 Analyzing complex Impedances (written test, approx. 14 % of a 60-minute written test, WS2022)	19
Exercise E1 Impedances at different Frequencies (written test, approx. 18 % of a 60-minute written test, WS2022)	20
Exercise E7 Impedances at different Frequencies (written test, approx. 18 % of a 60-minute written test, WS2022)	20
Exercise E1 Complex Impedance Circuit (written test, approx. 15 % of a 60-minute written test, WS2022)	

test, WS2022)	21
Exercise E8 Complex Impedance Circuit (written test, approx. 15 % of a 60-minute written	
test, WS2022)	24

Exercise E1 Resistance of a Wire by Resistivity (written test, approx. 6 % of a 60-minute written test, WS2022)

A heating element made of solid nichrome wire with a cross-section of 1.80 mm^2 is used. The electric power dissipation (= heat flow) of $P=40 \text{ W}$ is necessary.

Determine the current I needed to operate the heating elements.

The Nichrome wire has a resistivity of $1.10 \cdot 10^{-6} \text{ } \Omega \text{ m}$.

The heating element is 3 m long and has a diameter of 3.57 mm .

∴ Calculate the resistance R of the heating element.

Solution

$$\begin{aligned} P &= U \cdot I = R \cdot I^2 \quad \rightarrow \quad I = \\ \sqrt{\frac{P}{R}} &= \sqrt{\frac{40 \text{ W}}{0.33 \text{ } \Omega}} \end{aligned}$$

$$\begin{aligned} R &= \rho \cdot \frac{l}{A} \quad | \quad \text{with } A = r^2 \cdot \pi = \\ \frac{1}{4} d^2 \cdot \pi \quad | \quad R &= \rho \cdot \frac{4 \cdot l}{d^2 \cdot \pi} \quad \& \quad R = \\ 1.10 \cdot 10^{-6} \text{ } \Omega \text{ m} \cdot \frac{4 \cdot 3 \text{ m}}{(3.57 \cdot 10^{-3} \text{ m})^2 \cdot \pi} \quad & \end{aligned}$$

Exercise E1 Resistance of a Wire by Resistivity (written test, approx. 6 % of a 60-minute written test, WS2022)

A heating element made of solid nichrome wire with a cross-section of 1.80 mm^2 is used. The electric power dissipation (= heat flow) of $P=40 \text{ W}$ is necessary.

Determine the current I needed to operate the heating elements.

The Nichrome wire has a resistivity of $1.10 \cdot 10^{-6} \text{ } \Omega \text{ m}$.

The heating element is 3 m long and has a diameter of 3.57 mm .

∴ Calculate the resistance R of the heating element.

Solution

$$\begin{aligned} P &= U \cdot I = R \cdot I^2 \quad \rightarrow \quad I = \\ \sqrt{\frac{P}{R}} &= \sqrt{\frac{40 \text{ W}}{0.33 \text{ } \Omega}} \end{aligned}$$

$$\begin{aligned} R &= \rho \cdot \frac{l}{A} \quad | \quad \text{with } A = r^2 \cdot \pi = \\ \frac{1}{4} d^2 \cdot \pi \quad | \quad R &= \rho \cdot \frac{4 \cdot l}{d^2 \cdot \pi} \quad \& \quad R = \\ 1.10 \cdot 10^{-6} \text{ } \Omega \text{ m} \cdot \frac{4 \cdot 3 \text{ m}}{(3.57 \cdot 10^{-3} \text{ m})^2 \cdot \pi} \quad & \end{aligned}$$

Exercise E1 Temperature-dependent Resistance

(written test, approx. 6 % of a 60-minute written test, WS2022)

2. A refrigerator, which has a temperature coefficient of performance of 2.5, has a resistance of $10 \text{ k}\Omega$ at 25°C . Your answer.

Its temperature coefficients are: $\alpha = 0.01 \text{ K}^{-1}$ and $\beta = 71 \text{ K}^{-2}$.

Result The temperature inside the refrigeration system can reach down to -40°C .

$$R = 6.5 \text{ k}\Omega$$

The power transfer resistor P is the output of the circuit and generates heat. Therefore, a solution is to use a heat sink to cool up the refrigeration system.

Therefore, with constant U and increasing R the power decreases. Ten times more resistance decreases the heat flow to one-tenth.

$$R = R_0 (1 + \alpha \Delta T + \beta \Delta T^2) \quad \text{with } \Delta T = T_{\text{end}} - T_{\text{start}} \\ R = 10 \text{ k}\Omega \cdot \left((1 + 0.01 \text{ K}^{-1} \cdot (-40^\circ\text{C} - 25^\circ\text{C}) + 71 \text{ K}^{-2} \cdot (-40^\circ\text{C} - 25^\circ\text{C})^2) \right)$$

Exercise E2 Temperature-dependent Resistance**(written test, approx. 6 % of a 60-minute written test, WS2022)**

2. A refrigerator, which has a temperature coefficient of performance of 2.5, has a resistance of $10 \text{ k}\Omega$ at 25°C . Your answer.

Its temperature coefficients are: $\alpha = 0.01 \text{ K}^{-1}$ and $\beta = 71 \text{ K}^{-2}$.

Result The temperature inside the refrigeration system can reach down to -40°C .

$$R = 6.5 \text{ k}\Omega$$

The power transfer resistor P is the output of the circuit and generates heat. Therefore, a solution is to use a heat sink to cool up the refrigeration system.

Therefore, with constant U and increasing R the power decreases. Ten times more resistance decreases the heat flow to one-tenth.

$$R = R_0 (1 + \alpha \Delta T + \beta \Delta T^2) \quad \text{with } \Delta T = T_{\text{end}} - T_{\text{start}} \\ R = 10 \text{ k}\Omega \cdot \left((1 + 0.01 \text{ K}^{-1} \cdot (-40^\circ\text{C} - 25^\circ\text{C}) + 71 \text{ K}^{-2} \cdot (-40^\circ\text{C} - 25^\circ\text{C})^2) \right)$$

Exercise E1 Pure Resistor Network Simplification


(written test, approx. 13 % of a 60-minute written test, WS2022)

The following shall now be closed and integrated, $R_2 = R_3 = 100 \Omega$ and the switch between R_3 and R_4 shall be open. Calculate the equivalent resistance R_{eq} between A and B .

Solution

$$R_{\text{eq}} = 133.8 \Omega$$

Now a wye-delta transformation is necessary.



Since $R_2 = R_3$ and based on the equations for the transformation, the transformed R_Y is given as:


$$R_Y = \frac{R_2 \cdot R_3}{R_2 + R_3} = \frac{100 \cdot 100}{100 + 100} = 50 \Omega$$

The equivalent resistor is given by a parallel configuration of resistors in series:

$$R_{\text{eq}} = R_1 + (R_Y + R_4) \parallel (R_Y + R_5) = 100 + (50 + 100) \parallel (50 + 100) = 133.3 \Omega$$

The switch shall now be open. Calculate the equivalent resistance R_{eq} between A and B .

Solution



The equivalent resistor is given by a parallel configuration of resistors in series:

$$R_{eq} = (R_2 + R_1 + R_1) \parallel (R_2 + R_2) \parallel (100 \, \Omega + 200 \, \Omega + 200 \, \Omega) \parallel (100 \, \Omega + 100 \, \Omega) \parallel (500 \, \Omega) \parallel (200 \, \Omega) \parallel (500 \, \Omega \cdot 200 \, \Omega) / (500 \, \Omega + 200 \, \Omega)$$


Exercise E3 Pure Resistor Network Simplification (written test, approx. 13 % of a 60-minute written test, WS2022)

The following shall be solved with \$R_1 = 200 \, \Omega\$, \$R_2 = 100 \, \Omega\$, \$R_3 = 150 \, \Omega\$, \$R_4 = 100 \, \Omega\$, and the voltage source \$U_{SV} = 10 \, \text{V}\$.

Solution

$$R_{eq} = 132.8 \, \Omega$$

Now a wye-delta transformation is necessary.




Since $R_2 = R_3$ and based on the equations for the transformation, the transformed R_Y is given as:
$$R_Y = \frac{R_2 \cdot R_2}{R_2 + R_2 + R_2} = \frac{(100 \, \Omega)^2}{3 \cdot 100 \, \Omega} = \frac{1}{3} \cdot 100 \, \Omega = 33.33 \, \Omega$$

The equivalent resistor is given by a parallel configuration of resistors in series:

$$R_{\text{eq}} = R_Y + (R_Y + R_1 + R_1) \parallel (R_Y + R_2) \parallel R_{\text{eq}} = 33.33 \, \Omega + (33.33 \, \Omega + 400 \, \Omega) \parallel (33.33 \, \Omega + 100 \, \Omega)$$

1. The switch shall now be open. Calculate the equivalent resistance R_{eq} between A and B .

Solution




The equivalent resistor is given by a parallel configuration of resistors in series:

$$R_{\text{eq}} = (R_2 + R_1) \parallel (R_2 + R_2) \parallel (100 \, \Omega + 200 \, \Omega + 200 \, \Omega) \parallel (100 \, \Omega + 100 \, \Omega) \parallel (500 \, \Omega) \parallel (200 \, \Omega) \parallel R_{\text{eq}} = \frac{500 \, \Omega \cdot 200 \, \Omega}{500 \, \Omega + 200 \, \Omega}$$

Exercise E1 Equivalent linear Source (written test, approx. 14 % of a 60-minute written test, WS2022)

The circuit in the following has to be simplified.
Result


$$U_{\text{s}} = U_{\text{AB}} = 4.5 \, \text{V} \quad R_{\text{i}} = R_{\text{AB}} = 6 \, \Omega$$




Calculate the internal resistance R_i and the source voltage U_s of an equivalent linear voltage source on the connectors A and B. $\begin{aligned} R_1 &= 5.0 \, \Omega, \quad U_2 = 6.0 \, \text{V}, \quad R_3 = 10 \, \Omega, \quad I_4 = 4.2 \, \text{A}, \\ R_5 &= 10 \, \Omega, \quad R_6 = 7.5 \, \Omega, \quad R_7 = 15 \, \Omega \end{aligned}$ Use equivalent sources in order to simplify the circuit!

Solution

The best thing is to re-think the wiring like rubber bands and adjust them:



The linear voltage source of U_2 and R_1 can be transformed into a current source $I_2 = \frac{U_2}{R_1}$ and R_1 :



Now a lot of them can be combined. The resistors R_1 , R_3 , R_5 are in parallel, like also I_2 and I_4 :

$$R_{135} = R_1 || R_3 || R_5$$

$$I_{24} = I_2 - I_4 = \frac{U_{24}}{R_1} - I_4$$

The resulting circuit can again be transformed:



Here, the U_{24} is calculated by I_{24} as the following:

$$U_{24} = I_{24} \cdot R_{135}$$

$$U_{24} = U_{23} \cdot \frac{R_7}{R_6 + R_7 + R_1 \parallel R_3 \parallel R_5} = (U_2 - U_4) \cdot \frac{R_7}{R_6 + R_7 + R_1 \parallel R_3 \parallel R_5}$$

On the right side of the last circuit, there is a voltage divider given by R_{135} , R_6 , and R_7 .

Therefore the voltage between A and B is given as:

$$U_{AB} = U_{24} \cdot \frac{R_7}{R_6 + R_7 + R_1 \parallel R_3 \parallel R_5} = (U_2 - U_4) \cdot \frac{R_7}{R_6 + R_7 + R_1 \parallel R_3 \parallel R_5}$$

For the internal resistance R_i the ideal voltage source is substituted by its resistance ($=0\Omega$, so a short-circuit):

$$R_{AB} = R_7 \parallel (R_6 + R_1 \parallel R_3 \parallel R_5)$$

with $R_1 \parallel R_3 \parallel R_5 = 5\Omega \parallel 10\Omega \parallel 10\Omega = 5\Omega \parallel 5\Omega = 2.5\Omega$:

$$U_{AB} = \frac{6.0\text{V}}{5.0\Omega} - 4.2\Omega \cdot \frac{15\Omega \cdot 2.5\Omega}{7.5\Omega + 15\Omega + 2.5\Omega} \quad R_{AB} = 15\Omega \parallel (7.5\Omega + 2.5\Omega)$$


Exercise E4 Equivalent linear Source

(written test, approx. 14 % of a 60-minute written test, WS2022)

The circuit in the following has to be simplified.

Result


$$U_s = U_{AB} = 4.5\text{V} \quad R_i = R_{AB} = 6\Omega$$




Calculate the internal resistance R_i and the source voltage U_s of an equivalent linear voltage source on the connectors A and B. $\begin{aligned} R_1 &= 5.0 \, \Omega, \quad U_2 = 6.0 \, \text{V}, \quad R_3 = 10 \, \Omega, \quad I_4 = 4.2 \, \text{A}, \\ R_5 &= 10 \, \Omega, \quad R_6 = 7.5 \, \Omega, \quad R_7 = 15 \, \Omega \end{aligned}$ Use equivalent sources in order to simplify the circuit!

Solution

The best thing is to re-think the wiring like rubber bands and adjust them:



The linear voltage source of U_2 and R_1 can be transformed into a current source $I_2 = \frac{U_2}{R_1}$ and R_1 :



Now a lot of them can be combined. The resistors R_1 , R_3 , R_5 are in parallel, like also I_2 and I_4 :

$$R_{135} = R_1 || R_3 || R_5$$

$$I_{24} = I_2 - I_4 = \frac{U_2}{R_1} - I_4$$

The resulting circuit can again be transformed:



Here, the U_{24} is calculated by I_{24} as the following:

$$U_{24} = I_{24} \cdot R_{135}$$

$$\&= R_{135} \cdot I_{24} \quad \&= \left(\frac{U_2}{R_1} - I_4 \right) \cdot R_1 || R_3 || R_5$$

On the right side of the last circuit, there is a voltage divider given by R_{135} , R_6 , and R_7 .

Therefore the voltage between A and B is given as:
$$U_{\rm AB}$$

$$\begin{aligned} &= U_{24} \cdot \frac{R_7}{R_6 + R_7 + R_1 || R_3 || R_5} \parallel &= \\ &(\frac{U_2}{R_1}) - I_4 \cdot \frac{R_7 \cdot R_1 || R_3 || R_5}{R_6 + R_7 + R_1 || R_3 || R_5} \parallel \end{aligned}$$

For the internal resistance R_i the ideal voltage source is substituted by its resistance ($\mathcal{E}=0\Omega$, so a short-circuit):

$$R_{\text{AB}} = R_7 \parallel (R_6 + R_1 \parallel R_3 \parallel R_5)$$

with $R_1 || R_3 || R_5 = 5 \sim \Omega || 10 \sim \Omega || 10 \sim \Omega = 5 \sim \Omega || 5 \sim \Omega = 2.5 \sim \Omega$:

$$\begin{aligned} U_{\rm AB} &= \left(\frac{6.0 \, \rm V}{5.0 \, \Omega} - 4.2 \, \Omega \right) \\ &\cdot \left(\frac{15 \, \Omega \cdot 2.5 \, \Omega}{7.5 \, \Omega + 15 \, \Omega + 2.5 \, \Omega} \right) \\ R_{\rm AB} &= 15 \, \Omega \parallel (7.5 \, \Omega + 2.5 \, \Omega) \end{aligned}$$

Exercise E1 Charging Capacitors

(written test, approx. 16 % of a 60-minute written test, WS2022)

The circuit (shown in the figure below) consists of a battery with an EMF of 6 V , a $20 \text{ }\Omega$ resistor, a capacitor of capacitance $5 \text{ }\mu\text{F}$, and a switch S_1 . Initially, the switch S_1 is open. The voltage across the capacitor is again 0 V at the moment $t_0 = 0 \text{ s}$ when the switch S_1 is closed. Calculate the voltage $u_c(t_2)$ across the capacitor at $t_2 = 1 \text{ ms}$ after closing the switch.


```

% To solve this, first create an equivalent linear voltage source from $U$, $R_1$, and
% $R_2$.
\begin{align*} U_{\text{eq}} &= \frac{U}{1 + \frac{R_1}{R_2}} \\ R_{\text{eq}} &= \frac{R_1 R_2}{R_1 + R_2} \end{align*}


```

$$\text{The ideal } V_1 \text{ of } \mathbb{C}[x, y] \text{ is the ideal } V_1 = \langle x^2 - y^2 \rangle.$$

On an alternative view, one can try to create an equivalent linear voltage source again. Then, the internal resistance is given by substituting the ideal voltage source is again short-circuiting $R_{2\$}$.




The circuit contains a voltage source $U=12\text{ V}$, a switch S_1 , a resistor of $R_1=20\text{ }\Omega$ and a capacitor of $C=100\text{ }\mu\text{F}$. The switch S_2 to an additional consumer R_2 will be considered to be open for the first task. At the moment $t_0=0\text{ s}$ the switch S_1 is closed, the voltage across the capacitor is $u_c(t_0)=0\text{ V}$.



First do not consider the light bulb - it is not connected to the RC circuit. Calculate the point of time t_1 when $u_c(t_1)=0.5 \cdot U$.

Solution



So, here only R_1 and C gives the time constant: $\tau = R_1 \cdot C$

The following formula describes the time course of $u_C(t)$ which has to be $u_c(t_1)=0.5 \cdot U$:

$$u_c(t) = U \cdot (1 - e^{-t/\tau}) = 0.5 \cdot U$$
 It has to be rearranged to $(1 - e^{-t/\tau}) = 0.5$

$$e^{-t/\tau} = 0.5 \implies -t/\tau = \ln(0.5) \implies t = -\tau \cdot \ln(0.5) = R_1 \cdot C \cdot \ln(0.5)$$
 An equivalent linear voltage source can be given with U_s , R_1 , and R_B as seen in yellow.

Therefore, the voltage of the equivalent linear voltage source is: $U_s = U \cdot \frac{R_B}{R_1 + R_B} = \frac{1}{2} \cdot U$ The internal resistance is given by substituting the ideal voltage source with its resistance ($=0\text{ }\Omega$, short-circuit).

$$R_i = R_1 \parallel R_B = 10\text{ }\Omega$$

$$u_c(t_2) = U_s \cdot (1 - e^{-t_2/(R_i \cdot C)}) = \frac{1}{2} \cdot U \cdot (1 - e^{-1\text{ ms}/(10\text{ }\Omega \cdot 100\text{ }\mu\text{F})})$$

Exercise E5 Charging Capacitors

(written test, approx. 16 % of a 60-minute written test, WS2022)

The circuit (see the solution) consists of a 12 V voltage source, a $20\text{ }\Omega$ resistor, a $100\text{ }\mu\text{F}$ capacitor, and a $20\text{ }\Omega$ resistor. The voltage across the capacitor is again 0 V at the moment $t_0=0\text{ s}$ when the switch S_1 is closed. Calculate the voltage $u_c(t_2)$ across the capacitor at $t_2=1\text{ ms}$ after closing the switch.

Solution To solve this, first create an equivalent linear voltage source from U , R_1 , and R_B .


$$U_s = U \cdot \frac{R_B}{R_1 + R_B} = \frac{1}{2} \cdot U = 6\text{ V}$$

$$R_i = R_1 \parallel R_B = 10\text{ }\Omega$$

Solution

begin{align*} U_{R_2} = U \cdot \frac{R_2}{R_1 + R_2} = 12 \text{ V} \cdot \frac{20 \text{ } \Omega}{20 \text{ } \Omega + 20 \text{ } \Omega} = 6 \text{ V} \end{align*}

On an alternative view, one can try to create an equivalent linear voltage source again. Then, the internal resistance is given by substituting the ideal voltage source is again short-circuiting R_2




The circuit contains a voltage source $U = 12 \text{ V}$, a switch S_1 , a resistor of $R_1 = 20 \text{ } \Omega$ and a capacitor of $C = 100 \text{ } \mu\text{F}$.

The switch S_2 to an additional consumer R_2 will be considered to be open for the first tasks. At the moment $t_0 = 0 \text{ s}$ the switch S_1 is closed, the voltage across the capacitor is $u_c(t_0) = 0 \text{ V}$.

.. First do not consider the light bulb - it is not connected to the RC circuit.

Calculate the point of time t_1 when $u_c(t_1) = 0.5 \cdot U$.



Solution

An equivalent linear voltage source can be given with U , R_1 , and R_{B} as seen in yellow.

Therefore, the voltage of the equivalent linear voltage source is: $U_s = U \cdot \frac{R_{\text{B}}}{R_1 + R_{\text{B}}} = \frac{1}{2} \cdot U$ The internal resistance is given by substituting the ideal voltage source with its resistance ($= 0 \text{ } \Omega$, short-circuit).

$$R_{\text{int}} = R_1 \parallel R_{\text{B}} = 10 \text{ } \Omega$$

So, here only R_1 and C gives the time constant: $\tau = R_1 \cdot C$

The following formula describes the time course of $u_c(t)$ which has to be $u_c(t_1) = 0.5 \cdot U$:

$$u_c(t) = U \cdot (1 - e^{-t/\tau}) = 0.5 \cdot U$$

It has to be rearranged to t

$$(1 - e^{-t/\tau}) = 0.5 \implies e^{-t/\tau} = 0.5 \implies -t/\tau = \ln(0.5) \implies t = -\tau \cdot \ln(0.5) = R_1 \cdot C \cdot \ln(0.5)$$

Exercise E1 Analyzing complex Impedances**(written test, approx. 14 % of a 60-minute written test, WS2022)**

2. Calculate the phase angle of the solution $\underline{U} = 50 \angle 0^\circ$ V and $\underline{Z} = 0.24 + j4.68 \Omega$ in both the components. ($\$R\$$ and $\underline{X}_L$) shall be given.

After analysis, the full width of the component impedance can be extracted and the phase angle φ in phase $\varphi = \arctan\left(\frac{\text{Im}(\underline{Z})}{\text{Re}(\underline{Z})}\right) = \arctan\left(\frac{4.68}{0.24}\right) = 87.06^\circ$

.. Calculate the physical values of the two components.

Solution $\begin{aligned} R &= 0.24 \Omega \\ L &= \frac{4.68}{\omega} = \frac{4.68}{2\pi \cdot 300} = 1.24 \text{ mH} \end{aligned}$

Solution

$\underline{I} = \frac{\underline{U}}{\underline{Z}} = \frac{50 \angle 0^\circ}{0.24 + j4.68} = 10.42 \angle -87.06^\circ$ A

The current and voltage are in phase with the voltage source. The resulting impedance is $\underline{Z} = 0.24 + j4.68 \Omega$.

Therefore, the component 0.24Ω is a resistor with the same value 0.24Ω and the component $j4.68 \Omega$ is an inductor with the same value 4.68Ω .

Impedance $\underline{Z} = \text{Re}(\underline{Z}) + j\text{Im}(\underline{Z}) = 0.24 + j4.68 \Omega$

$\varphi = \arctan\left(\frac{\text{Im}(\underline{Z})}{\text{Re}(\underline{Z})}\right) = \arctan\left(\frac{4.68}{0.24}\right) = 87.06^\circ$

The phase angle φ can be calculated as $\varphi = \arctan\left(\frac{\text{Im}(\underline{Z})}{\text{Re}(\underline{Z})}\right) = \arctan\left(\frac{4.68}{0.24}\right) = 87.06^\circ$

With the complex part $\underline{Z} = 0.24 + j4.68 \Omega$ the physical values $R = 0.24 \Omega$ and $L = 1.24 \text{ mH}$ can be calculated as $R = \text{Re}(\underline{Z})$ and $L = \frac{\text{Im}(\underline{Z})}{\omega}$.

The phase angle φ can be calculated as $\varphi = \arctan\left(\frac{\text{Im}(\underline{Z})}{\text{Re}(\underline{Z})}\right) = \arctan\left(\frac{4.68}{0.24}\right) = 87.06^\circ$

Exercise E6 Analyzing complex Impedances**(written test, approx. 14 % of a 60-minute written test, WS2022)**

2. Calculate the phase angle of the solution $\underline{U} = 50 \angle 0^\circ$ V and $\underline{Z} = 0.24 + j4.68 \Omega$ in both the components. ($\$R\$$ and $\underline{X}_L$) shall be given.

After analysis, the full width of the component impedance can be extracted and the phase angle φ in phase $\varphi = \arctan\left(\frac{\text{Im}(\underline{Z})}{\text{Re}(\underline{Z})}\right) = \arctan\left(\frac{4.68}{0.24}\right) = 87.06^\circ$

.. Calculate the physical values of the two components.

Solution $\begin{aligned} R &= 0.24 \Omega \\ L &= \frac{4.68}{\omega} = \frac{4.68}{2\pi \cdot 300} = 1.24 \text{ mH} \end{aligned}$

Solution

$\underline{I} = \frac{\underline{U}}{\underline{Z}} = \frac{50 \angle 0^\circ}{0.24 + j4.68} = 10.42 \angle -87.06^\circ$ A

The current and voltage are in phase with the voltage source. The resulting impedance is $\underline{Z} = 0.24 + j4.68 \Omega$.

Therefore, the component 0.24Ω is a resistor with the same value 0.24Ω and the component $j4.68 \Omega$ is an inductor with the same value 4.68Ω .

Impedance $\underline{Z} = \text{Re}(\underline{Z}) + j\text{Im}(\underline{Z}) = 0.24 + j4.68 \Omega$

$\varphi = \arctan\left(\frac{\text{Im}(\underline{Z})}{\text{Re}(\underline{Z})}\right) = \arctan\left(\frac{4.68}{0.24}\right) = 87.06^\circ$

The phase angle φ can be calculated as $\varphi = \arctan\left(\frac{\text{Im}(\underline{Z})}{\text{Re}(\underline{Z})}\right) = \arctan\left(\frac{4.68}{0.24}\right) = 87.06^\circ$

With the complex part $\underline{Z} = 0.24 + j4.68 \Omega$ the physical values $R = 0.24 \Omega$ and $L = 1.24 \text{ mH}$ can be calculated as $R = \text{Re}(\underline{Z})$ and $L = \frac{\text{Im}(\underline{Z})}{\omega}$.

The phase angle φ can be calculated as $\varphi = \arctan\left(\frac{\text{Im}(\underline{Z})}{\text{Re}(\underline{Z})}\right) = \arctan\left(\frac{4.68}{0.24}\right) = 87.06^\circ$

$$\begin{aligned} X_L &= \frac{1}{\sqrt{(0.24 \sim \Omega)^2 + (4.68 \sim \Omega)^2}} \\ \phi &= \arctan \left(\frac{-4.68 \sim \Omega}{0.24 \sim \Omega} \right) \end{aligned}$$

Exercise E1 Impedances at different Frequencies (written test, approx. 18 % of a 60-minute written test, WS2022)

2. A capacitor \$C_1\$ shall have the same absolute value of the impedance as a capacitor \$C_2=40 \sim \{\rm nF\}\$ at \$f_1=4 \sim \{\rm MHz\}\$.

Solution

Solution $R_1 = 1.00 \sim \Omega$

$$\text{solution} \begin{array}{l} \text{begin}\{align*\} R \approx 10.0 \sim \Omega \end{array}$$

A series circuit means that the current is constant on every component.

The equivalent impedance for R and L combined is given by $\begin{aligned} & \end{aligned}$

[illegible]

$\{R_2\}^2 + \{X\{L_2\}\}^2$

Therefore, the resulting current of the parallel circuit is given as: \begin{align*}

$$\underline{I_3} = \underline{I_{3R}} + \underline{I_{3C}}$$
[illegible]
$$\left. \right)^2 - (2\pi \cdot 450 \sim \text{kHz} \cdot 4.7 \sim \text{μH})^2 \} \quad \end{align*}$$

Back to the first formula:
$$R^3 \cdot \{I\} \cdot \{3R\} = \{X\} \cdot \{3C\} \cdot$$

$$\{I\} \setminus \{3C\} \setminus B \equiv \{X\} \setminus \{3C\} \cdot \frac{\{I\} \setminus \{3C\}}{\{I\} \setminus \{3B\}} \setminus \equiv$$
$$\frac{\{1\}_{[5C]}}{\{1\}_{[5A]}} = \frac{\{X\}_{[5C]}}{\{X\}_{[5A]}} \cdot \frac{\{1\}_{[5C]}}{\{1\}_{[5B]}}$$
$$\frac{|I| \{3R\} |^2|}{|I| \{3R\}} \quad \end{align*}$$

Exercise E7 Impedances at different Frequencies (written test, approx. 18 % of a 60-minute written test, WS2022)

Exercise E1 Complex Impedance Circuit
(written test, approx. 15 % of a 60-minute written test, WS2022)

1. Calculate the equivalent impedance Z for the circuit in the AC voltage source $u(t) = 3.0 \sim \text{V} \cdot \sin(2\pi \cdot 15 \sim \text{kHz} \cdot t)$ and the resistor $R = 1.00 \sim \Omega$ and the capacitor $C = 40 \sim \text{nF}$ at $f = 4 \sim \text{MHz}$. The high-frequency test circuit is shown in the following diagram.

Solution:

$$Z = 1.00 \sim \Omega$$

$$Z = 10.0 \sim \Omega$$
Solution:

A series circuit means that the current is constant on every component.

The equivalent impedance for R and L combined is given by
$$Z_L = j\omega L = j2\pi \cdot 4 \cdot 10^6 \cdot 40 \cdot 10^{-9} = j10.0 \sim \Omega$$

 Parallel circuit means that the voltage is the same on R and L .

$$\frac{1}{Z} = \frac{1}{R} + \frac{1}{Z_L} = \frac{1}{1.00} + \frac{1}{j10.0} = 1.00 - j0.1 \sim \Omega^{-1}$$

$$Z = \frac{1}{1.00 - j0.1} = 1.01 + j0.01 \sim \Omega$$

 The resulting current of the parallel circuit is given as:

$$I = \frac{U}{Z} = \frac{3.0}{1.01 + j0.01} = 2.97 - j0.29 \sim \text{mA}$$

 Back to the first formula:

$$Z = \frac{U}{I} = \frac{3.0}{2.97 - j0.29} = 1.01 + j0.01 \sim \Omega$$

Exercise E1 Complex Impedance Circuit

(written test, approx. 15 % of a 60-minute written test, WS2022)

1. Calculate the equivalent impedance Z for the circuit in the AC voltage source $u(t) = 3.0 \sim \text{V} \cdot \sin(2\pi \cdot 15 \sim \text{kHz} \cdot t)$ and the resistor $R = 1.00 \sim \Omega$ and the capacitor $C = 40 \sim \text{nF}$ at $f = 4 \sim \text{MHz}$. The high-frequency test circuit is shown in the following diagram.

Solution:
 This linear source is connected with an inductor of $L = 330 \sim \mu\text{H}$ and a capacitor of $C = 0.22 \sim \mu\text{F}$, all in series.

Result:

$$Z = 107.37 \sim \Omega$$

 Draw the circuit diagram of the given circuit.
 Label all components, voltages, and currents.

$$Z = \frac{U}{I} = \frac{3.0}{2.97 - j0.29} = 1.01 + j0.01 \sim \Omega$$


$$Z_C = \frac{1}{j\omega C} = \frac{1}{j2\pi \cdot 15 \cdot 10^3 \cdot 0.22 \cdot 10^{-6}} = -j1.59 \sim \Omega$$


 With $f = 15 \sim \text{kHz}$:


$$Z_L = j\omega L = j2\pi \cdot 15 \cdot 10^3 \cdot 330 \cdot 10^{-6} = j31.8 \sim \Omega$$

$$Z = R + jX_L - jX_C = 1.00 + j31.8 - j1.59 = 1.00 + j30.2 \sim \Omega$$

$$|Z| = \sqrt{R^2 + X^2} = \sqrt{1.00^2 + 30.2^2} = 30.2 \sim \Omega$$







From:

<https://wiki.mexle.te.hs-heilbronn.de/> - **MEXLE Wiki**

Permanent link:

https://wiki.mexle.te.hs-heilbronn.de/electrical_engineering_1/ws2022_exam?rev=1680365940

Last update: **2023/04/01 18:19**

