

Exam Winter Semester 2022

Student Group

First Name	Surname	Matrikel Nr.

Table of Contents

Exercise E1 Resistance of a Wire by Resistivity (written test, approx. 6 % of a 60-minute written test, WS2022)	3
Exercise E1 Resistance of a Wire by Resistivity (written test, approx. 6 % of a 60-minute written test, WS2022)	3
Exercise E1 Temperature-dependent Resistance (written test, approx. 6 % of a 60-minute written test, WS2022)	3
Exercise E2 Temperature-dependent Resistance (written test, approx. 6 % of a 60-minute written test, WS2022)	4
Exercise E1 Pure Resistor Network Simplification (written test, approx. 13 % of a 60-minute written test, WS2022)	5
Exercise E3 Pure Resistor Network Simplification (written test, approx. 13 % of a 60-minute written test, WS2022)	6
Exercise E1 Equivalent linear Source (written test, approx. 14 % of a 60-minute written test, WS2022)	8
Exercise E4 Equivalent linear Source (written test, approx. 14 % of a 60-minute written test, WS2022)	12
Exercise E1 Charging Capacitors (written test, approx. 16 % of a 60-minute written test, WS2022)	16
Exercise E5 Charging Capacitors (written test, approx. 16 % of a 60-minute written test, WS2022)	17
Exercise E1 Analyzing complex Impedances (written test, approx. 14 % of a 60-minute written test, WS2022)	19
Exercise E6 Analyzing complex Impedances (written test, approx. 14 % of a 60-minute written test, WS2022)	19
Exercise E1 Impedances at different Frequencies (written test, approx. 18 % of a 60-minute written test, WS2022)	20
Exercise E7 Impedances at different Frequencies (written test, approx. 18 % of a 60-minute written test, WS2022)	20
Exercise E1 Complex Impedance Circuit (written test, approx. 15 % of a 60-minute written test, WS2022)	

test, WS2022)	21
Exercise E8 Complex Impedance Circuit (written test, approx. 15 % of a 60-minute written	
test, WS2022)	24

Exercise E1 Resistance of a Wire by Resistivity (written test, approx. 6 % of a 60-minute written test, WS2022)

A heating element made of solid nichrome wire with a cross-section of 1.80 mm^2 is used. The electric power dissipation (= heat flow) of $P=40 \text{ W}$ is necessary.

Determine the current I linked to the laboratory for heating elements.

The Nichrome wire has a resistivity of $1.10 \cdot 10^{-6} \text{ } \Omega \text{ m}$.

The heating element is 3 m long and has a diameter of 3.57 mm .

∴ Calculate the resistance R of the heating element.

Solution

$$\begin{aligned} P &= U \cdot I = R \cdot I^2 \quad \rightarrow \quad I = \sqrt{\frac{P}{R}} \\ &= \sqrt{\frac{40 \text{ W}}{0.33 \text{ } \Omega}} \end{aligned}$$

$$\begin{aligned} R &= \rho \cdot \frac{l}{A} \quad | \quad \text{with } A = r^2 \cdot \pi = \frac{1}{4} d^2 \cdot \pi \\ R &= \rho \cdot \frac{l}{\frac{1}{4} d^2 \cdot \pi} \quad \& \quad R = 1.10 \cdot 10^{-6} \text{ } \Omega \text{ m} \cdot \frac{4 \cdot 3 \text{ m}}{(3.57 \cdot 10^{-3} \text{ m})^2 \cdot \pi} \end{aligned}$$

Exercise E1 Resistance of a Wire by Resistivity (written test, approx. 6 % of a 60-minute written test, WS2022)

A heating element made of solid nichrome wire with a cross-section of 1.80 mm^2 is used. The electric power dissipation (= heat flow) of $P=40 \text{ W}$ is necessary.

Determine the current I linked to the laboratory for heating elements.

The Nichrome wire has a resistivity of $1.10 \cdot 10^{-6} \text{ } \Omega \text{ m}$.

The heating element is 3 m long and has a diameter of 3.57 mm .

∴ Calculate the resistance R of the heating element.

Solution

$$\begin{aligned} P &= U \cdot I = R \cdot I^2 \quad \rightarrow \quad I = \sqrt{\frac{P}{R}} \\ &= \sqrt{\frac{40 \text{ W}}{0.33 \text{ } \Omega}} \end{aligned}$$

$$\begin{aligned} R &= \rho \cdot \frac{l}{A} \quad | \quad \text{with } A = r^2 \cdot \pi = \frac{1}{4} d^2 \cdot \pi \\ R &= \rho \cdot \frac{l}{\frac{1}{4} d^2 \cdot \pi} \quad \& \quad R = 1.10 \cdot 10^{-6} \text{ } \Omega \text{ m} \cdot \frac{4 \cdot 3 \text{ m}}{(3.57 \cdot 10^{-3} \text{ m})^2 \cdot \pi} \end{aligned}$$

Exercise E1 Temperature-dependent Resistance

(written test, approx. 6 % of a 60-minute written test, WS2022)

2. A refrigerator, as shown in the figure, has a temperature coefficient of resistance $\alpha = 0.01 \text{ K}^{-1}$ and a temperature coefficient of resistance $\beta = 71 \text{ K}^{-2}$. Its temperature coefficients are: $\alpha = 0.01 \text{ K}^{-1}$ and $\beta = 71 \text{ K}^{-2}$.

Result: The temperature inside the refrigeration system can reach down to -40°C .

Result: The temperature inside the refrigeration system can reach down to -40°C .

Result: The temperature inside the refrigeration system can reach down to -40°C .

Result: The temperature inside the refrigeration system can reach down to -40°C .

Result: The temperature inside the refrigeration system can reach down to -40°C .

Result: The temperature inside the refrigeration system can reach down to -40°C .

Exercise E2 Temperature-dependent Resistance**(written test, approx. 6 % of a 60-minute written test, WS2022)**

2. A refrigerator, as shown in the figure, has a temperature coefficient of resistance $\alpha = 0.01 \text{ K}^{-1}$ and a temperature coefficient of resistance $\beta = 71 \text{ K}^{-2}$. Its temperature coefficients are: $\alpha = 0.01 \text{ K}^{-1}$ and $\beta = 71 \text{ K}^{-2}$.

Result: The temperature inside the refrigeration system can reach down to -40°C .

Result: The temperature inside the refrigeration system can reach down to -40°C .

Result: The temperature inside the refrigeration system can reach down to -40°C .

Result: The temperature inside the refrigeration system can reach down to -40°C .

Result: The temperature inside the refrigeration system can reach down to -40°C .

Result: The temperature inside the refrigeration system can reach down to -40°C .

Exercise E1 Pure Resistor Network Simplification


(written test, approx. 13 % of a 60-minute written test, WS2022)

The following shall now be closed and integrated, $R_2 = R_3 = 100 \Omega$ and the switch between R_1 and R_2 shall be open. Calculate the equivalent resistance R_{eq} between A and B .

Solution

$$R_{\text{eq}} = 133.8 \Omega$$

Now a wye-delta transformation is necessary.



Since $R_2 = R_3$ and based on the equations for the transformation, the transformed R_Y is given as:


$$R_Y = \frac{R_2 \cdot R_3}{R_2 + R_3} = \frac{100 \cdot 100}{100 + 100} = 50 \Omega$$

The equivalent resistor is given by a parallel configuration of resistors in series:

$$R_{\text{eq}} = R_Y + (R_Y + R_1 + R_1) \parallel (R_Y + R_2) = 50 + (50 + 100 + 100) \parallel (50 + 100)$$

.. The switch shall now be open. Calculate the equivalent resistance R_{eq} between A and B .

Solution



The equivalent resistor is given by a parallel configuration of resistors in series:

$$R_{eq} = (R_2 + R_1 + R_3) \parallel (R_2 + R_4) \parallel (100 \, \Omega + 200 \, \Omega + 200 \, \Omega) \parallel (100 \, \Omega + 100 \, \Omega) \parallel (500 \, \Omega) \parallel (200 \, \Omega) \parallel (500 \, \Omega \cdot 200 \, \Omega) \over {500 \, \Omega + 200 \, \Omega}$$


Exercise E3 Pure Resistor Network Simplification (written test, approx. 13 % of a 60-minute written test, WS2022)

The following shall be simplified with $R_1 = 200 \, \Omega$, $R_2 = 100 \, \Omega$, $R_3 = 150 \, \Omega$, $R_4 = 100 \, \Omega$, $R_5 = 500 \, \Omega$, $R_6 = 200 \, \Omega$, $R_7 = 100 \, \Omega$ and the voltage source $U_{SV} = 10 \, \text{V}$.
Result given: $R_{eq} = 132.8 \, \Omega$.

Solution

$$R_{eq} = 132.8 \, \Omega$$

Now a wye-delta transformation is necessary.




Since $R_2 = R_3$ and based on the equations for the transformation, the transformed R_Y is given as:
$$R_Y = \frac{R_2 \cdot R_2}{R_2 + R_2 + R_2} = \frac{(100 \, \Omega)^2}{3 \cdot 100 \, \Omega} = \frac{1}{3} \cdot 100 \, \Omega = 33.33 \, \Omega$$

The equivalent resistor is given by a parallel configuration of resistors in series:

$$R_{\text{eq}} = R_Y + (R_Y + R_1 + R_1) \parallel (R_Y + R_2) \parallel R_{\text{eq}} = 33.33 \, \Omega + (33.33 \, \Omega + 400 \, \Omega) \parallel (33.33 \, \Omega + 100 \, \Omega) \parallel$$

1. The switch shall now be open. Calculate the equivalent resistance R_{eq} between A and B .

Solution




The equivalent resistor is given by a parallel configuration of resistors in series:

$$R_{\text{eq}} = (R_2 + R_1) \parallel (R_2 + R_2) \parallel R_{\text{eq}} = (100 \, \Omega + 200 \, \Omega + 200 \, \Omega) \parallel (100 \, \Omega + 100 \, \Omega) \parallel R_{\text{eq}} = \{ \{ 500 \, \Omega \cdot 200 \, \Omega \} \over {500 \, \Omega + 200 \, \Omega} \} \parallel$$

Exercise E1 Equivalent linear Source (written test, approx. 14 % of a 60-minute written test, WS2022)

The circuit in the following has to be simplified.
Result


$$U_{\text{s}} = U_{\text{AB}} = 4.5 \, \text{V} \quad R_{\text{i}} = R_{\text{AB}} = 6 \, \Omega$$




Calculate the internal resistance R_i and the source voltage U_s of an equivalent linear voltage source on the connectors A and B. $\begin{aligned} R_1 &= 5.0 \, \Omega, \quad U_2 = 6.0 \, \text{V}, \quad R_3 = 10 \, \Omega, \quad I_4 = 4.2 \, \text{A}, \\ R_5 &= 10 \, \Omega, \quad R_6 = 7.5 \, \Omega, \quad R_7 = 15 \, \Omega \end{aligned}$ Use equivalent sources in order to simplify the circuit!

Solution

The best thing is to re-think the wiring like rubber bands and adjust them:



The linear voltage source of U_2 and R_1 can be transformed into a current source $I_2 = \frac{U_2}{R_1}$ and R_1 :



Now a lot of them can be combined. The resistors R_1 , R_3 , R_5 are in parallel, like also I_2 and I_4 :

$$R_{135} = R_1 || R_3 || R_5$$

$$I_{24} = I_2 - I_4 = \frac{U_2}{R_1} - I_4$$

The resulting circuit can again be transformed:



Here, the U_{24} is calculated by I_{24} as the following:

$$U_{24} = I_{24} \cdot R_{135}$$

$$U_{24} = U_{23} \cdot \frac{R_7}{R_6 + R_7 + R_1 \parallel R_3 \parallel R_5} = (U_2 - U_4) \cdot \frac{R_7}{R_6 + R_7 + R_1 \parallel R_3 \parallel R_5}$$

On the right side of the last circuit, there is a voltage divider given by R_{135} , R_6 , and R_7 .

Therefore the voltage between A and B is given as:

$$U_{AB} = U_{24} \cdot \frac{R_7}{R_6 + R_7 + R_1 \parallel R_3 \parallel R_5} = (U_2 - U_4) \cdot \frac{R_7}{R_6 + R_7 + R_1 \parallel R_3 \parallel R_5}$$

For the internal resistance R_i the ideal voltage source is substituted by its resistance ($=0\Omega$, so a short-circuit):

$$R_{AB} = R_7 \parallel (R_6 + R_1 \parallel R_3 \parallel R_5)$$


with $R_1 \parallel R_3 \parallel R_5 = 5\Omega \parallel 10\Omega \parallel 10\Omega = 5\Omega \parallel 5\Omega = 2.5\Omega$:

$$U_{AB} = \frac{6.0\text{V}}{5.0\Omega} - 4.2\Omega \cdot \frac{15\Omega \cdot 2.5\Omega}{7.5\Omega + 15\Omega + 2.5\Omega} \parallel R_{AB} = 15\Omega \parallel (7.5\Omega + 2.5\Omega)$$

Exercise E4 Equivalent linear Source (written test, approx. 14 % of a 60-minute written test, WS2022)

The circuit in the following has to be simplified.
Result


$$U_s = U_{AB} = 4.5\text{V} \parallel R_i = R_{AB} = 6\Omega$$




Calculate the internal resistance R_i and the source voltage U_s of an equivalent linear voltage source on the connectors A and B. $\begin{aligned} R_1 &= 5.0 \, \Omega, \quad U_2 = 6.0 \, \text{V}, \quad R_3 = 10 \, \Omega, \quad I_4 = 4.2 \, \text{A}, \\ R_5 &= 10 \, \Omega, \quad R_6 = 7.5 \, \Omega, \quad R_7 = 15 \, \Omega \end{aligned}$ Use equivalent sources in order to simplify the circuit!

Solution

The best thing is to re-think the wiring like rubber bands and adjust them:



The linear voltage source of U_2 and R_1 can be transformed into a current source $I_2 = \frac{U_2}{R_1}$ and R_1 :



Now a lot of them can be combined. The resistors R_1 , R_3 , R_5 are in parallel, like also I_2 and I_4 :

$$R_{135} = R_1 || R_3 || R_5$$

$$I_{24} = I_2 - I_4 = \frac{U_2}{R_1} - I_4$$

The resulting circuit can again be transformed:



Here, the U_{24} is calculated by I_{24} as the following:

$$U_{24} = I_{24} \cdot R_{135}$$

$$U_{AB} = U_{24} \cdot \left(\frac{R_7}{R_6 + R_7 + R_1 \parallel R_3 \parallel R_5} \right) - I_4 \cdot R_1 \parallel R_3 \parallel R_5$$

On the right side of the last circuit, there is a voltage divider given by R_{135} , R_6 , and R_7 .

$$U_{AB} = U_{24} \cdot \left(\frac{R_7}{R_6 + R_7 + R_1 \parallel R_3 \parallel R_5} \right) - \left(\frac{U_2}{R_1} - I_4 \right) \cdot \frac{R_7 \cdot R_1 \parallel R_3 \parallel R_5}{R_6 + R_7 + R_1 \parallel R_3 \parallel R_5}$$

For the internal resistance R_i the ideal voltage source is substituted by its resistance ($=0 \Omega$, so a short-circuit):

$$R_{AB} = R_7 \parallel (R_6 + R_1 \parallel R_3 \parallel R_5)$$

with $R_1 \parallel R_3 \parallel R_5 = 5 \Omega \parallel 10 \Omega \parallel 10 \Omega = 5 \Omega \parallel 5 \Omega = 2.5 \Omega$:

$$U_{AB} = \left(\frac{6.0 \text{ V}}{5.0 \Omega} - 4.2 \text{ A} \right) \cdot \frac{15 \Omega \cdot 2.5 \Omega}{7.5 \Omega + 15 \Omega + 2.5 \Omega} \quad R_{AB} = 15 \Omega \parallel (7.5 \Omega + 2.5 \Omega)$$

Exercise E1 Charging Capacitors


(written test, approx. 16 % of a 60-minute written test, WS2022)

The circuit below is a battery with an internal resistance of $R_1 = 5 \Omega$ and a charging capacitor $C = 2 \mu\text{F}$ and a resistor $R_2 = 10 \Omega$ in series. The voltage across the capacitor is again 0 V at the moment $t_0 = 0 \text{ s}$ when the switch S_1 is closed. Calculate the voltage $u_c(t_2)$ across the capacitor at $t_2 = 1 \text{ ms}$ after closing the switch.


Solution
Hint: To solve this, first create an equivalent linear voltage source from U , R_1 , and R_2 .

Solution
The equivalent circuit is shown below. The ideal voltage source U_{eq} is given by $U_{eq} = \frac{U}{1 + \frac{R_1}{R_2}} = \frac{12 \text{ V}}{1 + \frac{5 \Omega}{10 \Omega}} = 8 \text{ V}$.

On an alternative view, one can try to create an equivalent linear voltage source again. Then, the internal resistance is given by substituting the ideal voltage source is again short-circuiting R_2 .




The circuit contains a voltage source $U=12\text{ V}$, a switch S_1 , a resistor of $R_1=20\text{ }\Omega$ and a capacitor of $C=100\text{ }\mu\text{F}$. The switch S_2 to an additional consumer R_2 will be considered to be open for the first task. At the moment $t_0=0\text{ s}$ the switch S_1 is closed, the voltage across the capacitor is $u_c(t_0)=0\text{ V}$.



First do not consider the light bulb - it is not connected to the RC circuit. Calculate the point of time t_1 when $u_c(t_1)=0.5 \cdot U$.

Solution



So, here only R_1 and C gives the time constant: $\tau = R_1 \cdot C$

The following formula describes the time course of $u_c(t)$ which has to be $u_c(t_1)=0.5 \cdot U$:

$$u_c(t) = U \cdot (1 - e^{-t/\tau}) = 0.5 \cdot U$$
 It has to be rearranged to $(1 - e^{-t/\tau}) = 0.5$

$$e^{-t/\tau} = 0.5 \quad t/\tau = \ln(0.5) \quad t = \tau \cdot \ln(0.5) = R_1 \cdot C \cdot \ln(0.5)$$
 An equivalent linear voltage source can be given with U_s , R_1 , and R_B as seen in yellow.

Therefore, the voltage of the equivalent linear voltage source is: $U_s = U \cdot \frac{R_B}{R_1 + R_B} = \frac{1}{2} \cdot U$ The internal resistance is given by substituting the ideal voltage source with its resistance ($=0\text{ }\Omega$, short-circuit).

$$R_i = R_1 \parallel R_B = 10\text{ }\Omega$$

$$u_c(t_2) = U_s \cdot (1 - e^{-t_2/(R_i \cdot C)}) = \frac{1}{2} \cdot U \cdot (1 - e^{-1\text{ ms}/(10\text{ }\Omega \cdot 100\text{ }\mu\text{F})})$$

Exercise E5 Charging Capacitors

(written test, approx. 16 % of a 60-minute written test, WS2022)

The circuit (see the solution) consists of a 12 V DC voltage source U , a switch S_1 , a resistor $R_1=20\text{ }\Omega$, a capacitor $C=100\text{ }\mu\text{F}$, and a light bulb $R_B=20\text{ }\Omega$. The voltage across the capacitor is again 0 V at the moment $t_0=0\text{ s}$ when the switch S_1 is closed. Calculate the voltage $u_c(t_2)$ across the capacitor at $t_2=1\text{ ms}$ after closing the switch.

Solution

To solve this, first create an equivalent linear voltage source from U , R_1 , and R_B .


$$U_s = U \cdot \frac{R_B}{R_1 + R_B} = \frac{1}{2} \cdot U = 6\text{ V}$$

$$R_i = R_1 \parallel R_B = 10\text{ }\Omega$$

Solution

begin{align*} U_{R_2} = U \cdot \frac{R_2}{R_1 + R_2} = 12 \text{ V} \cdot \frac{20 \text{ } \Omega}{20 \text{ } \Omega + 20 \text{ } \Omega} = 6 \text{ V} \end{align*}

On an alternative view, one can try to create an equivalent linear voltage source again. Then, the internal resistance is given by substituting the ideal voltage source is again short-circuiting R_2




The circuit contains a voltage source $U = 12 \text{ V}$, a switch S_1 , a resistor of $R_1 = 20 \text{ } \Omega$ and a capacitor of $C = 100 \text{ } \mu\text{F}$.

The switch S_2 to an additional consumer R_2 will be considered to be open for the first tasks. At the moment $t_0 = 0 \text{ s}$ the switch S_1 is closed, the voltage across the capacitor is $u_c(t_0) = 0 \text{ V}$.

.. First do not consider the light bulb - it is not connected to the RC circuit.

Calculate the point of time t_1 when $u_c(t_1) = 0.5 \cdot U$.



Solution

An equivalent linear voltage source can be given with U , R_1 , and R_B as seen in yellow.

Therefore, the voltage of the equivalent linear voltage source is: $U_s = U \cdot \frac{R_B}{R_1 + R_B} = 1/2 \cdot U$ The internal resistance is given by substituting the ideal voltage source with its resistance ($= 0 \text{ } \Omega$, short-circuit).

$$R_i = R_1 \parallel R_B = 10 \text{ } \Omega$$

So, here only R_1 and C gives the time constant: $\tau = R_1 \cdot C$

The following formula describes the time course of $u_c(t)$ which has to be $u_c(t_1) = 0.5 \cdot U$:
$$u_c(t) = U \cdot (1 - e^{-t/\tau}) = 0.5 \cdot U$$
 It has to be rearranged to
$$(1 - e^{-t/\tau}) = 0.5 \implies e^{-t/\tau} = 0.5 \implies -t/\tau = \ln(0.5) \implies t = -\tau \cdot \ln(0.5) = R_1 \cdot C \cdot \ln(0.5)$$

Exercise E1 Analyzing complex Impedances**(written test, approx. 14 % of a 60-minute written test, WS2022)**

2. Calculate the phase angle of the solution $\underline{U} = 50 \angle 0^\circ$ V and $\underline{Z} = 0.24 - j4.68 \Omega$ in both the components. (φ and $\underline{X}_L$) shall be given.

After analysis, the full bridge dimensioned circuit impedance can be extracted and the phase angle φ can be calculated as $\varphi = \arctan\left(\frac{\text{Im}(\underline{Z})}{\text{Re}(\underline{Z})}\right) = \arctan\left(\frac{-4.68}{0.24}\right) = -87.06^\circ$

.. Calculate the physical values of the two components.

Solution $\underline{R} = 0.24 \Omega$ and $\underline{X}_L = 4.68 \Omega$ and $\varphi = -87.06^\circ$

Solution

$\underline{I} = \frac{\underline{U}}{\underline{Z}} = \frac{50 \angle 0^\circ}{0.24 - j4.68} = 10.42 \angle 87.06^\circ$ A

The current and voltage are in phase since the impedance is purely real (the imaginary part is zero).

Therefore, the component 4.68Ω is a pure inductor with an inductance $L = \frac{X_L}{\omega} = \frac{4.68}{2\pi \cdot 300} = 1.24 \text{ mH}$.

The phase angle φ can be calculated as $\varphi = \arctan\left(\frac{\text{Im}(\underline{Z})}{\text{Re}(\underline{Z})}\right) = \arctan\left(\frac{-4.68}{0.24}\right) = -87.06^\circ$.

With the complex part $0.24 - j4.68$ we can calculate the magnitude $|\underline{Z}| = \sqrt{0.24^2 + 4.68^2} = 4.69 \Omega$ and the phase angle $\varphi = \arctan\left(\frac{-4.68}{0.24}\right) = -87.06^\circ$.

The phase angle φ can be calculated as $\varphi = \arctan\left(\frac{\text{Im}(\underline{Z})}{\text{Re}(\underline{Z})}\right) = \arctan\left(\frac{-4.68}{0.24}\right) = -87.06^\circ$.

Exercise E6 Analyzing complex Impedances**(written test, approx. 14 % of a 60-minute written test, WS2022)**

2. Calculate the phase angle of the solution $\underline{U} = 50 \angle 0^\circ$ V and $\underline{Z} = 0.24 - j4.68 \Omega$ in both the components. (φ and $\underline{X}_L$) shall be given.

After analysis, the full bridge dimensioned circuit impedance can be extracted and the phase angle φ can be calculated as $\varphi = \arctan\left(\frac{\text{Im}(\underline{Z})}{\text{Re}(\underline{Z})}\right) = \arctan\left(\frac{-4.68}{0.24}\right) = -87.06^\circ$

.. Calculate the physical values of the two components.

Solution $\underline{R} = 0.24 \Omega$ and $\underline{X}_L = 4.68 \Omega$ and $\varphi = -87.06^\circ$

Solution

$\underline{I} = \frac{\underline{U}}{\underline{Z}} = \frac{50 \angle 0^\circ}{0.24 - j4.68} = 10.42 \angle 87.06^\circ$ A

The current and voltage are in phase since the impedance is purely real (the imaginary part is zero).

Therefore, the component 4.68Ω is a pure inductor with an inductance $L = \frac{X_L}{\omega} = \frac{4.68}{2\pi \cdot 300} = 1.24 \text{ mH}$.

The phase angle φ can be calculated as $\varphi = \arctan\left(\frac{\text{Im}(\underline{Z})}{\text{Re}(\underline{Z})}\right) = \arctan\left(\frac{-4.68}{0.24}\right) = -87.06^\circ$.

With the complex part $0.24 - j4.68$ we can calculate the magnitude $|\underline{Z}| = \sqrt{0.24^2 + 4.68^2} = 4.69 \Omega$ and the phase angle $\varphi = \arctan\left(\frac{-4.68}{0.24}\right) = -87.06^\circ$.

The phase angle φ can be calculated as $\varphi = \arctan\left(\frac{\text{Im}(\underline{Z})}{\text{Re}(\underline{Z})}\right) = \arctan\left(\frac{-4.68}{0.24}\right) = -87.06^\circ$.

$$\begin{aligned} X_L &= \frac{1}{\sqrt{(0.24 \sim \Omega)^2 + (4.68 \sim \Omega)^2}} \\ \phi &= \arctan \left(\frac{-4.68 \sim \Omega}{0.24 \sim \Omega} \right) \end{aligned}$$

Exercise E1 Impedances at different Frequencies (written test, approx. 18 % of a 60-minute written test, WS2022)

2. A capacitor \$C_1\$ shall have the same absolute value of the impedance as a capacitor \$C_2=40 \sim \{\rm nF\}\$ at \$f_1=4 \sim \{\rm MHz\}\$.

Solution

$$\text{Solution} \quad R_1 = 1.00 \sim \Omega$$
$$\text{solution} \begin{array}{l} \begin{array}{l} \text{begin}\{align*\} \\ R \geq 10.0 \end{array} \end{array} \sim \Omega$$

A series circuit means that the current is constant on every component.

The equivalent impedance for R and L combined is given by $\begin{aligned} & \end{aligned}$

Parallel circuit implies that the voltage is the same on \$B-P\$ and \$C-Q\$. So

$$V_{BP} = V_{CQ} \implies R_1 I_1 = R_2 I_2 \implies I_1 = \frac{R_2}{R_1} I_2$$
Since the current through \$P-Q\$ is perpendicular to the magnetic field, the force on \$P-Q\$ is

$$F_{PQ} = I_1 L B \sin 90^\circ = I_1 L B$$
Similarly, the force on \$C-Q\$ is

$$F_{CQ} = I_2 L B \sin 90^\circ = I_2 L B$$
Since \$I_1 = \frac{R_2}{R_1} I_2\$, we have

$$F_{PQ} = \frac{R_2}{R_1} I_2 L B = \frac{R_2}{R_1} F_{CQ}$$
Therefore, the forces are in the ratio \$R_2 : R_1\$.

[illegible]

Therefore, the resulting current of the parallel circuit is given as: \begin{align*}

$$\underline{I}^3 = \underline{I}^{3R} + \underline{I}^{3C} \quad \forall$$
[illegible]
$$\left. \right)^2 - (2\pi \cdot 450 \sim \{\text{rm kHz}\} \cdot 4.7 \sim \{\text{rm }\mu\text{H}\})^2 \} \quad \end{align*}$$

Back to the first formula:
$$R \cdot 3 \cdot I \cdot 3R = X \cdot 3C \cdot$$

$$\{I\} \setminus \{3C\} \parallel R \text{ } 3 \&= \{X\} \setminus \{3C\} \cdot \frac{\{I\} \setminus \{3C\}}{\{I\} \setminus \{3R\}} \parallel \&=$$
$$\{ \{1\} \backslash \overline{2\pi} \cdot f \cdot C \} \} \cdot \{ \{ \sqrt{|I|} \cdot \{3\} \}^2 \cdot$$
$$\frac{|I| \{3R\}^2}{|I| \{3R\}} \quad \end{align*}$$

Exercise E7 Impedances at different Frequencies (written test, approx. 18 % of a 60-minute written test, WS2022)

Exercise E1 The resistor values $R_1 = 100 \text{ k}\Omega$, $R_2 = 470 \text{ k}\Omega$, and $R_3 = 10 \text{ k}\Omega$ are given in the AC-circuit diagram of Fig. 1. A voltage source $u(t) = 3.0 \sin(2\pi \cdot 15 \text{ kHz} \cdot t) \text{ V}$ is connected in series with an inductor of $L = 330 \text{ }\mu\text{H}$ and a capacitor of $C = 0.22 \text{ }\mu\text{F}$. All components are in series.

Solution:

$$R_1 = 100 \text{ k}\Omega$$

$$R_2 = 470 \text{ k}\Omega$$

$$R_3 = 10 \text{ k}\Omega$$

A series circuit means that the current is constant on every component.

The equivalent impedance for R and L combined is given by

$$Z_L = j\omega L = j2\pi \cdot 15 \text{ kHz} \cdot 330 \text{ }\mu\text{H} = j3.16 \text{ }\Omega$$

$$Z_R = R_1 + R_2 + R_3 = 100 \text{ k}\Omega + 470 \text{ k}\Omega + 10 \text{ k}\Omega = 580 \text{ k}\Omega$$

$$Z_{RL} = Z_R + Z_L = 580 \text{ k}\Omega + j3.16 \text{ }\Omega$$

$$|Z_{RL}| = \sqrt{(580 \text{ k}\Omega)^2 + (3.16 \text{ }\Omega)^2} \approx 580 \text{ k}\Omega$$

$$\angle Z_{RL} = \arctan\left(\frac{3.16 \text{ }\Omega}{580 \text{ k}\Omega}\right) \approx 0.03^\circ$$

$$Z_C = \frac{1}{j\omega C} = \frac{1}{j2\pi \cdot 15 \text{ kHz} \cdot 0.22 \text{ }\mu\text{F}} = -j1.59 \text{ }\Omega$$

$$Z_{RLC} = Z_{RL} + Z_C = 580 \text{ k}\Omega + j3.16 \text{ }\Omega - j1.59 \text{ }\Omega = 580 \text{ k}\Omega + j1.57 \text{ }\Omega$$

$$|Z_{RLC}| = \sqrt{(580 \text{ k}\Omega)^2 + (1.57 \text{ }\Omega)^2} \approx 580 \text{ k}\Omega$$

$$\angle Z_{RLC} = \arctan\left(\frac{1.57 \text{ }\Omega}{580 \text{ k}\Omega}\right) \approx 0.03^\circ$$

$$I = \frac{U}{|Z_{RLC}|} = \frac{3.0 \text{ V}}{580 \text{ k}\Omega} = 5.17 \text{ }\mu\text{A}$$

$$I_{\text{eff}} = \frac{I}{\sqrt{2}} = 3.64 \text{ }\mu\text{A}$$

$$P = I_{\text{eff}}^2 \cdot R = (3.64 \text{ }\mu\text{A})^2 \cdot 580 \text{ k}\Omega = 7.7 \text{ mW}$$

Exercise E1 Complex Impedance Circuit

(written test, approx. 15 % of a 60-minute written test, WS2022)

1. Calculate the complex impedance Z for the circuit in Fig. 1. The voltage source $u(t) = 3.0 \sin(2\pi \cdot 15 \text{ kHz} \cdot t) \text{ V}$ is connected in series with an inductor of $L = 330 \text{ }\mu\text{H}$ and a capacitor of $C = 0.22 \text{ }\mu\text{F}$. All components are in series.

Solution:

$$Z_L = j\omega L = j2\pi \cdot 15 \text{ kHz} \cdot 330 \text{ }\mu\text{H} = j3.16 \text{ }\Omega$$

$$Z_C = \frac{1}{j\omega C} = \frac{1}{j2\pi \cdot 15 \text{ kHz} \cdot 0.22 \text{ }\mu\text{F}} = -j1.59 \text{ }\Omega$$

$$Z_R = R_1 + R_2 + R_3 = 100 \text{ k}\Omega + 470 \text{ k}\Omega + 10 \text{ k}\Omega = 580 \text{ k}\Omega$$

$$Z_{RLC} = Z_R + Z_L + Z_C = 580 \text{ k}\Omega + j3.16 \text{ }\Omega - j1.59 \text{ }\Omega = 580 \text{ k}\Omega + j1.57 \text{ }\Omega$$

$$|Z_{RLC}| = \sqrt{(580 \text{ k}\Omega)^2 + (1.57 \text{ }\Omega)^2} \approx 580 \text{ k}\Omega$$

$$\angle Z_{RLC} = \arctan\left(\frac{1.57 \text{ }\Omega}{580 \text{ k}\Omega}\right) \approx 0.03^\circ$$

Result:

$$Z = 580 \text{ k}\Omega + j1.57 \text{ }\Omega$$

$$|Z| = 580 \text{ k}\Omega$$


$$\angle Z = 0.03^\circ$$


$$I = \frac{U}{|Z|} = \frac{3.0 \text{ V}}{580 \text{ k}\Omega} = 5.17 \text{ }\mu\text{A}$$

$$I_{\text{eff}} = \frac{I}{\sqrt{2}} = 3.64 \text{ }\mu\text{A}$$

$$P = I_{\text{eff}}^2 \cdot R = (3.64 \text{ }\mu\text{A})^2 \cdot 580 \text{ k}\Omega = 7.7 \text{ mW}$$

1 2 3 4 5 6 7 8 9 10 ..





From:

<https://wiki.mexle.te.hs-heilbronn.de/> - **MEXLE Wiki**

Permanent link:

https://wiki.mexle.te.hs-heilbronn.de/electrical_engineering_1/ws2022_exam?rev=1680387346

Last update: **2023/04/02 00:15**

