

Exam Winter Semester 2022

Student Group

First Name	Surname	Matrikel Nr.

Table of Contents

Exercise E1 Resistance of a Wire by Resistivity (written test, approx. 6 % of a 60-minute written test, WS2022)	3
Exercise E1 Resistance of a Wire by Resistivity (written test, approx. 6 % of a 60-minute written test, WS2022)	3
Exercise E1 Temperature-dependent Resistance (written test, approx. 6 % of a 60-minute written test, WS2022)	3
Exercise E2 Temperature-dependent Resistance (written test, approx. 6 % of a 60-minute written test, WS2022)	4
Exercise E1 Pure Resistor Network Simplification (written test, approx. 13 % of a 60-minute written test, WS2022)	5
Exercise E3 Pure Resistor Network Simplification (written test, approx. 13 % of a 60-minute written test, WS2022)	6
Exercise E1 Equivalent linear Source (written test, approx. 14 % of a 60-minute written test, WS2022)	8
Exercise E4 Equivalent linear Source (written test, approx. 14 % of a 60-minute written test, WS2022)	12
Exercise E1 Charging Capacitors (written test, approx. 16 % of a 60-minute written test, WS2022)	16
Exercise E5 Charging Capacitors (written test, approx. 16 % of a 60-minute written test, WS2022)	17
Exercise E1 Analyzing complex Impedances (written test, approx. 14 % of a 60-minute written test, WS2022)	19
Exercise E6 Analyzing complex Impedances (written test, approx. 14 % of a 60-minute written test, WS2022)	19
Exercise E1 Impedances at different Frequencies (written test, approx. 18 % of a 60-minute written test, WS2022)	20
Exercise E7 Impedances at different Frequencies (written test, approx. 18 % of a 60-minute written test, WS2022)	20
Exercise E1 Complex Impedance Circuit (written test, approx. 15 % of a 60-minute written test, WS2022)	

test, WS2022)	21
Exercise E8 Complex Impedance Circuit (written test, approx. 15 % of a 60-minute written	
test, WS2022)	24

Exercise E1 Resistance of a Wire by Resistivity (written test, approx. 6 % of a 60-minute written test, WS2022)

A heating element made of solid nichrome wire with a cross-section of 1.80 mm^2 is used. The electric power dissipation (= heat flow) of $P=40 \text{ W}$ is necessary.

Determine the current I needed for operation.

The Nichrome wire has a resistivity of $1.10 \cdot 10^{-6} \text{ } \Omega \cdot \text{m}$.

The heating element is 3 m long and has a diameter of 3.57 mm .

∴ Calculate the resistance R of the heating element.

Solution

$$\begin{aligned} P &= U \cdot I = R \cdot I^2 \quad \rightarrow \quad I = \\ \sqrt{\frac{P}{R}} &= \sqrt{\frac{40 \text{ W}}{0.33 \text{ } \Omega}} \end{aligned}$$

$$\begin{aligned} R &= \rho \cdot \frac{l}{A} \quad | \quad \text{with } A = r^2 \cdot \pi = \\ \frac{1}{4} d^2 \cdot \pi \quad | \quad R &= \rho \cdot \frac{4 \cdot l}{d^2 \cdot \pi} \quad \& \quad R = \\ 1.10 \cdot 10^{-6} \text{ } \Omega \cdot \text{m} \cdot \frac{4 \cdot 3 \text{ m}}{(3.57 \cdot 10^{-3} \text{ m})^2 \cdot \pi} \quad \& \quad \end{aligned}$$

Exercise E1 Resistance of a Wire by Resistivity (written test, approx. 6 % of a 60-minute written test, WS2022)

A heating element made of solid nichrome wire with a cross-section of 1.80 mm^2 is used. The electric power dissipation (= heat flow) of $P=40 \text{ W}$ is necessary.

Determine the current I needed for operation.

The Nichrome wire has a resistivity of $1.10 \cdot 10^{-6} \text{ } \Omega \cdot \text{m}$.

The heating element is 3 m long and has a diameter of 3.57 mm .

∴ Calculate the resistance R of the heating element.

Solution

$$\begin{aligned} P &= U \cdot I = R \cdot I^2 \quad \rightarrow \quad I = \\ \sqrt{\frac{P}{R}} &= \sqrt{\frac{40 \text{ W}}{0.33 \text{ } \Omega}} \end{aligned}$$

$$\begin{aligned} R &= \rho \cdot \frac{l}{A} \quad | \quad \text{with } A = r^2 \cdot \pi = \\ \frac{1}{4} d^2 \cdot \pi \quad | \quad R &= \rho \cdot \frac{4 \cdot l}{d^2 \cdot \pi} \quad \& \quad R = \\ 1.10 \cdot 10^{-6} \text{ } \Omega \cdot \text{m} \cdot \frac{4 \cdot 3 \text{ m}}{(3.57 \cdot 10^{-3} \text{ m})^2 \cdot \pi} \quad \& \quad \end{aligned}$$

Exercise E1 Temperature-dependent Resistance

(written test, approx. 6 % of a 60-minute written test, WS2022)

2. A refrigerator, as shown in the figure, has a temperature coefficient of resistance $\alpha = 0.01 \text{ K}^{-1}$ and a temperature coefficient of resistance $\beta = 71 \text{ K}^{-2}$. Its temperature coefficients are: $\alpha = 0.01 \text{ K}^{-1}$ and $\beta = 71 \text{ K}^{-2}$.

Result: The temperature inside the refrigeration system can reach down to -40°C .

Result: The temperature inside the refrigeration system can reach down to -40°C .

Result: The temperature inside the refrigeration system can reach down to -40°C .

Result: The temperature inside the refrigeration system can reach down to -40°C .

Therefore, with constant U and increasing R the power decreases. Ten times more resistance decreases the heat flow to one-tenth.

$$R = R_0 (1 + \alpha \Delta T + \beta \Delta T^2) \quad \text{with } \Delta T = T_{\text{end}} - T_{\text{start}} \\ R = 10 \text{ k}\Omega \cdot \left((1 + 0.01 \text{ K}^{-1} \cdot (-40^\circ\text{C} - 25^\circ\text{C}) + 71 \text{ K}^{-2} \cdot (-40^\circ\text{C} - 25^\circ\text{C})^2) \right)$$

Exercise E2 Temperature-dependent Resistance**(written test, approx. 6 % of a 60-minute written test, WS2022)**

2. A refrigerator, as shown in the figure, has a temperature coefficient of resistance $\alpha = 0.01 \text{ K}^{-1}$ and a temperature coefficient of resistance $\beta = 71 \text{ K}^{-2}$. Its temperature coefficients are: $\alpha = 0.01 \text{ K}^{-1}$ and $\beta = 71 \text{ K}^{-2}$.

Result: The temperature inside the refrigeration system can reach down to -40°C .

Result: The temperature inside the refrigeration system can reach down to -40°C .

Result: The temperature inside the refrigeration system can reach down to -40°C .

Result: The temperature inside the refrigeration system can reach down to -40°C .

Therefore, with constant U and increasing R the power decreases. Ten times more resistance decreases the heat flow to one-tenth.

$$R = R_0 (1 + \alpha \Delta T + \beta \Delta T^2) \quad \text{with } \Delta T = T_{\text{end}} - T_{\text{start}} \\ R = 10 \text{ k}\Omega \cdot \left((1 + 0.01 \text{ K}^{-1} \cdot (-40^\circ\text{C} - 25^\circ\text{C}) + 71 \text{ K}^{-2} \cdot (-40^\circ\text{C} - 25^\circ\text{C})^2) \right)$$

Exercise E1 Pure Resistor Network Simplification


(written test, approx. 13 % of a 60-minute written test, WS2022)

The following shall now be closed and integrated, $R_2 = R_3 = 100 \Omega$ and the switch between R_3 and R_4 shall be open. Calculate the equivalent resistance R_{eq} between A and B .

Solution

$$R_{eq} = 133.8 \Omega$$

Now a wye-delta transformation is necessary.



Since $R_2 = R_3$ and based on the equations for the transformation, the transformed R_Y is given as:


$$R_Y = \frac{R_2 \cdot R_2}{R_2 + R_2 + R_2} = \frac{(100 \Omega)^2}{3 \cdot 100 \Omega} = \frac{1}{3} \cdot 100 \Omega = 33.33 \Omega$$

The equivalent resistor is given by a parallel configuration of resistors in series:

$$R_{eq} = R_Y + (R_Y + R_1 + R_1) \parallel (R_Y + R_2) \parallel R_{eq} = 33.33 \Omega + (33.33 \Omega + 400 \Omega) \parallel (33.33 \Omega + 100 \Omega)$$

.. The switch shall now be open. Calculate the equivalent resistance R_{eq} between A and B .

Solution



The equivalent resistor is given by a parallel configuration of resistors in series:

$$R_{\text{eq}} = (R_2 + R_1 + R_1) \parallel (R_2 + R_2) \parallel R_{\text{eq}} = (100 \sim \Omega + 200 \sim \Omega + 200 \sim \Omega) \parallel (100 \sim \Omega + 100 \sim \Omega) \parallel R_{\text{eq}} = (500 \sim \Omega) \parallel (200 \sim \Omega) \parallel R_{\text{eq}} = \frac{500 \sim \Omega \cdot 200 \sim \Omega}{500 \sim \Omega + 200 \sim \Omega} \parallel$$


Exercise E3 Pure Resistor Network Simplification (written test, approx. 13 % of a 60-minute written test, WS2022)

The following shall be solved with \$R_1=200 \sim \Omega\$, \$R_2=R_3=150 \sim \Omega\$ and the source \$B\$ given. \$R_{\text{B}}\$.

Solution

$$R_{\text{eq}} = 132.8 \sim \Omega$$

Now a wye-delta transformation is necessary.




Since $R_2 = R_3$ and based on the equations for the transformation, the transformed R_Y is given as:
$$R_Y = \frac{R_2 \cdot R_2}{R_2 + R_2 + R_2} = \frac{(100 \, \Omega)^2}{3 \cdot 100 \, \Omega} = \frac{1}{3} \cdot 100 \, \Omega = 33.33 \, \Omega$$

The equivalent resistor is given by a parallel configuration of resistors in series:

$$R_{\text{eq}} = R_Y + (R_Y + R_1 + R_1) \parallel (R_Y + R_2) \parallel R_{\text{eq}} = 33.33 \, \Omega + (33.33 \, \Omega + 400 \, \Omega) \parallel (33.33 \, \Omega + 100 \, \Omega)$$

1. The switch shall now be open. Calculate the equivalent resistance R_{eq} between A and B .

Solution



The equivalent resistor is given by a parallel configuration of resistors in series:

$$\begin{aligned} R_{\text{eq}} &= (R_2 + R_1 + R_3) \parallel (R_4 + R_5) \\ R_{\text{eq}} &= (100 \, \Omega + 200 \, \Omega + 200 \, \Omega) \parallel (100 \, \Omega + 100 \, \Omega) \\ R_{\text{eq}} &= (500 \, \Omega) \parallel (200 \, \Omega) \\ R_{\text{eq}} &= \frac{500 \, \Omega \cdot 200 \, \Omega}{500 \, \Omega + 200 \, \Omega} \end{aligned}$$


Exercise E1 Equivalent linear Source

(written test, approx. 14 % of a 60-minute written test, WS2022)

The circuit in the following has to be simplified.

Result

$$\begin{aligned} U_s &= U_{\text{AB}} = 4.5 \, \text{V} \\ R_i &= R_{\text{AB}} = 6 \, \Omega \end{aligned}$$




Calculate the internal resistance R_{int} and the source voltage U_s of an equivalent linear voltage source on the connectors A and B.

$R_1 = 5.0 \, \Omega$, $U_2 = 6.0 \, \text{V}$, $R_3 = 10 \, \Omega$, $I_4 = 4.2 \, \text{A}$,
 $R_5 = 10 \, \Omega$, $R_6 = 7.5 \, \Omega$, $R_7 = 15 \, \Omega$


Use equivalent sources in order to simplify the circuit!

Solution

The best thing is to re-think the wiring like rubber bands and adjust them:



The linear voltage source of U_2 and R_1 can be transformed into a current source $I_2 = \frac{U_2}{R_1}$ and R_1 :



Now a lot of them can be combined. The resistors R_1 , R_3 , R_5 are in parallel, like also I_2 and I_4 :

$$R_{135} = R_1 || R_3 || R_5$$

$$I_{24} = I_2 - I_4 = \frac{U_2}{R_1} - I_4$$

The resulting circuit can again be transformed:



Here, the U_{24} is calculated by I_{24} as the following:

$$U_{24} = I_{24} \cdot R_{135}$$

$$U_{24} = U_2 \cdot \frac{R_7}{R_6 + R_7 + R_1 || R_3 || R_5} = (U_2 - U_4) \cdot \frac{R_1 || R_3 || R_5}{R_6 + R_7 + R_1 || R_3 || R_5}$$

On the right side of the last circuit, there is a voltage divider given by R_{135} , R_6 , and R_7 .

Therefore the voltage between A and B is given as:

$$U_{AB} = U_{24} \cdot \frac{R_7}{R_6 + R_7 + R_1 || R_3 || R_5} = (U_2 - U_4) \cdot \frac{R_7 \cdot R_1 || R_3 || R_5}{R_6 + R_7 + R_1 || R_3 || R_5}$$

For the internal resistance R_i the ideal voltage source is substituted by its resistance ($= 0 \Omega$, so a short-circuit):

$$R_{AB} = R_7 || (R_6 + R_1 || R_3 || R_5)$$


with $R_1 || R_3 || R_5 = 5 \Omega || 10 \Omega || 10 \Omega = 5 \Omega || 5 \Omega = 2.5 \Omega$:

$$U_{AB} = \frac{6.0 \text{ V}}{5.0 \Omega} - 4.2 \Omega \cdot \frac{15 \Omega \cdot 2.5 \Omega}{7.5 \Omega + 15 \Omega + 2.5 \Omega} \quad R_{AB} = 15 \Omega || (7.5 \Omega + 2.5 \Omega)$$

Exercise E4 Equivalent linear Source (written test, approx. 14 % of a 60-minute written test, WS2022)

The circuit in the following has to be simplified.
Result


$$U_s = U_{AB} = 4.5 \text{ V} \quad R_i = R_{AB} = 6 \Omega$$




Calculate the internal resistance R_{int} and the source voltage U_s of an equivalent linear voltage source on the connectors A and B. $\begin{aligned} R_1 &= 5.0 \, \Omega, \quad U_2 = 6.0 \, \text{V}, \quad R_3 = 10 \, \Omega, \quad I_4 = 4.2 \, \text{A}, \\ R_5 &= 10 \, \Omega, \quad R_6 = 7.5 \, \Omega, \quad R_7 = 15 \, \Omega \end{aligned}$ Use equivalent sources in order to simplify the circuit!

Solution

The best thing is to re-think the wiring like rubber bands and adjust them:



The linear voltage source of U_2 and R_1 can be transformed into a current source $I_2 = \frac{U_2}{R_1}$ and R_1 :



Now a lot of them can be combined. The resistors R_1 , R_3 , R_5 are in parallel, like also I_2 and I_4 :

$$R_{135} = R_1 || R_3 || R_5$$

$$I_{24} = I_2 - I_4 = \frac{U_2}{R_1} - I_4$$

The resulting circuit can again be transformed:



Here, the U_{24} is calculated by I_{24} as the following:

$$U_{24} = I_{24} \cdot R_{135}$$

$$U_{AB} = U_{24} \cdot \left(\frac{U_2}{R_1} - I_4 \right) \cdot R_1 \parallel R_3 \parallel R_5$$

On the right side of the last circuit, there is a voltage divider given by R_{135} , R_6 , and R_7 .

Therefore the voltage between A and B is given as:

$$U_{AB} = U_{24} \cdot \left(\frac{R_7}{R_6 + R_7 + R_1 \parallel R_3 \parallel R_5} \right) \cdot \left(\frac{U_2}{R_1} - I_4 \right) \cdot R_1 \parallel R_3 \parallel R_5$$

For the internal resistance R_i the ideal voltage source is substituted by its resistance ($=0\Omega$, so a short-circuit):

$$R_{AB} = R_7 \parallel (R_6 + R_1 \parallel R_3 \parallel R_5)$$

with $R_1 \parallel R_3 \parallel R_5 = 5\Omega \parallel 10\Omega \parallel 10\Omega = 5\Omega \parallel 5\Omega = 2.5\Omega$:

$$U_{AB} = \left(\frac{6.0\text{V}}{5.0\Omega} - 4.2\text{A} \right) \cdot \left(\frac{15\Omega \cdot 2.5\Omega}{7.5\Omega + 15\Omega + 2.5\Omega} \right) \parallel R_{AB} = 15\Omega \parallel (7.5\Omega + 2.5\Omega)$$

Exercise E1 Charging Capacitors


(written test, approx. 16 % of a 60-minute written test, WS2022)

The circuit below is a fully charged circuit with a 10V DC voltage source, a 2Ω resistor, a 2F capacitor, and a 2A current source. The voltage across the capacitor is again 0V at the moment $t_0=0\text{s}$ when the switch S_1 is closed. Calculate the voltage $u_c(t_2)$ across the capacitor at $t_2=1\text{ms}$ after closing the switch.


Hint: To solve this, first create an equivalent linear voltage source from U , R_1 , and R_2 .

$$U_{eq} = \frac{U \cdot R_2}{R_1 + R_2} = \frac{10\text{V} \cdot 2\Omega}{2\Omega + 2\Omega} = 5\text{V}$$

On an alternative view, one can try to create an equivalent linear voltage source again. Then, the internal resistance is given by substituting the ideal voltage source is again short-circuiting R_2 .




The circuit contains a voltage source $U=12\text{ V}$, a switch S_1 , a resistor of $R_1=20\text{ }\Omega$ and a capacitor of $C=100\text{ }\mu\text{F}$. The switch S_2 to an additional consumer R_2 will be considered to be open for the first task. At the moment $t_0=0\text{ s}$ the switch S_1 is closed, the voltage across the capacitor is $u_c(t_0)=0\text{ V}$.



First do not consider the light bulb - it is not connected to the RC circuit. Calculate the point of time t_1 when $u_c(t_1)=0.5 \cdot U$.

Solution



So, here only R_1 and C gives the time constant: $\tau = R_1 \cdot C$

The following formula describes the time course of $u_C(t)$ which has to be $u_c(t_1)=0.5 \cdot U$:
$$u_c(t) = U \cdot (1 - e^{-t/\tau}) = 0.5 \cdot U$$
 It has to be rearranged to $(1 - e^{-t/\tau}) = 0.5$. An equivalent linear voltage source can be given with U_s , R_1 , and R_B as seen in yellow.

Therefore, the voltage of the equivalent linear voltage source is: $U_s = U \cdot \frac{R_B}{R_1 + R_B} = \frac{1}{2} \cdot U$. The internal resistance is given by substituting the ideal voltage source with its resistance ($=0\text{ }\Omega$, short-circuit).
$$R_i = R_1 \parallel R_B = 10\text{ }\Omega$$

$$u_c(t_2) = U_s \cdot (1 - e^{-t_2/(R_i \cdot C)}) = \frac{1}{2} \cdot U \cdot (1 - e^{-1\text{ ms}/(10\text{ }\Omega \cdot 100\text{ }\mu\text{F})})$$

Exercise E5 Charging Capacitors

(written test, approx. 16 % of a 60-minute written test, WS2022)

The circuit (see the solution) consists of a 12 V voltage source, a $20\text{ }\Omega$ resistor, a $100\text{ }\mu\text{F}$ capacitor, a $20\text{ }\Omega$ resistor, and a light bulb. The voltage across the capacitor is again 0 V at the moment $t_0=0\text{ s}$ when the switch S_1 is closed. Calculate the voltage $u_c(t_2)$ across the capacitor at $t_2=1\text{ ms}$ after closing the switch.


Solution

To solve this, first create an equivalent linear voltage source from U , R_1 , and R_B .
$$U_s = U \cdot \frac{R_B}{R_1 + R_B} = \frac{1}{2} \cdot U = 6\text{ V}$$

Solution

The ideal voltage source is given by $U_s = U \cdot \frac{R_1}{R_1 + R_B}$ and the internal resistance is given by $R_i = R_1 \parallel R_B$.

On an alternative view, one can try to create an equivalent linear voltage source again. Then, the internal resistance is given by substituting the ideal voltage source is again short-circuiting R_2 .




The circuit contains a voltage source $U = 12 \text{ V}$, a switch S_1 , a resistor of $R_1 = 20 \text{ }\Omega$ and a capacitor of $C = 100 \text{ }\mu\text{F}$.

The switch S_2 to an additional consumer R_2 will be considered to be open for the first tasks. At the moment $t_0 = 0$ the switch S_1 is closed, the voltage across the capacitor is $u_c(t_0) = 0 \text{ V}$.

First do not consider the light bulb - it is not connected to the RC circuit.

Calculate the point of time t_1 when $u_c(t_1) = 0.5 \cdot U$.



Solution

An equivalent linear voltage source can be given with U_s , R_1 , and R_B as seen in yellow.

Therefore, the voltage of the equivalent linear voltage source is: $U_s = U \cdot \frac{R_B}{R_1 + R_B} = \frac{1}{2} \cdot U$. The internal resistance is given by substituting the ideal voltage source with its resistance ($R_i = 0 \text{ }\Omega$, short-circuit).

$$R_i = R_1 \parallel R_B = 10 \text{ }\Omega$$

So, here only R_1 and C gives the time constant: $\tau = R_1 \cdot C$

The following formula describes the time course of $u_c(t)$ which has to be $u_c(t_1) = 0.5 \cdot U$:

$$u_c(t) = U \cdot (1 - e^{-t/\tau}) = 0.5 \cdot U$$

It has to be rearranged to t :

$$(1 - e^{-t/\tau}) = 0.5 \implies e^{-t/\tau} = 0.5 \implies -t/\tau = \ln(0.5) \implies t = -\tau \cdot \ln(0.5) = R_1 \cdot C \cdot \ln(0.5)$$

Exercise E1 Analyzing complex Impedances**(written test, approx. 14 % of a 60-minute written test, WS2022)**

2. Calculate the complex power $\underline{S}$ and the real power P and the reactive power Q in the circuit shown in the figure. The voltage $\underline{U}$ and the current $\underline{I}$ shall be given.

After analysis, the full bridge dimensioned impedance $\underline{Z}$ shall be extracted and the magnitude $|\underline{Z}|$ and the phase φ_Z shall be given. The current $\underline{I}$ shall be given in the form $\underline{I} = I_m \cdot e^{j(\omega t + \varphi_I)}$ and the voltage $\underline{U}$ shall be given in the form $\underline{U} = U_m \cdot e^{j(\omega t + \varphi_U)}$.

3. Calculate the physical values of the two components.

Solution: $\underline{R} = 10 \Omega$ and $\underline{X}_L = 4.68 \Omega$ (inductor) and $\underline{X}_C = 2.4 \Omega$ (capacitor)

Solution

$\underline{I} = \frac{\underline{U}}{\underline{Z}}$ and $\underline{Z} = \underline{R} + j\underline{X}_L - j\underline{X}_C$ $\underline{I} = \frac{50 \text{ V}}{10 \Omega + j4.68 \Omega - j2.4 \Omega} = \frac{50 \text{ V}}{10 \Omega + j2.28 \Omega} = 4.68 \text{ A} \cdot e^{-j27.96^\circ}$

The current and voltage are in phase since the impedance is purely real (the imaginary part is zero). The resulting impedance is $\underline{Z} = 10 \Omega + j2.28 \Omega$. Therefore, the component 4.68Ω is an inductor with the same absolute value of 4.68Ω as the component 2.4Ω is a capacitor with the same absolute value of 2.4Ω . The phase φ_Z can be calculated as $\varphi_Z = \arctan\left(\frac{\text{Im}(\underline{Z})}{\text{Re}(\underline{Z})}\right) = \arctan\left(\frac{2.28}{10}\right) = 12.96^\circ$. The magnitude $|\underline{Z}|$ can be calculated as $|\underline{Z}| = \sqrt{10^2 + 2.28^2} = 10.26 \Omega$. The phase φ_Z can be calculated as $\varphi_Z = \arctan\left(\frac{\text{Im}(\underline{Z})}{\text{Re}(\underline{Z})}\right) = \arctan\left(\frac{2.28}{10}\right) = 12.96^\circ$. The phase φ_Z can be calculated as $\varphi_Z = \arctan\left(\frac{\text{Im}(\underline{Z})}{\text{Re}(\underline{Z})}\right) = \arctan\left(\frac{2.28}{10}\right) = 12.96^\circ$.

Exercise E6 Analyzing complex Impedances**(written test, approx. 14 % of a 60-minute written test, WS2022)**

2. Calculate the complex power $\underline{S}$ and the real power P and the reactive power Q in the circuit shown in the figure. The voltage $\underline{U}$ and the current $\underline{I}$ shall be given.

After analysis, the full bridge dimensioned impedance $\underline{Z}$ shall be extracted and the magnitude $|\underline{Z}|$ and the phase φ_Z shall be given. The current $\underline{I}$ shall be given in the form $\underline{I} = I_m \cdot e^{j(\omega t + \varphi_I)}$ and the voltage $\underline{U}$ shall be given in the form $\underline{U} = U_m \cdot e^{j(\omega t + \varphi_U)}$.

3. Calculate the physical values of the two components.

Solution: $\underline{R} = 10 \Omega$ and $\underline{X}_L = 4.68 \Omega$ (inductor) and $\underline{X}_C = 2.4 \Omega$ (capacitor)

Solution

$\underline{I} = \frac{\underline{U}}{\underline{Z}}$ and $\underline{Z} = \underline{R} + j\underline{X}_L - j\underline{X}_C$ $\underline{I} = \frac{50 \text{ V}}{10 \Omega + j4.68 \Omega - j2.4 \Omega} = \frac{50 \text{ V}}{10 \Omega + j2.28 \Omega} = 4.68 \text{ A} \cdot e^{-j27.96^\circ}$

The current and voltage are in phase since the impedance is purely real (the imaginary part is zero). The resulting impedance is $\underline{Z} = 10 \Omega + j2.28 \Omega$. Therefore, the component 4.68Ω is an inductor with the same absolute value of 4.68Ω as the component 2.4Ω is a capacitor with the same absolute value of 2.4Ω . The phase φ_Z can be calculated as $\varphi_Z = \arctan\left(\frac{\text{Im}(\underline{Z})}{\text{Re}(\underline{Z})}\right) = \arctan\left(\frac{2.28}{10}\right) = 12.96^\circ$. The magnitude $|\underline{Z}|$ can be calculated as $|\underline{Z}| = \sqrt{10^2 + 2.28^2} = 10.26 \Omega$. The phase φ_Z can be calculated as $\varphi_Z = \arctan\left(\frac{\text{Im}(\underline{Z})}{\text{Re}(\underline{Z})}\right) = \arctan\left(\frac{2.28}{10}\right) = 12.96^\circ$. The phase φ_Z can be calculated as $\varphi_Z = \arctan\left(\frac{\text{Im}(\underline{Z})}{\text{Re}(\underline{Z})}\right) = \arctan\left(\frac{2.28}{10}\right) = 12.96^\circ$.

The absolute value of the impedance is $Z = \sqrt{(0.24 \sim \Omega)^2 + (4.68 \sim \Omega)^2} = 4.7 \sim \Omega$.
 The phase φ is $\varphi = \arctan\left(\frac{4.68}{0.24}\right) = 87.1^\circ$.
 With the complex part comes the physical value: $X_L = \omega L = 2\pi f L = 2\pi \cdot 4.7 \sim \Omega \cdot 10^{-6} \text{ s} = 29.4 \sim \mu\Omega$.
 The phase φ is $\varphi = \arctan\left(\frac{4.68}{0.24}\right) = 87.1^\circ$.
 The phase φ is $\varphi = \arctan\left(\frac{4.68}{0.24}\right) = 87.1^\circ$.

Exercise E1 Impedances at different Frequencies

(written test, approx. 18 % of a 60-minute written test, WS2022)

A series circuit means that the current is constant on every component.
 The equivalent impedance for R and L combined is given by $Z = \sqrt{R^2 + X_L^2}$.
 Back to the first formula: $R_3 \cdot I_3 = X_{L3} \cdot I_3 = X_{L3} \cdot \frac{U}{Z}$.
 Result: $R_3 = \frac{X_{L3} \cdot U}{Z} = \frac{2\pi f L \cdot U}{Z}$.
 Back to the first formula: $R_3 \cdot I_3 = X_{L3} \cdot I_3 = X_{L3} \cdot \frac{U}{Z}$.
 Result: $R_3 = \frac{X_{L3} \cdot U}{Z} = \frac{2\pi f L \cdot U}{Z}$.

Solution

$R_1 = 1.00 \sim \Omega$

$R_2 = 10.0 \sim \Omega$

A series circuit means that the current is constant on every component.

The equivalent impedance for R and L combined is given by $Z = \sqrt{R^2 + X_L^2}$.

Parallel circuit means that the voltage is the same on R_2 and C_2 .
 $\frac{U}{Z} = \frac{U}{R_2 + X_{L2}}$.
 $\frac{U}{Z} = \frac{U}{R_2 + X_{L2}}$.
 $\frac{U}{Z} = \frac{U}{R_2 + X_{L2}}$.

$\frac{U}{Z} = \frac{U}{R_2 + X_{L2}}$.
 $\frac{U}{Z} = \frac{U}{R_2 + X_{L2}}$.
 $\frac{U}{Z} = \frac{U}{R_2 + X_{L2}}$.

Therefore, the resulting current of the parallel circuit is given as:

$I_3 = \frac{U}{Z} = \frac{U}{R_2 + X_{L2}}$

Back to the first formula: $R_3 \cdot I_3 = X_{L3} \cdot I_3 = X_{L3} \cdot \frac{U}{Z}$.
 Result: $R_3 = \frac{X_{L3} \cdot U}{Z} = \frac{2\pi f L \cdot U}{Z}$.

Back to the first formula: $R_3 \cdot I_3 = X_{L3} \cdot I_3 = X_{L3} \cdot \frac{U}{Z}$.

Result: $R_3 = \frac{X_{L3} \cdot U}{Z} = \frac{2\pi f L \cdot U}{Z}$.

Back to the first formula: $R_3 \cdot I_3 = X_{L3} \cdot I_3 = X_{L3} \cdot \frac{U}{Z}$.

Result: $R_3 = \frac{X_{L3} \cdot U}{Z} = \frac{2\pi f L \cdot U}{Z}$.

Back to the first formula: $R_3 \cdot I_3 = X_{L3} \cdot I_3 = X_{L3} \cdot \frac{U}{Z}$.

Exercise E7 Impedances at different Frequencies

(written test, approx. 18 % of a 60-minute written test, WS2022)

Exercise E1 Complex Impedance Circuit
(written test, approx. 15 % of a 60-minute written test, WS2022)

1. Calculate the equivalent impedance Z for the circuit shown in the AC network diagram of Fig. 1. The AC voltage source $u(t) = 3.0 \sin(2\pi \cdot 15 \text{ kHz} \cdot t) \text{ V}$ is connected in series with an inductor of $L = 330 \text{ } \mu\text{H}$ and a capacitor of $C = 0.22 \text{ } \mu\text{F}$. All components, voltages, and currents are given in the diagram.

Solution

Result

Solution

Solution

A series circuit means that the current is constant on every component.

The equivalent impedance for R and L combined is given by

Parallel circuit means that the voltage is the same on R_1 and R_2 .

$$\underline{U} = \underline{U}_1 = \underline{U}_2$$

$$\underline{I} = \underline{I}_1 + \underline{I}_2$$

$$\underline{U} = \underline{I}_1 R_1 = \underline{I}_2 R_2$$

$$\underline{I}_1 = \frac{\underline{U}}{R_1}$$

$$\underline{I}_2 = \frac{\underline{U}}{R_2}$$

$$\underline{I} = \underline{U} \left(\frac{1}{R_1} + \frac{1}{R_2} \right)$$

$$\underline{I} = \underline{U} \frac{R_1 + R_2}{R_1 R_2}$$

$$\underline{U} = \underline{I} \frac{R_1 R_2}{R_1 + R_2}$$

$$\underline{U} = \underline{I} \underline{Z}$$

$$\underline{Z} = \frac{R_1 R_2}{R_1 + R_2}$$

Therefore, the resulting current of the parallel circuit is given as:

$$\underline{I} = \frac{\underline{U}}{\underline{Z}} = \frac{\underline{U} (R_1 + R_2)}{R_1 R_2}$$

Back to the first formula:
$$\underline{U} = \underline{I} \underline{Z}$$

$$\underline{U} = \frac{\underline{U} (R_1 + R_2)}{R_1 R_2} \underline{Z}$$

$$\underline{U} = \frac{\underline{U} (R_1 + R_2)}{R_1 R_2} \underline{Z}$$

$$\underline{U} = \frac{\underline{U} (R_1 + R_2)}{R_1 R_2} \underline{Z}$$

$$\underline{U} = \frac{\underline{U} (R_1 + R_2)}{R_1 R_2} \underline{Z}$$

$$\underline{U} = \frac{\underline{U} (R_1 + R_2)}{R_1 R_2} \underline{Z}$$

$$\underline{U} = \frac{\underline{U} (R_1 + R_2)}{R_1 R_2} \underline{Z}$$

$$\underline{U} = \frac{\underline{U} (R_1 + R_2)}{R_1 R_2} \underline{Z}$$

Exercise E1 Complex Impedance Circuit

(written test, approx. 15 % of a 60-minute written test, WS2022)

1. Calculate the equivalent impedance Z for the circuit shown in the AC network diagram of Fig. 1. The AC voltage source $u(t) = 3.0 \sin(2\pi \cdot 15 \text{ kHz} \cdot t) \text{ V}$ is connected in series with an inductor of $L = 330 \text{ } \mu\text{H}$ and a capacitor of $C = 0.22 \text{ } \mu\text{F}$. All components, voltages, and currents are given in the diagram.

Solution

Result

Solution

Solution

$$\underline{Z} = \frac{R_1 R_2}{R_1 + R_2}$$

$$\underline{Z} = \frac{R_1 R_2}{R_1 + R_2}$$

$$\underline{Z} = \frac{R_1 R_2}{R_1 + R_2}$$

$$\underline{Z} = \frac{R_1 R_2}{R_1 + R_2}$$

$$\underline{Z} = \frac{R_1 R_2}{R_1 + R_2}$$

$$\underline{Z} = \frac{R_1 R_2}{R_1 + R_2}$$


$$\underline{Z} = \frac{R_1 R_2}{R_1 + R_2}$$


$$\underline{Z} = \frac{R_1 R_2}{R_1 + R_2}$$

$$\underline{Z} = \frac{R_1 R_2}{R_1 + R_2}$$

$$\underline{Z} = \frac{R_1 R_2}{R_1 + R_2}$$

$$\underline{Z} = \frac{R_1 R_2}{R_1 + R_2}$$





From:

<https://wiki.mexle.te.hs-heilbronn.de/> - **MEXLE Wiki**

Permanent link:

https://wiki.mexle.te.hs-heilbronn.de/electrical_engineering_1/ws2022_exam?rev=1680388421

Last update: **2023/04/02 00:33**

