

Block 16 - Ampère's Law and Magnetomotive Force (MMF)

Student Group

First Name	Surname	Matrikel Nr.

Table of Contents

Block 16 - Ampère's Law and Magnetomotive Force (MMF)	2
<i>Learning objectives</i>	2
<i>Preparation at Home</i>	2
<i>90-minute plan</i>	2
<i>Conceptual overview</i>	2
<i>Core content</i>	2
<i>Generalization of the Magnetic Field Strength</i>	2
Notice:	3
Notice:	4
<i>Common pitfalls</i>	5
<i>Exercises</i>	5
Task 3.2.3 Magnetic Potential Difference	5
Exercise E1 Magnetic Voltage (written test, approx. 6 % of a 120-minute written test, SS2021)	7
Exercise E1 Magnetic Field Lines (written test, approx. 6 % of a 120-minute written test, SS2024)	8
Exercise E2 Magnetic Potential (written test, approx. 8 % of a 120-minute written test, SS2024)	9
Exercise E1 Fields of an coax Cable (written test, approx. 12 % of a 120-minute written test, SS2024)	10
<i>Embedded resources</i>	12

Block 16 - Ampère's Law and Magnetomotive Force (MMF)

Learning objectives

After this 90-minute block, you can

- ...

Preparation at Home

Well, again

- read through the present chapter and write down anything you did not understand.
- Also here, there are some clips for more clarification under 'Embedded resources' (check the text above/below, sometimes only part of the clip is interesting).

For checking your understanding please do the following exercises:

- ...

90-minute plan

1. Warm-up (x min):
 1.
2. Core concepts & derivations (x min):
 1. ...
3. Practice (x min): ...
4. Wrap-up (x min): Summary box; common pitfalls checklist.

Conceptual overview

1. ...

Core content

Generalization of the Magnetic Field Strength

So far, only the rotational symmetric problem on a single wire was considered in formula, when the current I and the length s of a magnetic field line around it is given:

$$\begin{aligned} \quad H_{\varphi} = \frac{I}{s} = \frac{I}{2 \cdot \pi \cdot r} \quad \Leftrightarrow \end{aligned}$$

$$\oint \vec{H} \cdot d\vec{s} = I_{\text{enc}} \quad \text{applies only to the long, straight conductor}$$

Now, this shall be generalized. For this purpose, we will look back at the electric field. For the electric field strength E of a capacitor with two plates at a distance of s and the potential difference U holds:

$$U = E \cdot s \quad \text{applies to capacitor only}$$

In words: The potential difference is given by adding up the field strength along the path of a probe from one plate to the other.

This was extended to the voltage between two points 1 and 2 . Additionally, we know by Kirchhoff's voltage law that the voltage on a closed path is "0".

$$\oint \vec{E} \cdot d\vec{s} = 0$$

We can now try to look for similarities. Also for the magnetic field, the magnitude of the field strength is summed up along a path to arrive at another field-describing quantity.

Because of the similarity the so-called **magnetic potential difference V_m** between point 1 and 2 is introduced:

$$V_m = \int \vec{H} \cdot d\vec{s} \quad \text{applies to rotational symmetric problems only}$$

$$V_m = \int \vec{H} \cdot d\vec{s} = \theta$$

We need to take a closer look here. Any closed path in the static electric field leads to a potential difference of $\oint \vec{E} \cdot d\vec{s} = 0$.

BUT: closed paths in the static magnetic field leads to a magnetic potential difference which is **not mandatorily** 0 ! $V_m = \oint \vec{H} \cdot d\vec{s} = \theta$

Another new quantity is introduced: the **magnetic voltage θ** :

1. The magnetic voltage θ is the magnetic potential difference on a closed path.
2. Since the magnetic voltage θ is valid for exactly one turn along our single wire, θ is also equal to the current through the wire:

$$\theta = I \quad \text{applies only to the long, straight conductor}$$
3. The magnetic potential difference can take a fraction or a multiple of one turn and is therefore **not mandatorily** equal to I .
4. The magnetic voltage is generalized in the following box.

Notice:

The path integral of the magnetic field strength along an arbitrary closed path is equal to the free currents (= current density) through the surface enclosed by the path.

The magnetic voltage θ (and therefore the current) is the cause of the magnetic field strength.

This leads to the **Ampere's Circuital Law**

$$\oint_{\vec{S}} \vec{H} \cdot d\vec{s} = \theta$$

The magnetic voltage θ can be given as

- $\theta = I$ for a single conductor
- $\theta = N \cdot I$ for a coil
- $\theta = \sum_n I_n$ for multiple conductors
- $\theta = \int_A \vec{S} \cdot d\vec{A}$ for any spatial distribution (see [block15](#))

The unit of the magnetic voltage θ is **Ampere** (or **Ampere-turns**).


In the english literature the magnetic voltage is called **Magnetomotive force**

Notice:

$\oint \vec{S} \cdot d\vec{A}$ and $\oint \vec{A} \cdot d\vec{s}$ in $\oint \vec{H} \cdot d\vec{s} = \theta = \int_A \vec{S} \cdot d\vec{A}$ build a right-hand system.

1. Once the thumb of the right hand is pointing along $\oint \vec{A} \cdot d\vec{s}$, the fingers of the right hand show the correct direction for $\oint \vec{S} \cdot d\vec{A}$ for positive $\oint \vec{H} \cdot d\vec{s}$ and $\oint \vec{S} \cdot d\vec{A}$
2. Currents into the direction of the right hand's thumb count positive. Currents antiparallel to it count negative.

Fig. 1: Right hand rule



Common pitfalls

- ...


Exercises

Task 3.2.3 Magnetic Potential Difference

Fig. 3: different trajectories around current-carrying conductors

Result 6)

$$6) \oint \vec{H} \cdot d\vec{l} = I_{enc} = 2.5 \text{ A} \quad \vec{H} = -2.5 \text{ A/m} \quad \vec{H} = -2.5 \text{ A/m}$$



Given are the adjacent closed trajectories in the magnetic field of current-carrying conductors (see figure 3). Let $I_1 = 2 \text{ A}$ and $I_2 = 4.5 \text{ A}$ be valid.

In each case, the magnetic potential difference V_{m} along the drawn path is sought.

Path

- The magnetic potential difference is given as the **sum of the current through the area within a closed path**.
- The direction of the current and the path have to be considered with the righthand rule.

Exercise E1 Magnetic Voltage


(written test, approx. 6 % of a 120-minute written test, SS2021)

The following images show cross-sections of electrical cables.

A closed path is shown as a dashed line. The magnetic voltage θ on these paths shall be analyzed.

The following values are given for the currents:

- $I_1 = 5 \text{ A}$ $I_2 = -4 \text{ A}$ $I_3 = 1 \text{ A}$ $I_4 = 4 \text{ A}$
- $I_3 = 1 \text{ A}$
 - $I_4 = 4 \text{ A}$



Specify which magnetic voltages $\theta_{(1)}$, $\theta_{(2)}$, and $\theta_{(3)}$ result. Note the direction of the path in each case!

Path

For the resulting current the direction of the path has to be considered with the right-hand rule:

- $I_{(1)} = +I_2 - I_1 - I_3 \quad \rightarrow \quad \theta_{(1)} = 2 \text{ A}$

- $\{ \sim \text{rm A} \} - 1 \{ \sim \text{rm A} \}$
- $\$I_{(2)} = +I_3 + I_4 - I_1 \quad \text{quad} \quad \text{rightarrow} \quad \text{quad} \quad \theta_{(2)} = 1 \{ \sim \text{rm A} \} + 4 \{ \sim \text{rm A} \} - 5 \{ \sim \text{rm A} \}$
- $\$I_{(3)} = +I_3 - I_4 - I_2 \quad \text{quad} \quad \text{rightarrow} \quad \text{quad} \quad \theta_{(3)} = 1 \{ \sim \text{rm A} \} - 4 \{ \sim \text{rm A} \} - 2 \{ \sim \text{rm A} \}$

Exercise E1 Magnetic Field Lines

(written test, approx. 6 % of a 120-minute written test, SS2024)


The following setup of a permanent magnet affects the H-field, based on the fundamental definition of the H-field.

- Four conductors are located perpendicular to the plane of the diagram

Result All of them conduct a current with the same magnitude, but not in the same direction.


- A permanent magnet is located in between the conductors.

- The H-field is defined by currents $\sum I = \int H \{ \text{rm d} \} s$.
- In the permanent magnet, there are no free currents.
- The bound currents (of the permanent magnet) create also an H field.
- This exits on the north pole and enters the magnet on the south pole (similar to the B-field)
- $H = B / \mu$
- The H-field from task 1 gets distracted



.. Do not consider the permanent magnet at first. Draw at least 10 field lines of the H-field qualitatively. Give a a correct representation of their direction, and density for the shown area.

Result



Exercise E2 Magnetic Potential

(written test, approx. 8 % of a 120-minute written test, SS2024)


Calculate the magnetic potential difference V_{m} for the following paths as shown by the solid lines.

Dotted lines are only for there for symmetry aspects!

The wires conduct the following currents:

- $|I_1| = 2 \text{ A}$
- $|I_2| = 5 \text{ A}$
- $|I_3| = 11 \text{ A}$
- $|I_4| = 7 \text{ A}$

Pay attention to the signs of the currents (given by the diagrams) and of the results!



Result

Based on the right-hand rule and the part of a full revolution the following results:

1. Task: $+I_1 - I_2 = -3 \text{ A}$
2. Task: $+ \frac{1}{4} I_3 = 11/4 \text{ A}$ (it does not matter which way the path goes from the startpoint to the endpoint, as long as it has the same direction and number of revolutions)
3. Task: $- \frac{1}{4} I_1 = -0.5 \text{ A}$
4. Task: $+2 \cdot I_2 - 1 \cdot I_3 = -1 \text{ A}$

Exercise E1 Fields of an coax Cable

(written test, approx. 12 % of a 120-minute written test, SS2024)

2. With the graph of the magnitude of $B(r)$ with r in mm (see diagram 4.0.6) the cross-section of the coax cable is given. The diagram shows the cross-section of the coax cable with the origin in the center of the cable. The diagram is given in the following diagram:

- Inner conductor: $+3.3 \text{ mA}$, $+10 \text{ nC}$ (current into the plane of the diagram)
- Outer conductor: -3.3 mA , -10 nC (current out of the plane of diagram)
- for $(0.1 \text{ mm} | 0)$: $B(r) = 3.28 \text{ A/m}$
- for $(0.55 \text{ mm} | 0)$: $B(r) = 0.985 \text{ A/m}$

The magnitude of the electric displacement field D can be calculated by: $\int D \cdot dA = Q$.

In general, the B -field is proportional to $\frac{1}{r}$ for the situation between both conductors. Here, for any position radial to the center, the surrounding area is the surface of a cylindrical shape (here for simplicity without the round endings).

Since the charges are within the surface of the conductor, there is no D -field within the conductor. This leads to: $D(r) = \frac{Q}{A} = \frac{Q}{2\pi r l}$ within a circle with the radius r .

Embedded resources

Explanation (video): ...

From:

<https://wiki.mexle.te.hs-heilbronn.de/> - **MEXLE Wiki**

Permanent link:

https://wiki.mexle.te.hs-heilbronn.de/electrical_engineering_and_electronics_1/block16?rev=1763838138

Last update: **2025/11/22 20:02**

