

rechnung_signalzeitverlauf_umkehrintegrator

Student Group

First Name	Surname	Matrikel Nr.

Table of Contents

\$I.\quad\$ Am Punkt \$t_1\$

$$U_A(t_1) = -\frac{1}{\tau} \cdot \int_{t_0}^{t_1} U_E \, dt + U_A(t_0)$$

$$U_A(t_1) = -\frac{1}{5 \, \text{ms}} \cdot \int_0^{10 \, \text{ms}} 1 \, dt + 0 \, \text{V}$$

$$U_A(t_1) = -\frac{1}{5 \, \text{ms}} \cdot 1 \, \text{V} \cdot \int_0^{10 \, \text{ms}} dt$$

$$U_A(t_1) = -\frac{1}{5 \, \text{ms}} \cdot 1 \, \text{V} \cdot [t]_0^{10 \, \text{ms}} = -2 \, \text{V}$$

\$I.\quad\$ Am Punkt \$t_2\$

$$U_A(t_1) = -\frac{1}{\tau} \cdot \int_{t_0}^{t_1} U_E \, dt + U_A(t_0)$$

$$U_A(t_1) = -\frac{1}{5 \, \text{ms}} \cdot \int_{10 \, \text{ms}}^{20 \, \text{ms}} (-1 \, \text{V}) \, dt + 0 \, \text{V} = 0 \, \text{V}$$

\$I.\quad\$ Am Punkt \$t_3\$

$$U_A(t_1) = -\frac{1}{\tau} \cdot \int_{t_0}^{t_1} U_E \, dt + U_A(t_0)$$

$$U_A(t_1) = -\frac{1}{5 \, \text{ms}} \cdot \int_{10 \, \text{ms}}^{20 \, \text{ms}} (-2 \, \text{V}) \, dt + 0 \, \text{V} = -2 \, \text{V}$$

From:
<https://wiki.mexle.te.hs-heilbronn.de/> - MEXLE Wiki

Permanent link:
https://wiki.mexle.te.hs-heilbronn.de/elektronische_schaltungstechnik/rechnung_signalzeitverlauf_umkehrintegrator?rev=1590079917

Last update: 2021/05/09 09:53

