

task_1m3izw2szosswtto_with_calculation

Student Group

First Name	Surname	Matrikel Nr.

Table of Contents

Exercise E5 Analyzing a Scope Plot (written test, approx. 12 % of a 60-minute written test,
SS2023)

2

exam ee1 SS2023


Exercise E5 Analyzing a Scope Plot**(written test, approx. 12 % of a 60-minute written test, SS2023)**

On which scale does the RMS value of the periodic signals lie? (in radians and degree)?

Result The measured current curve shall be visible as a dashed line.

The continuous line shows the voltage.

Solution



Use the correct symbols and units in your answers!

1. Calculate the frequency f of the periodic signals.

Solution

Frequency f is given by the period T . The period can be measured in the image of the scope.

1. The sine waves repeat after 6 divisions (e.g. from falling turning point to falling turning point of one curve)
2. The scale is 0.1 ms/Div

$$f = \frac{1}{T} \quad T = 6 \text{ Div} \cdot 0.1 \text{ ms/Div} \quad \rightarrow f = \frac{1}{6 \text{ Div} \cdot 0.1 \text{ ms/Div}}$$

From:

<https://wiki.mexle.te.hs-heilbronn.de/> - **MEXLE Wiki**

Permanent link:

https://wiki.mexle.te.hs-heilbronn.de/electrical_engineering_and_electronics/task_1m3izw2szosswtto_with_calculation

Last update: **2023/12/06 13:03**

