

task_w3m7fo4hjahlkzogl_with_calculatlon

Student Group

First Name	Surname	Matrikel Nr.

Table of Contents

Exercise E1 Toroidal Coil (written test, approx. 5 % of a 120-minute written test, SS2021)

..... 2

magnetostatic, flux density, coil, toroid, exam ee2 SS2021

Exercise E1 Toroidal Coil

(written test, approx. 5 % of a 120-minute written test, SS2021)

A magnetic field with a flux density of at least 50 mT is to be achieved in a ring-shaped coil (toroidal coil).

The coil has 60 turns, wound around soft iron with $\mu_{\text{r}} = 1200$.

The average field line length in the coil should be $l = 12 \text{ cm}$.

Result:
 $I = 0.66 \text{ A}$
 $B = 4 \pi \cdot 10^{-7} \cdot \mu_{\text{r}} \cdot N \cdot I$

What is the minimum current that must flow through a single winding?

Path

The magnetic field strength of a toroidal coil is given as:

$$H = \frac{N \cdot I}{l}$$

Based on the flux density the magnetic field strength can be derived by $B = \mu_0 \mu_r H$.

By this, the formula can be rearranged:

$$H = \frac{N \cdot I}{l} \quad || \quad \frac{B}{\mu_0 \mu_r} = H \\ \frac{N \cdot I}{l} = \frac{B}{\mu_0 \mu_r} \quad || \quad I = \frac{B \cdot l}{\mu_0 \mu_r \cdot N}$$

$$\text{Putting in the numbers: } I = \frac{0.05 \text{ T} \cdot 0.12 \text{ m}}{4\pi \cdot 10^{-7} \frac{\text{Vs}}{\text{Am}} \cdot 1'200 \cdot 60} = 0.6631... \frac{\text{T} \cdot \text{m}}{\frac{\text{Vs}}{\text{Am}}} = 0.6631... \frac{\text{Vs}}{\text{m}^2} \cdot \text{m} \cdot \frac{\text{m}}{\frac{\text{Vs}}{\text{Am}}} = 0.6631... \text{ A}$$

From:

<https://wiki.mexle.te.hs-heilbronn.de/> - MEXLE Wiki

Permanent link:

https://wiki.mexle.te.hs-heilbronn.de/ee2/task_w3m7fo4hjahkzogw_with_calculation

Last update: **2024/07/03 08:23**

